

amateur radio

JOURNAL OF THE WIRELESS INSTITUTE OF AUSTRALIA



VOL. 46, No. 5

MAY 1978

CONTENTS

TECHNICAL

- A Direct Reading Inductance and Capacitance Meter 12
- Afterthoughts 6
- How to Make Your VFO as Solid as a Rock 10

GENERAL

- A Call to Help the Citizens Radio Service 18
- A Visit to China 17
- John Moyle Memorial National Field Day Contest Results — 1978 40
- Mobilising Around Australia 19
- RAOTC Dinner 1978 26
- The Man Behind the Microphone 26

DEPARTMENTS

- Amateur Satellites 29
- Around the Trade 35
- Awards Column 41
- Contests 35
- Hamads 42
- IARU News 41
- Intruder Watch 41
- Ionospheric Predictions 26
- Letters to the Editor 36
- Magazine Index 35
- QSP 3, 6, 14, 21, 26, 40
- Silent Keys 42
- VHF-UHF — an expanding world 27
- WIANEWS 5
- 20 Years Ago 41

COVER PHOTO

Jim Davis VK7NOW at the controls of his impressive Novice station. Further details on page 26.

Photo by Phillip Payne of "The Advocate", Burnie.

HAM

RADIO SUPPLIERS

323 ELIZABETH STREET, MELBOURNE, VIC., 3000

Phones: 67-7329, 67-4286

Our Disposals Store at 104 HIGHETT ST., RICHMOND (Phone 42-8136) is open Mondays to Fridays, 9.00 a.m. to 5.00 p.m., and on Saturdays to midday.

WALKIE TALKIE SPECIFICATIONS:

TRANSMITTER — Frequency: in 27 MC citizen band, 27240. Final input power: 100 mW (max.). Communication Mod.: (AM) balanced mod. Oscillator: Crystal controlled. Antenna: Vertical type, telescopic antenna, 37" fully extended.

RECEIVER: Receiving System: Crystal controlled superheterodyne system. Sensitivity: S/N 10 dB or better at 10 uV 5 mW output. Selectivity: Thermistor: D-325. Power Supply: 0069 9V. Dimensions: H — 17.6 cm, W — 6.5 cm, D — 4.4 cm. Weight: 500g. PMG approved.

PRICE \$58.90 PAIR
Postage \$2.40

POWER-SWR METER

This is an in-line and SWR meter for ham radio and CB radio. This power meter indicates the output power of your transmitter and SWR meter reads the ratio of travelling power to your antenna and reflected back from antenna. Compact and inclined front design meet any radio operation desk.

SPECIFICATIONS — Range measured: Power meter 0-10, 100 watts, 2 ranges VSWR 1:1 — 1:3. Freq. response: 3-150 MHz. Impedance: 50 ohm. Dimensions: 70 x 96 x 100 mm. Weight: 900g.

PRICE \$38.90
Postage \$2.40

PL-259 Plug W/Reducer \$1.50
PL-259 Plug W/O Reducer \$1.80 (Adaptors 85c)
SO-239 Chassis Socket \$1.50
Right-Angle Joiner \$2.75
"T" Connection \$3.50
PL-259 to R.C.A. Adaptor \$2.75
Coax Joiner, female to female, male to male \$2.75

BNC Plugs \$1.95
BNC Sockets \$1.75
Belling Lee Plugs 75c
Belling Lee Sockets 50c
Belling Lee Joiner 85c
100 Meters Roll Hook-Up Wire \$4.50
All above items plus postage

YAESU FRG-7

THE RADIO FOR WORLD-WIDE LISTENING
AT ITS BEST — 0.5-29.9 MHz COVERAGE
SYNTHESIZED COMMUNICATION RECEIVER



The model FRG-7 is a precision built high performance communication receiver designed to cover the band from 0.5-29.9 MHz. Its state of the art technology offers an unprecedented level of versatility. The Wadley Loop System (drift cancellation circuit) coupled with a triple conversion super heterodyne system guarantees an extremely high sensitivity and excellent stability. It provides complete satisfaction to amateurs as well as BCLs with superb performance and many features such as RF attenuator, selectable tone, and automatic noise suppression circuit.

\$338

BULK STORE DISPOSALS

AT 104 HIGHETT STREET
RICHMOND, 3121
Phone (03) 42-8136

NEW AWA-THORN TV TUNERS

Type ENR5758, fitted with 6GK5 and 6G57 valves.

\$2 each plus P&P

NEW MAGNAVOX 53TS SPEAKERS

5" x 3" 8ohm, ideal for small extension speaker for communication equipment.

\$1.95 each plus P&P

CRYSTALS FOR CITIZENS RADIO

Channel No.	Freq. MHz	Channel No.	Freq. MHz
1	27.015	11	27.135
2	27.025	12	27.155
3	27.035	13	27.165
4	27.055	14	27.175
5	27.065	15	27.185
6	27.085	16	27.195
7	27.095	17	27.205
8	27.105	18	27.225
9	27.115	19	27.280
10	27.125	20	27.240

\$7.50 PAIR — Postage 25c

CRYSTALS MADE TO ORDER

\$9.50 — Postage 25c

HANSEN SWR6 POWER METER & FIELD STRENGTH INDICATOR

Handy for checking transmitter operation. Use bridge method for SWR measurements. Simple and accurate operation. CM method employed for RF power measurement.

PRICE \$22.00
Postage \$1.80

100 METRE ROLLS SPEAKER WIRE

\$11.90 per roll — Post free

2 STN INTERCOM and battery 9V \$12.90
3 STN INTERCOM and battery 9V \$18.90 ea.
4 STN INTERCOM and battery 9V \$26.90 ea.

Complete with 60 ft. wire, ideal for garage, baby room, etc. — **Postage \$1.50**

ARLEC PLUG-PACK

PLUG-IN POWER SUPPLY

Plugs directly into 240 volt mains supply power sockets and provides 12 volt 1 amp smoothed DC for powering low voltage and battery operated equipment — Transceivers, cassette recorders, cartridge players, burglar alarms, electric models and toys, car radios, etc. 12 Volt 1 amp SEC approved, double insulated, overvoltage protected.

PRICE \$16.90
Postage \$1.80

We also have a large range of **ELECTRONIC DISPOSALS** equipment, including TRANSFORMERS, CABLE, TEST EQUIPMENT, TRANSMITTERS, etc.

You are invited to call in and inspect. **NO PARKING PROBLEMS** AT 104 HIGHETT STREET RICHMOND. Phone 42 8136.

WE STOCK CB GEAR AS WELL AT VERY COMPETITIVE PRICES, INCLUDING ANTENNAS AND ACCESSORIES.

KEMTRONIC SSB1000

SSB/AM TRANSCEIVER

27 MHz CITIZENS RADIO SERVICE
The SSB 1000 embodies the latest in high frequency transceiver design techniques. It is designed to operate on either AM, USB or LSB. It is capable of transmitting and receiving on a total of 54 channels (18 AM, 18 USB, 18 LSB). The 18 channels are in accordance with the P&T Dept conditions for operation of the Citizens Radio Service.

NETT PRICE \$220.00
Registered Post — \$4.00

TRADIPER MODEL TE-15

The Model TE-15 Transistorised Grid Dip Meter is a very accurate instrument operating from a 9 volt battery power supply. Six plug-in coils are supplied with each unit, covering the frequency range of 360 kHz to 240 MHz. The Model TE-15 can be used for a number of useful purposes. With the most common use as a Grid Dip Meter, can also be employed as a relative field strength meter. It is ruggedly constructed and very light in weight. Because of transistorised circuit employed there is no need for an AC power supply as used in many other models. The Model TE-15 will certainly prove invaluable to radio amateurs.

PRICE \$65.00
Postage \$2.40

ARLEC PLUG-IN BATTERY CHARGER

Delivers 1 amp output at 12 volts. Designed to run continuously over long periods, will maintain a fully charged battery in peak condition or recharge flat battery. Double insulated for max. safety. electrically protected by fully automatic circuit breaker. No mains leads to get tangled, plugs directly into power socket. Comes with 3 metre battery leads fitted with clips. For use on 240V, 50 Hz supply.

PRICE \$14.90
Postage \$1.80

SPECIAL

8" x 6" SPEAKERS — brand new in cartons — 4 ohm impedance — ideal for car cassettes, radios, etc.

PRICE \$4.00 EACH — Postage \$1.00
10 FOR \$3.00 — BULK BUY

MAIL ORDERS WELCOMED. Please allow pack and post on items listed on this page. If further information required send a stamped SAE for immediate reply from the above address. Larger items can be sent F.O.B. Due to circumstances beyond our control, prices quoted in this advertisement are subject to alteration without notice.



amateur radio

Published monthly as its official journal by the Wireless Institute of Australia, founded 1910.

MAY 1978

Vol. 46, No. 5

PRICE: 90 CENTS

(Sent free and post paid to all members)

Registered Office:

2/517 Toorak Road,
Toorak, Victoria, 3142.

Registered at the G.P.O. Melbourne for trans-
mission by Post as a Periodical — Cate-
gory "B".

EDITOR:

BRUCE BATHOLDS* VK3JUV

ASSISTANT EDITORS:

RON COOK* VK3JFW

GIL SONES* VK3AUI

TECHNICAL EDITORS:

BILL RICE* VK3ABP

KEN PALISER VK3GJ

CONTRIBUTING EDITORS:

BOB ARNOLD VK3ZBB

BRIAN AUSTIN VK5CA

ROD CHAMPNESS VK3UG

SYD CLARK* VK3ASC

RON FISHER* VK3CM

DAVID HULL VK3ZDH

ERIC JAMESON VK5LP

KEN JEWELL VK3AKK

PETER MILL VK3ZPP

KEVIN PHILLIPS VK3AUQ

LEN POYNTER* VK3ZGP

DRAFTING:

ALL DISTRICTS DRAFTING SERVICE

KEN GILLESPIE* VK3GK

PHOTOGRAPHER:

REG GOUDGE —

BUSINESS MANAGER:

PETER CORD VK3CIF

ADVERTISING:

PETER SIMMONS

*Member of Publications Committee

Enquiries and material to:

The Editor,
PO Box 2611W, GPO Melb., 3001

Copy is required by the third of each month. Acknowledgement may not be made unless specially requested. All important items should be sent by certified mail. The editor reserves the right to edit all material, including Letters to the Editor and Hamads, and reserves the right to refuse acceptance of any material, without specifying a reason.

Advertising: Material should be sent direct to P.O. Box 150, Toorak, Vic., 3142, by the 25th of the second month preceding publication. Phone: (03) 24 8652.—Hamads should be sent direct to P.O. Box 150, Toorak, Vic., 3142, by the 3rd of the month preceding publication.

Trade Practices Act: It is impossible for us to ensure that advertisements submitted for publication comply with the Trade Practices Act 1974. Therefore advertisers and advertising agents will appreciate the absolute need for themselves to ensure that the provisions of the Act are complied with strictly. Readers are reminded that, when buying, obtaining or receiving goods from overseas importers or organisations in this journal, Customs import duties and Sales Tax may be levied on the goods at the time of importation. These amounts, if any, are payable by the purchaser unless the terms of sale state otherwise and the seller has made specific provision to this effect in his quotation to the buyer or unless other prior arrangements are in force between the buyer and the seller.

Printers: EQUITY PRESS PTY. LTD.

50-52 Islington Street, Collingwood, 3066

Tel.: 41-5054, 41-5055

QSP —

SPECIALIST ADVICE NEEDED

It is now some time since the three Regional Conferences of the IARU decided upon a common amateur radio position to be put forward to Administrations when considering WARC79.

Amateur radio societies throughout the world adopted the common position with details and a model paper drafted by the dedicated band of workers led by IARU President Noel Eaton VE3CJ. The work of this international group is a continuing process but the IARU as a whole and many member societies have become most anxiously aware that the preparations for WARC79 require specialised technical treatment.

To this end IARU has sought the very best advice obtainable throughout the world for the benefit of a great many countries unable to secure access to this kind of information. The IARU in this respect acts as a co-ordinating agency and members may be assured that no stones are being left unturned both at the national and international levels.

However, the recent meeting chaired by Noel Eaton VE3CJ recognised the need for specialist advice to be obtainable during the actual WARC itself at short notice on any unforeseeable questions.

Thus, any comments relating to WARC79 matters would be welcome in this context. Although tremendous thought has been put into considering every conceivable angle relating to technical matters, there always seems to be something not given the proper perspective in advance.

D. A. WARDLAW VK3ADW, Federal President.

WIRELESS INSTITUTE OF AUSTRALIA

Federal President: Dr. D. A. Wardlaw VK3ADW

Federal Council:

VK1 Brig. R. K. Roseblade VK1QJ

VK2 Mr. T. I. Mills VK2ZTM

VK3 Mr. J. Payne VK3AED

VK4 Mr. N. F. Wilson VK4NP

VK5 Mr. I. J. Hunt VK5OX

VK6 Mr. N. R. Penfold VK6NE

VK7 Mr. P. D. Frith VK7PF

Staff: Mr. P. B. Dodd VK3CIF, Secretary.

Part-time: Col. C. W. Perry, Mrs. J. M. Seddon and Mr. P. Simmons (AR advertising).

Executive Office: P.O. Box 150, Toorak, Vic., 3142.

2/517 Toorak Rd., Toorak, Ph. (03) 24 8652.

Divisional Information (all broadcasts are on Sun-
days unless otherwise stated):

ACT:

President — Mr. E. W. Howell VK1TH

Secretary — Mr. Ted Radcliffe VK1TR

Broadcasts: 3570 kHz & 145.5 MHz: 10.00Z.

NSW:

President — Mr. T. I. Mills VK2ZTM

Secretary — Mr. I. A. Mackenzie VK2ZIM

Broadcasts: 1825, 3595, 7145 kHz, 28.5, 62.1,
52.625, 144.1, Ch. 8 and other relay
stations: 01.00Z. (Also Sunday even-
ings 09.30Z and Hunter Branch,
Mondays 09.30Z on 3570 kHz and ch.
3 and 8).

VIC:

President — Mr. S. T. Clark VK3ASC

Secretary — Mr. J. A. Adcock VK3ACA

Broadcasts: 1825, 3600, 7135 kHz — also on 6m,
2m SSB and 2m Ch. 2 repeater: 00.30Z
(Also on Radio 3HA).

QLD:

President — Mr. A. J. Aarse VK4QA

Secretary — Mr. W. L. Gielis VK4ABG

Broadcasts: 1825, 3590, 7146, 14342 kHz: 09.00

EST:

SA:

President — Mr. C. J. Hurst VK5HI

Secretary — Mr. C. M. Pearson VK5PE

Broadcasts: 1820, 3550, 7125, 14175 kHz: 28.5

and 35.1 MHz, 2m (Ch. 8): 09.00

S.A.T.

WA:

President — Mr. R. Greenaway VK6DA

Secretary — Mr. N. R. Penfold VK6NE

Broadcasts: 3600, 7090, 14100, 14175 kHz, 52.650

and 2m (Ch. 2): 01.30Z.

TAS:

President — Mr. R. K. Emmett VK7KK

Secretary — Mr. H. E. Hewens VK7HE

Broadcasts: 3570, 7130 kHz: 09.30 EST.

NT:

Secretary — Mr. Henry Andersson VK6HA

Broadcasts: Relay of VK5WI on 3.55 MHz and on

146.5 MHz at 2330Z. Slow morse

transmission by VK6HA on 3.55 MHz

at 1000Z almost every day.

Postal information:

VK1 — P.O. Box 46, Canberra, 2600.

VK2 — 14 Atchison St., Grows Nest, 2065 (Ph. (02)

43 5795 Tues & Thurs (10.00-14.00h).

VK3 — 412 Brunswick St., Fitzroy, 3065 (Ph. (03)

41 3535 Sat 10.00-12.00h).

VK4 — G.P.O. Box 638, Brisbane, 4001.

VK5 — G.P.O. Box 1234, Adelaide, 5001 — HQ at

West Thebarton Rd., Thebarton (Ph. (08)

254 7442).

VK6 — G.P.O. Box N1002, Perth, 6001.

VK7 — P.O. Box 1010, Launceston, 7250.

VK8 — (incl. with VK5), Darwin AR Club, P.O. Box

1418, Darwin, 5794.

Slow morse transmissions — most week-day even-
ings about 09.30Z onwards around 3550 kHz.



De-Luxe HF transceiver

FT901DM, the ham's dream, a deluxe 160-10m Tcvt with a host of new unusual features placing it far ahead of other sets. P.A. 2x6146B, Dig. and analogue readout, Freq. memory, electronic keyer, AC/DC operation, RF speech processor, variable I.F. band width, special circuitry to reduce spurious and harmonic emissions, etc!

\$1575



FT-901DM

FT-101E TRANSCEIVER: 160-10 Mx, SSB, AM, CW, \$895

FT-301S 160-10mX, fully solid state Tcvt suitable for Novice use. 25W PEP max. \$789. Inc. VOX control, offset tuning, calibrator.

FT-301 160-10mX, Fully solid state Tcvt, built in RF Speech Processor, 200W PEP Input. \$1076.

FT-301D DELUXE DIGITAL Tcvt, Similar to FT-301, \$1269.

FP-301 MATCHING POWER SUPPLY, 20 Amp 12V suit all 301 Transceivers. \$189.

FP-301D DELUXE POWER SUPPLY, With built in 24 hr or 12 Hour Clock and auto — CW ident Keyer provision. \$299.

YO-301 MATCHING MONITORSCOPE for FT-301 Series. \$399.

FC-301 ANTENNA COUPLER, Inc. SWR & Pwr meters, ant. switch and connectors. \$235.

R-301 RELAY BOX for FT-301 to FL-2100B. \$25.00

FL-110 SOLID STATE LINEAR 200W PEP Input, 160-10mX, \$249.

FL-2100B LINEAR AMPLIFIER: 80-10mX, uses 2 x 572B \$578.

FRG-7 WADLEY LOOP RECEIVER: 0.5-29.9 MHz. \$348.00

*Power Supply Price applies only with purchase of matching transceiver.

FR-101D RECEIVER: All solid state, 23 bands incl. all amateur bands 160-10m plus 6 and 2m, FM, CW, etc., etc. \$1065.

FR-101D DIGITAL: Has all the options of the FR-101D \$1268.

FTV-650B SIX METRE TRANSVERTER: Converts 28 MHz. SSB to VHF, and includes receiving converter. 50W PEP. \$295.

FTV-250 TWO METRE TRANSVERTER: Similar FTV-650B. 10W-15W output, but all solid state and built-in AC PS. \$335.

FT-223 TWO METRE TRANSCEIVER: 10W, 23 Channels, plus one priority channel. Inc. 40, 50 & 51, \$149, (a few only.)

FT-227R 2mX, FM Tcvt, 800 Ch, with Dig. Readout, memory \$375

YO-100 MONITORSCOPE: Matches the FT-101E, \$299.

YP-150 DUMMY LOAD/POWER METER: For use over the frequency range 1.8-200MHz. Three power ranges, 0-5W, 0-30W, 0-150W with built-in cooling fan. \$108.

Servicing facilities for our Amateur and Novice equipment. We check all sets before sale and provide a 90 day warranty. All prices incl. S.T. Postage and freight extra. Add ins., 50¢ per \$100. Prices and specifications subject to change without notice. Availability depends on stock position at time of ordering.



ELECTRONIC SERVICES

60 Shannon St., Box Hill North, Vic., 3129. Phone 89 2213

Agents in all States and A.C.T.

FRED BAIL VK3YS

JIM BAIL VK3ABA

JAS7778-49

An Amateur Radio Community Service Announcement!

How to recognise the export quality set you should be getting for your money!

Are you concerned about warranty, after sales service, and spare parts availability for your purchase of amateur radio equipment? Would you pay for a transceiver and be happy to accept it without an English language instruction manual, made for operation only on 220V A.C. instead of the more usual Australian line voltage of 230-240V (250V in W.A.), equipped with a non-Australian standard (illegal) two core A.C. power cable, possibly less some features that may be considered normal or necessary by a conscientious factory authorised importer?

O.K., we believe we know the answers to these questions, but how can you identify the equipment?

First of all, check that your chosen dealer is a factory authorised agent or that he is an agent approved distributor. Is he prepared to spend a reasonable amount of time showing you the set, providing a genuine warranty, etc. or does he push a sealed carton under your nose with the suggestion that, e.g., "You are getting it cheap enough what more do you expect?"

Do ensure that your purchase of an A.C. operated transceiver is fitted with an Australian approved 3 core A.C. power cable and 3 pin plug. Look for the official approval numbers stamped on the cable and plug. Does it include an English language instruction manual? Amateur transceivers produced by the Yaesu Musen Co. Ltd. of Japan

for authorised sale in Australia include the characteristic export blue and white covered English language manual, usually printed on glossy paper — not a black and white covered manual or a photo copy.

Check that the equipment is fitted with a 234V primary power transformer and carries the Yaesu factory 234V sticker, and that the serial number has not been removed or obliterated. As an example an authorised dealer imported FT-101E should include speech processor, cooling fan, crystals for all amateur bands 160M-10M with full coverage on all ranges, microphone, A.C. and D.C. power cables, accessory connectors, etc.

An FT-301S should have crystals installed for 80M-10M (28.5-29 MHz on 10M), reject control, connectors, microphone, VOX, crystal marker calibrator, etc.

In other words make sure that the set that you are purchasing is an Australian Standard export quality set and not an unauthorised imported ("bootlegged") job!

This space was donated in the interests of better amateur radio by Bail Electronic Services of Box Hill North, Melbourne, Australian Yaesu agent since 1963.

WIANEWS

REGULATIONS

A further letter from the Postal and Telecommunications Department arrived in March.

This was RB4/4/18 received on the 15th. This is the text —

Reference is made to your letter of 8 August 1977 concerning matters relating to the operation of the Amateur Service and in particular a request for permission for novice amateur licensees to use Variable Frequency Oscillator control.

The Department in investigating this matter agrees with the proposal and therefore is pleased to advise that, effective forthwith, novice amateur stations may employ transmitter Variable Frequency Oscillator control.

This approval is on the understanding that the licensee of the novice amateur station shall take all steps necessary to ensure that emissions from his station are within the limits of the amateur frequency band authorised for novice station transmissions.

Would you please give this matter publicity through the avenues available to the Institute. Offices of this Department have been notified accordingly.

NOVICE EXAMINATION

WIANEWS in April AR reported a meeting with Departmental officers during February. A further meeting with them was attended on 16th March during which the Department presented the WIA with a new draft syllabus for the Novice exams under cover of letter RB4/4/4 of that date. This draft went some way towards meeting the Federal Education Co-ordinator's objections that the first draft received in February lacked depth.

Unfortunately the new draft introduced a number of subjects which did not appear in the February draft. Further negotiations ensued with the result that some of these new subjects were deleted but the Department insisted upon the retention of several others. When these further negotiations concluded on 21st March, the Federal Education Co-ordinator, Graeme Scott VK3ZR, and his assistants sat down and revised the carefully prepared WIA syllabus to conform with the "final" draft of the Departmental syllabus. The WIA syllabus then became a study guide to give some indication to instructors of the depth of teaching to be given to candidates bearing in mind that Novice theory deals in an elementary manner with the subjects concerned.

This study guide has been submitted to the Department for endorsement as suitable for Novice level candidates and will be published as soon as possible thereafter.

However, a problem still appears to remain concerning the Novice theory question bank. One batch of nearly 200 questions (without answers) prepared by Graeme Scott, assisted by John Kolm VK3YJK, Brenda Edmonds VK3KT, and Danny McManus VK3NG, were handed over to the Department at the meeting on 16th March. Another similar batch is under preparation. The questions were culled from many sources and were carefully scrutinised before being considered suitable for submission. The reactions of the Department are awaited.

Meantime letter 7/3/78 of 17th March arrived from the Department confirming the points discussed with them at the meetings on 23rd February and 16th March. This letter confirmed that the WIA syllabus would serve admirably as a study guide and would be endorsed for that purpose. It also confirmed that the WIA Novice exam questions would be used for inclusion in the bank of Departmental questions for setting Novice exams. Once this bank has been established there seemed no reason why they should not be published by the WIA to assist students, stated the letter.

Thirdly the letter stated: "a joint WIA/Department committee will be established to discuss the activities and administration of the Amateur Radio Service in order to resolve any difference of opinion which may arise from time to time". The suggestion was made that the committee should meet at an early date to examine

SCALAR

for Antennae



Illustrated is a BASE STATION ANTENNA
Omnidirectional Gain 3 dB and 6 dB
Models G11, G21, G22.

Scalar's range of HIGH GAIN base station antennas provide an omnidirectional radiation pattern combined with gains of 3 dB and 6 dB depending on Model number. They are designed as base station antennas for two-way radio systems. Constructed of high grade aluminium, the radiating elements are completely enclosed within a fibreglass radome.

C.B. CITIZEN BAND AND PAGING ANTENNAS
MARINE AND MOBILE H.F.
TUNEABLE GROUNDPLANE ANTENNAS
SIDE MOUNT DIPOLES
COAXIAL DIPOLES
HIGH GAIN ANTENNAS
DISCONE ANTENNAS
FIXED FREQUENCY GROUNDPLANE ANTENNAS —
MOBILE COAXIAL DIPOLES
UNITY GAIN — (FIBREGLASS) WHIPS
4.5 dB GAIN (FIBREGLASS) WHIPS
PHASED SIDE MOUNT DIPOLES
VHF-UHF DIRECTIONAL ANTENNAS YAGI
MAGNABASE — MAGNETIC BASE
HELICAL WHIPS — 6ft, 8ft, 12ft, 15ft.
PAGING ANTENNA H.F. BALUNS
ANTENNA MOUNTING HARDWARE
ACCESSORIES
FILTERS AND DIPLEXERS PORTABLE WHIPS
H.F. MOBILE WHIPS — 6ft, 8ft, 12ft, 15ft.
FLEXIBLE, MOBILE WHIPS



SCALAR
Industries Pty Ltd
Communication Antennae Engineers

VICTORIA: 18 Shelley Ave., Kilsyth, Vic., 3137. Ph: 725-9677
Cables: WELKIN, MELBOURNE. Telex: AA34341.

Qld.: 969 Ann Street, Fortitude Valley 4006
Telephone (07) 52 2594. Telex AA 43007 WELKI.

the issues raised in the submission to the Department of 8th August 1977 (published in AR September 1977).

1978 CONVENTION AGENDA ITEMS

Since this issue of AR will reach members after the Convention there is little point in quoting the Agenda Items received too late for inclusion in April AR. Nevertheless members might be interested in the general tenor of these items. VK1 Division submitted two items seeking discussion on enlarging the frequencies available for Novices. VK3 Division submitted 7 items dealing with —

Contributions for WARC79 from non-members; handling of QSL cards for non-members; common band segment for all grades of licensee; morse speed endorsements; Novice conditions; four tier licensing structure; RD contest SSB segment.

VK5 Division submitted 14 items on —

ATV calling channel on 2m; CB relations; Novices on WICEN frequencies; removal of log book requirement; engaging public relations firm; 10m beacons.

VK2 Division submitted 14 items —

25 kHz spacings on 2m; designation of numbers for 2m repeaters; review of 70cm band plan; 2m ATV liaison frequency; 70cm upper segment ATV frequency; common band for all licensees; 6m band repeaters; 10m band repeaters; band 4 TV segment; discuss Novice conditions; multimode stations one licence fee; compensation if bands lost; increased power for loss of 11m band.

This concludes the Agenda Items for this Convention. A considerable range of other matters will be discussed during the debates on the various Annual Reports, as well as latest reports about WARC79 preparations.

QSP

SATELLITE ELECTROSTATIC CHARGES

"Communications satellites are usually placed in a geostationary orbit some 35,400 km above the earth, where local conditions are greatly influenced by the ionosphere below and the magnetosphere above. Plasma gases (hydrogen, helium, oxygen) escaping from the magnetosphere bombard satellites in geostationary orbit with electrically charged particles, sometimes causing a static electricity build up of dangerous proportions. The static electricity can then cause arcing on the satellites' surface that in turn can damage solar power cells and thermal insulation; and can generate interference with transmission of signals, resulting in garbled information and spurious switching of spacecraft functions." Continuing this article in December 1977 Telecommunication Journal news is given of the intention by the USAF to launch a satellite in January 1979 to study such effects.

CANADIAN CB

December 1977 Telecommunication Journal quotes a Canadian Department of Communications release that more than 600,000 Canadians hold licences for the General Radio Service Citizens' Band (CB) radios. This is over twice as many as one year ago and GRS operators now outnumber all other classes of Canadian radio users combined.

ARRL THREATENED WITH \$50 MILLION LAW SUIT
The ARRL has been threatened with a law suit claiming damages of \$50 million. This has been due to the ARRL adopting an advertising policy known as the ARRL Code of Ethics.

This policy would involve refusing advertisements in QST from traders who sell amateur gear to non-amateurs.

A group known as the Communications Attorney Service has threatened the law suit as they claim the policy contravenes US trade laws.

This confrontation could mean heavy liabilities for the ARRL and echoes the recent reply published in AR in response to a letter protesting the sale of Amateur Linear Amplifiers in CB publications. From Jan. 1978 QQ.

OFFICIAL INTEREST

The photograph indicates the amount of interest QSL (Canada) have in communicating with the Amateur fraternity.

Both FCC and DCC make extensive efforts to have their field officers attend ham and CB con-



ventions to facilitate good communications with the users.

Perhaps the Australian authorities could take a leaf out of their book!

Photograph supplied by Vicom International Pty. Limited.

AMATEURS AND CB

"The radio hobbyist should be given a friendly hand into amateur radio before he or she gets caught up in the ideas of modifying their CB, building beams, adding liners and using any frequency one desires (piracy). Such a state of affairs does not benefit either service. Within CB the first step is to know that a hobby called amateur radio exists, the second is to offer an opportunity to get involved in the hobby, and the third step is to become sufficiently enthusiastic so as to personally commit oneself to studying for the amateur licence. As the CB user becomes interested in radio as a hobby the VKCB club members are able to direct the energies of such enthusiasts in the right direction." Report of activities of the Amateur and Citizen Radio (VKCB) Club, August 1977 to February 1978.

OT's MEET AGAIN

On 14th March 1978, a CW QSO between VK2BWC and VK3TJ revealed that these two had met in Hong Kong on February 2, 1978 and had not seen or heard of each other since that date.

QSL 388DA

All stations wishing to QSL 388DA and 387DA are requested to forward SAE and IRC to: Alex Mootoo, 388DA, 39 Brown Squard Ave., Vacca, Mauritius.

MEDIA PUBLICITY

At the end of March much time and effort were expended in preparations for a 25 minute programme on amateur radio for showing on the HSV7 network's "This week has seven days" on dates later in April. Many amateurs were involved under the chairmanship of Peter Wollenden VK3ZPA, Executive Vice-Chairman. It is hoped to obtain a videotape of this show to add to the Executive's small library of videotapes available for loan to Divisions and clubs. These include the ARRL publicity films in colour, and the "Aerial Circus" videotape which is currently being edited and improved.

POSTAL MOTION AND EDP

A postal motion circulated to Divisions, seeking covering approval of the expenditure of funds to convert the WIA programmes to the 6700 computer, was passed. The Executive was also examining the costs of an in-house computer but it is expected these will still be too great for WIA requirements.

PUBLICATIONS COMMITTEE

One matter exercising the minds of Committee members is the dearth of material in AR suitable for Novices and SWLs. The reason is simple. AR is your journal. It cannot exist without articles and contributions by members. If there is very little suitable for Novices and SWLs it is because no one is contributing useful publishable material for them.

HANDBOOK REVISION AND CUSTOMS

At the Executive meeting on 23rd March Jim Lloyd VK3CDR/1 agreed to undertake the task of handling this revision. Bill Colborne VK3BP agreed to undertake an investigation into and give a report on the problems of Customs duties on amateur arials and 70cm transmitting equipment.

VK1 REPEATER STOLEN

A message from the President of the WIA ACT Division advises that the ACT Division's channel 7 repeater installation at Mt. Ginihi was stolen on the night of 1st/2nd April. This was a home brew rig and members are asked to keep an eye and ear open respecting anything unusual concerning such a rig. Please advise WIA ACT Division, Box 46, Canberra, 2600, on any information.

NSW DIVISION MORSE TAPES

A message from the NSW Division is that the morse tape loan service has been discontinued. This service has been replaced by the sale of pre-recorded 600 cassettes with any speed 5 to 12 w.p.m. Send stamped, self-addressed envelope with \$2 per cassette, stating morse speed required, to WIA NSW Division, 14 Atchison Street, Crows Nest, NSW 2065. Price is post paid.

RTTY CONTEST

Are you making preparations to participate in the RTTY Section of the VK/ZL/O DX contest on the 7th/8th October. This RTTY contest will be administered on behalf of the Executive by the New South Wales RTTY group. The rules will be published shortly.

AFTERTHOUGHTS

An error occurred in the circuit (Fig. 2) of "Modifications To The Yaesu FT-100B", page 10, March '78 AR. The two capacitors in series between the collector and base of the BC208 transistor are shown as 0.002 uF. The correct value for each capacitor is 0.022 uF.

A SOLID STATE VIDEO MODULATION SYSTEM

AR, JULY 1977, page 6

The 6.8k bias resistor, Fig. 2, should be returned to the collector of the MPS6514 transistor and not to the +12 volt rail as shown.



YAESU from DICK SMITH

WHEN YOU REALLY CONSIDER THE ALTERNATIVES - THERE ARE NONE!



COMPUTER TECHNOLOGY COMES TO VHF COMMUNICATIONS

AS REVIEWED IN
MARCH E.A.



FABULOUS YAESU FT227R
2m FM
MOBILE **\$335**

WHAT ARE THE FREQUENCY SPLITS FOR REPEATERS?
Don't worry! Yaesu has computerised it. In addition to a conventional $\pm 600\text{kHz}$ split, any transmitter offset frequency is memorised with the touch of a button.

WHAT WAS MY LAST FREQUENCY?

Don't check - a touch of a button will bring you back to the memorised channel instantly.

WHY ONE KNOB TO SELECT A CHANNEL OUT OF 800?
Yaesu utilises an 'OPTICAL COUPLING' system to select each channel in 10kHz steps and the channel may be offset 5kHz higher with the touch of a button. Thus 800 fully synthesised channels are provided with one knob and no rotary switches to get oxidised or noisy.

WHAT ARE THE OTHER FEATURES OF THE 227R?

Many. Just to name a few - tone burst accessed repeater operation; automatic final protection; busy channel indicator; high and low power output selection... we could go on & on.

WHY SETTLE FOR ANYTHING LESS THAN THE 227R?

The fabulous FT-227R. Yours for the low, low Dick Smith price of only \$335.00. Cat. D-2890

GREAT CIRCLE WORLD MAPS: Ideal for the shack - based on Australian east coast. Mount under the rotator pointer for true bearings.
Cat B-4502

...\$3.00
CLUBS - Apply on your club letterhead and we'll send you a copy of the world map FREE! (Limit one per club)
Cat D-7080

...\$19.50
WORLD CALLSIGN MAP: Shows prefix on each country plus capitals and major cities, also DX zones. Cat B-2264

...\$27.50
SHINWA TVI FILTER: We don't have to tell you how good the Shinwa is! 1dB insertion loss, 30MHz cut-off, max. attn from app. 50MHz.
Cat K-3132

...\$34.95
2m 45W AMPLIFIER KIT: 8-12W of drive for 35-45W of output. F'glass pcb, instructions inc.
Cat K-3133

...\$34.95
80m 30W AMPLIFIER KIT: Ideal for novice! F'glass pcb, 13.8V required. Full instructions.
Cat K-3133

...\$34.95
AIR-WOUND COILS: Make your own antenna tuning units and high power linears. Separately boxed coils with full data.
Cat D-7050 (20mm)

...\$4.70
Cat D-7052 (40mm)

...\$5.50
Cat D-7054 (40mm)

...\$6.60
Cat D-7056 (60mm)

...\$7.90
OSKER BLOCK: The SWR & power meter for the amateur operator. Through-line type metering. 2kW rating.
Cat O-1340

...\$67.50
G6-144 2M COLINEAR: 117" high for repeater or fixed operation. 1kW rating, low SWR. 6dB gain over 1/2 wave dipole.
Cat D-4200

...\$89.00
WORLD ATLAS: A favourite with all DXers contains 20 pages of world maps, 4 colour.
Cat B-2268

...\$3.90
CO-AX SWITCHES: Will handle 1kW at 150 MHz. Save \$4.00 while stocks last.
Cat D-5204

...\$17.50
LOW POWER TYPE: Handles 150W at 30MHz (although we've used them at 144MHz). 3 positions. Cat D-5206

...\$11.75
RG58RU CO-AX: Quality black co-ax at a bargain price - 30 cents per metre for 100 metres or more. 52 ohm, light duty.
Cat W-2090

...\$1.35/m - 100m +
UR67 CO-AX (RG8U): Low loss, ideal for feeder systems. Maximum signal transfer.
Cat W-2095

...\$1.35/m - 100m +
PRE-AMPLIFIERS: For 27MHz, 52MHz & 144MHz. Mount in aerial circuit, fully tested units. Big savings NOW!
27MHz (ERB27) Cat D-3827

...\$25.90
52MHz (ERB6) Cat D-3806

...\$25.90
144MHz (ERB2) Cat D-3802

...\$25.90
These were selling for up to \$39.00 each!
BUILD A BEAM: Our antenna brackets make it easy. Insulating nylon bracket accepts 10mm elements, up to 17mm boom.
Cat D-4650

...\$5c ea
Cadmium plated brackets for larger beams - 17mm elements and 20mm booms.
Cat D-4652

...\$1.00 ea
VHF TRIMMER CAPACITORS: Compression type, 1001 uses. 3 capacitance ranges:
1.5 - 20pF Cat R-2900

...70c
7 - 60pF Cat R-2905

...\$1.30
15 - 115pF Cat R-2910

...\$1.75
VHF CONVERTERS: For 6 & 2 metres, output on 28-30MHz. 9-12V DC 9-15mA. Supplied complete with circuit. Save \$6.00 on each!
6 metre (EXC 6) Cat D-3836

...\$29.50
2 metre (EXC 2) Cat D-3832

...\$29.50
(Both these converters were selling for \$35.50!)

RAK BLSOA BALUN: T shape, ideal for use as centre support for dipoles or yags. 1kW rating.
Cat D-5310

...\$21.50
A-580N ANTENNA: Deluxe multiband transmitting/receiving antenna. 80 thru 10m, full 2kW rating. Complete.
Cat D-4705

...\$51

...\$39.50
CG-144 2M ANTENNA: 5.4dB gain over 1/4 wave mobile, suitable for any ball mount (not included). 200 watts rating. 85" high.
Cat D-4192

...\$49.50

...\$29.50
48TV VERTICAL: Four band trap vertical covers 40, 20, 15 & 10. Optional 80m resonator - 2kW rating, low SWR. Strong!
Cat D-4150

...\$115.00
Optional 80 metre resonator for the 48TV vertical: Cat D-4156

...\$29.50
MOBILE ANTENNA BASE: Quality base designed for any antenna using the standard 3/8 24TPI thread. Through-roof mount (5/8" hole required) Cat D-4056

...\$4.50
VHF WHIP ANTENNA: Suitable for 70 to 500 MHz depending on cut. Stainless steel & chrome, use with above base. Cat D-4015

...\$5.00
BALUN KITS: Contains a quality ferrite ring with enamelled copper wire and winding details for baluns from 1:1 to 1:9 ratio. Save \$3.50 - was \$12.50! Cat D-5350

...\$9.00

DID YOU GET YOURS?

THE 1978 DICK SMITH SUPER-CATALOGUE WAS IN ELECTRONICS AUSTRALIA LAST MONTH.

If you missed out, copies are still available from your nearest Dick Smith store or dealer for only 75c.

Also available through the mail order department - P.O. Box 747, Crows Nest, NSW, 2065.



Sideband Electronics Sales

DISTRIBUTORS OF COMMUNICATION

TRANSCEIVERS

NEW! SKY-BAND MOBILE ANTENNAS

THIS NEWLY DESIGNED UNIQUE MOBILE ANTENNA HELICALLY WOUND EXTRA HEAVY DUTY. SIX FEET LONG, AND CAN HANDLE UP TO 400 WATTS P.E.P.

FEATURES:

Light weight.
S.W.R. better than 1: 1.05 at resonance
Covered with highest grade fireproof insulation
Chrome base with 3/8 24 tpi. thread
Available in colours, grey, white, blue, green
burnt orange, brown and black.

AVAILABLE:

SKY. 80M 3.5 Special Novice
3.65
SKY. 40M 7.06
SKY. 20 14.150
SKY. 15 21.100 and up.
SKY. 10 28.5 and up.

PRICE LIST:

SKY 80 6 feet long 3.5 MHz \$28
SKY 40 6 feet long 7.060 \$26
SKY 20 6 feet long 14.150 \$26
SKY 15 6 feet long 21.100 \$25
SKY 10 6 feet long 28.500 \$24
Swivel mounts and chrome
plated springs for all \$13

All Sky-Band Antennas are carefully designed and have been individually tested. High quality fibreglass rod, wound with optimum thickness of wire to keep weight down, but maintain High Q. An elegant design to those who only want the best. All antennas are factory tuned for the lowest portion of the desired band and can simply be trimmed for your chosen frequency. Yes it is all Australian made! You don't pay for large overheads, instead we use the best material available and offer a mobile antenna which will resonate to our frequencies, unlike the previous overseas designed antennas.

ORDER NOW AND SPECIFY THE COLOUR YOU REQUIRE

New designs on the way similar to the famous 'Band Spanner' from 80-10 metres, tunable centre loaded, to be released soon.



SEND FOR A FREE CATALOGUE AND PRICE LIST



SALES & SERVICE 24 KURRI ST., LOFTUS. N.S.W. | OPEN SATURDAYS TILL
P.O. BOX 184, SUTHERLAND. 2232 | NOON. Phone: 521-7573

YAESU

The radio



Dentron MLA-2500

ANDREWS SYSTEMS

COMMUNICATIONS

for



YAESU
KENWOOD
DENTRON
WILSON, etc.

SYDNEY 349-5792

SHOP 7, GARDEN STREET,
MAROUBRA JUNCTION, SYDNEY
P.O. Box 33, Kensington, 2033

FINANCE AVAILABLE — BANKCARD HERE

Wilson's SYSTEM ONE

Sideband Electronics Sales

Distributors of COMMUNICATIONS TRANSCIVERS

STOP PRESS NEW! 2 M TRANSCIVERS TYPE I - \$789 ALL MODE TY #1 - \$385 25W OUTPUT FM 800 CHANNELS

HF TRANSCIVERS	
ASTRO - 200 digital solid state 200 W.P.E.P.	\$1,000
TRIO KENWOOD new model TS-520-S	\$ 685
TRIO KENWOOD model TS-820S AC only 160 to 10 M with digital readout.	\$1,050
TRIO KENWOOD MODEL TS-820 AC only 160 to 10 M.	\$ 900
TRIO KENWOOD model TS-600-A FM - AM	\$ 680
TRIO KENWOOD model TR-7400 2 meter FM transceiver 10 to 25 watts output Frequency range 144.00 to 147.995 MHz	\$ 400
ICOM	
VHF TRANSCIVERS SSB	
ICOM model IC-502 6 M SSB portable trans- ceivers 52-53 MHz	\$ 215
ICOM model IC-245	\$ 450
ICOM 701 new model	\$1,160
ICOM model IC-211	\$ 785
YAESU MUSEN FT 901 new model	\$1,575
YAESU MUSEN FT 7 new model	\$ 570
YAESU MUSEN model FT-101-E AC-DC transceivers 10 to 160 M with speech processor	\$ 849
YAESU MUSEN model FL-2100-B Lineal Ampl.	\$ 569
YAESU MUSEN FRG-7 Wadley Loop Receiver All solid state, 0.5-29.9 MHz in thirty 1MHz bands. Electronic band selection	\$ 338
YAESU MUSEN FL110 Solid State Linear Amplifier. Companion unit to FT-301S. 10-15W drive, 200W PEP Input, 160-10mx.	\$ 249
YAESU MUSEN YC-500E 500MHz Freq. Counter. Accurate to .02ppm.	\$ 574
YAESU MUSEN YC-500S 500MHz Freq. Counter. Accurate to 1ppm.	\$ 446
YAESU MUSEN YC500J 500MHz Freq. Counter. Accurate to 10ppm.	\$ 319
YAESU MUSEN YO100 Monitorscope. Matches the FT-101E, but can be used with other Yaesu equipment. (IF kits 455 kHz and 9MHz optional extra). (IF Kits \$12.00 each)	\$ 285
YAESU MUSEN FTV-650B Six Metre Transverter. Converts 28 MHz. SSB to VHF, and includes receiving converter. 50W PEP. Primarily designed for coupling with Yaesu Transmitters.	\$ 249
YAESU MUSEN FTV-250 Two Metre Transverter. Similar FTV-650B. 10W-15W output, but all solid state and built-in AC PS.	\$ 249
YAESU MUSEN FT227 New model	\$ 370
YAESU MUSEN QTR-24 24 Hour World Clock. At a glance the time anywhere in the world can be read.	\$ 33

AUSTRALIA'S SOLE DIST. OF KLM PRODUCTS

KLM SOLID STATE POWER AMPLIFIERS	
(MHz)	144-148 PA10 - 80BL 80 OUTPUT (watts)
"	PA10 - 140BL 140 "
"	PA 10 - 160BL 160 "
"	PA 2 - 70BL 70 "
400-470	PA10 - 70CL 70 "
"	PA 2 - 12B 12 Watts
"	PA 2 - 25BL 25 Watts P.O.A.

New Shipment expected soon.

For personal attention: 24 KURRI STREET, LOFTUS
P.O. BOX 184, SUTHERLAND, 2232 TELEPHONE: 521-7573

YAESU FROM SIDEBAND

SKY-BAND MOBILE HELICAL ANTENNAS	
SKY 80 six feet long 3.5 MHz	\$ 28.00
SKY 40 six feet long 7.060	\$ 26.00
SKY 20 six feet long 14.150	\$ 26.00
SKY 15 six feet long 21.100	\$ 25.00
SKY 10 six feet long 28.500	\$ 24.00
Swivel mounts and chrome plated springs for all	\$ 13.00

ANTENNA ROTATORS

KEN model KR-400 for all medium size hf beams with internal disc brake	\$ 138
KEN KR500 (all rotators 230V AC	\$ 150
Control cable to above	65 cents per metre
Emotor.	
502CXX Similar to Ham11	\$ 219
1102MXX Heavy Duty	\$ 325
1213 Mast clamp for 502CXX	\$ 29.50
300 Mast Stay bearing for above	\$ 32.00
301 Tower top bearing	\$ 32.00

HF ANTENNAS

HADAKA VS 40-80 Vertical	\$ 115
HADAKA VS 33 Tribender	\$ 265
DX 33 Western	\$ 240
HADAKA VS-22-3 Element 15-10m in balun	\$ 173
HADAKA VS-RG Radial kit for VS41	\$33.50

COAX CABLE CONNECTORS

PL-259	\$ 1.20
SO-239 Chassi Mount	\$ 1.20
Male to male joiner	\$ 1.20
Female to female joiner	\$ 1.20
Angle connector	\$ 2.00
T-connector	\$ 2.50
RG8AU Coax Cable	\$1.30 per metre

SWR METER

Twin meter model: Y.M. - I.E. 3.5 to 145 MHz	\$ 28
DRAKE TV - 3300 TV 1 lowpass filter	\$ 34

CRYSTAL FILTER, 9MHz, similar to

FT-200 ones. With carrier crystals.	\$ 35
APOLLO 3 position co-ax switches	\$ 15

MORSE KEYS

EK-127 Electronic Keyer	\$ 99
EK-150S Single Paddle Electronic Keyer	\$ 136
EK-150D Double Paddle Electronic Keyer	\$ 136
MK-1024 Programmable Keyer, 1024 bit memory	\$ 233

HI-MOUND

HK-710 De luxe heavy duty morse key. Heavy base. A really beautifully constructed and finished unit. Fitted with a dust cover, standard knob and knob plate. Ball bearing shaft.	\$ 45
HK-808 Similar HK-710 but with full miniature ball race bearings and more precise adjustments	\$ 75
HK-707 Similar to above but with dust cover and standard knob. On standard base	\$ 19
MK 701 Side Swiper Electronic keyer	\$ 45
BK-100 (BUG) Semi-automatic bug key	\$ 49

VALVES 572 B \$55, 6KD6 \$12.50, 6JS6 \$10.50
6JM6 \$9.50, S2001 (6146B) \$13.50, 12GB7 \$8.50
7360 \$14.50, 6GK6 \$6.

Go RTTY with DOVETRON'S MPC - sparse multi path Diversity
Terminal Units. The Rolls Royce of all terminal units. We are
appointed distributors.

HAL ST5000 - Economy terminal unit. 170-450-850 shifts.
We have locally built units for lower prices, SOON AVAILABLE.
SSTV with Robot 400 \$898 Video Display Units
KEY BOARDS - Write for PRICE DETAILS.

SIDEBAND ELECTRONICS SALES OPEN ON SATURDAYS TILL 12 NOON PETER SCHULZ, VK2ZXL

All prices quoted are net SYDNEY, N.S.W., on cash with order basis, sales tax included in all cases, but subject to changes
without prior notice. ALL-RISK INSURANCE from now on free with all orders over \$100; small orders add 50c
for insurance. Allow for freight, postage or carriage; excess remitted will be refunded.

HOW TO MAKE YOUR VFO AS SOLID AS A ROCK

John F. Ingham VK5KG
37 Second Avenue, Sefton Park 5083

From the beginning amateurs have strived to maintain frequency stability over their transmitters and receivers. Until now the methods which combine the ability to change frequency with the ability to maintain frequency have come under either of two headings.

- (1) Stable variable frequency oscillators.
- (2) Synthesized variable frequency oscillators.

Although the manufacturers of modern HF transceivers using stable VFOs claim drift figures such as 100 Hz/hour, they put in the proviso "after warm-up". Just how much drift occurs during warm-up and how long warm-up takes is not often stated, but figures like 2 kHz in the first hour are not uncommon. How many amateurs have the time to let their rigs warm up for an hour or so before use?

Synthesized variable frequency oscillators are coming into their own on VHF where operation (particularly on FM) is often confined to a finite number of channels each some 25 kilohertz apart. However HF operation requires continuous tuning and the ability to operate on any of an infinite number of closely spaced frequencies. This poses almost insoluble difficulties for the synthesized VFO approach.

So far, Frequency Locking has been limited to Automatic Frequency Control Systems which lock on to an existing carrier, e.g. AM, FM, TV, DSB. Even the proposal to lock a SSB receiver to a transmission by the use of a narrowband notch in the transmitter spectrum requires the transmission to be present, thus negating its advantage for long-term frequency watch-keeping or indeed transmission.

The system to be described is used with a Heathkit HW101 transceiver and a Heathkit SB550 digital readout. However the idea is adaptable to any transceiver and counter. (The SB550 computes and displays the actual operational frequency from the various local oscillators present in the transceiver; such a complex instrument is unnecessary for this project and a simple counter for just the VFO will suffice as long as the other local oscillators are crystal controlled — more on this later.)


Imagine a system which could record in a memory all the digits of the "required" frequency, compare these to those of the "actual" frequency and generate a correction voltage which is fed to the VFO. Because of the number of registers and comparators required this approach would be expensive. However, to achieve our purpose of eliminating frequency drift, it is only necessary to compare the least significant digits (the righthand digit of a frequency readout). For as soon as drift commences it is this digit which will be

first to change and as long as the rate of control is faster than the rate of drift all the other digits will stay constant and thus be of no consequence.

However by the use of only the least significant digit (LSD) an ambiguity of direction of control can occur. As an illustration suppose the "required" frequency has an LSD whose value is 9. Further, suppose that the frequency drifts low so that "actual" frequency has an LSD of 8. A comparison of 9 and 8 will show that the VFO has drifted low and the appropriate control voltage is generated. But, using the same starting LSD of 9, if the frequency drifts high by one unit, the displayed LSD is 0. A comparison of 9 and 0 will show that the VFO has drifted low (instead of high as has in fact happened) and so the control voltage generated will reinforce rather than correct the frequency drift.

To avoid this ambiguity the "required" LSD (no matter what it actually is) is offset to midrange between 0 and 9, i.e. 5. The "actual" display can now show a drift of as much as 4 units high or 5 units low before an incorrect control voltage is generated. In practice this is ample as any frequency drift is continuously corrected long before an error of this magnitude is allowed to accumulate. When the offset "actual" LSD digit is compared to the offset "required" LSD digit (which is now always "5") we get 3 possible output states from the comparator; frequency too high, frequency too low or frequency correct.

The magnitude of the error is determined and corrected as follows. A digitally controlled DC voltage source capable of producing a monotonous voltage staircase of 1024 steps has its output fed to the incremental tuning (or clarifier) line of the transceiver's VFO. When a frequency drift is detected by the above means the controlling voltage is incremented up or down (as appropriate) one step per frequency counter cycle until the error is cancelled



The stabiliser installed on vertical shield.



John Ingham VK5KG in HF section of his shack.

whereupon the controlling voltage is held steady at the new level until further drift occurs.

For consistent control the voltage generator should be linear throughout its range, i.e. each up or down increment should lead to an identical increase or decrease in control voltage. It is more important, however, that the generator be monotonic — i.e. each positive (or negative) input increment leads to a positive (or negative) change in output voltage. Any part of the range which is not monotonic will lead to hunting of the VFO around one frequency.

To ensure that the circuit does not run out of range the output is initially centered on the middle step of the staircase so that both positive and negative frequency drift may be corrected.

In deciding the specifications for the project certain objectives must be kept in mind. The range of control must be adequate to handle the expected drift — approximately 3 kHz should be ample and this is primarily determined by the sensitivity of the transceiver's incremental tuning and the total available swing of the control voltage.

For a given range of control, the smallest change in control voltage should produce a barely perceptible change in note when listening to a CW signal. If the control is too fine the total available range of control will be restricted, if too coarse the operation of the device will be obvious. Also the smallest change in frequency must be smaller than the resolution of the counter, or the control voltage will continuously hunt or oscillate around the required level. As the maximum resolution of my counter is 10 Hz (see reference 1), I chose 3 Hz per step, a nice compromise of all the above factors.

The cycle rate of the counter plays an important part in determining the speed of correction after a step change in frequency (such as when the VFO knob is bumped) because there is only one correction step available for every counter cycle. Generally a counter's resolution is inversely proportional to its cycle rate. For example, the

cycle rate of my counter at 100 Hz resolution is 160 msec.; at 10 Hz it's 1.6 secs. (The accuracy of control achieved is the same for both ranges; the 100 Hz resolution gives "channels" at 100 Hz spacing, the 10 Hz gives 10 Hz spacing. The higher the resolution of the counter the smaller is the maximum permissible step-change in frequency, and the slower is the rate of correction of frequency. However, if the rate of control is faster than the rate of drift, and if there are no large jumps in frequency, effective control is maintained.)

DETAILS OF CIRCUIT

Referring now to the circuit diagram (Fig.

1), IC (b) is a 4 bit latch in which the required LSD is loaded in binary coded decimal form. IC (a) is a 4 bit programmable up/down decade counter which at the end of every frequency counter cycle is loaded with the actual LSD.

IC (c) is a 4 bit comparator whose A = B output is high only when the two LSDs are the same. If the two LSDs are not the same the low output from IC (c) is inverted in IC (d) and used to gate clock pulses (approximately 100 x the counter cycle rate) through IC (e) to the up-count input of IC (a). If the digit from IC (b) is larger than IC (a) only one or two clock

pulses are required to step the digit in IC (a) up to that in IC (b) at which time IC (c) detects A = B and via IC (d) closes gate IC (e). If the digit from IC (b) is smaller than that from IC (a) 8 or 9 clock pulses will be required to step the digit in IC (a) right around the decade until IC (c) detects that both digits are the same and via IC (d) closes gate IC (e).

Gated clock pulses are also fed to IC (f), another programmable up/down decade counter identical to IC (a). Whenever IC (a) is loaded with the latest counter LSD, IC (f) is loaded with binary coded "5" which is "hard wired" into its programmable inputs. After IC (c) has allowed clocking to take place IC (f) will contain a digit either greater than 5 (if only one or two clock pulses were gated) or a digit less than 5 (if 8 or 9 clock pulses were required). IC (g), a 4 bit comparator identical to IC (c), continuously compares a binary "5" hard-wired into one set of inputs with the output of IC (f). If the digit in IC (f) is 5 both the used outputs of IC (g) are low. If the digit in IC (f) is greater than 5 the A > B output of IC (g) goes high; if less than 5 the A < B output goes high.

ICs (j), (k) and (l) are 4 bit programmable up/down binary counters which, together with the following R/2R digital-to-analog converter, generate an increasing staircase output voltage when IC (j)'s "Up" input is pulsed, or a decreasing staircase output voltage when IC (j)'s "Down" input is pulsed. In order to give IC (j) one pulse per Frequency Counter cycle, a suitable pulse from IC (c) is gated by the A > B or A < B signals in IC (h) and IC (i).

Whenever power is applied to the equipment the reset switch should be operated momentarily; this sets the output voltage to a point midway up the staircase by loading a hard-wired binary 512 (half way point of the possible 1024 steps) into the inputs of the 74193s. (Although this could be done automatically it is in any case desirable to have this function under manual control if need be.)

The 10 parallel output bits from ICs (j), (k) and (l) are converted to a staircase output voltage by the digital to analog converter, which is arranged so that in moving from the most to the least significant bit, each successive step has exactly half the control over the output voltage as the preceding one. The 741 Operational Amplifier IC (m) converts the available range of control voltage from the D/A converter to that required by the VFO and provides, if necessary, a DC offset.

CONSTRUCTIONAL DETAILS

I have not included a layout because my unit never proceeded past the initial layout which, although is a little messy, works well. However, if you use a Veroboard layout roughly similar to the layout of the circuit diagram, you should have no problems. The system works at a 1 or 2 Hz rate (the fastest rate is that of the clock which need be only 100 x that of the cycle rate) so the layout from this viewpoint is non-critical.

To maintain monotonic operation of the D/A converter the resistors in the R/2R




FIGURE 1

circuit should be as close as possible to the same value. I purchased 100 x 2 K Ω resistors for only several dollars and by the use of a digital VOM chose those closest together in value for the R/2R network. The actual value is unimportant; the uniformity is. Two such resistors were used in parallel to make up each 1 K Ω resistance, thus ensuring smooth A/D performance.

The range of output voltage is determined by the precise value of the 1 K 5 Ω feedback resistor between pins 2 and 6 of IC (m). The 1 K Ω resistor marked * may be trimmed if compression of output voltage is experienced at either end of its range.

The connections from this circuit to the Heathkit Frequency Display SB650 are as follows —

BCD data —

- A connect to IC18 pin 16
- B connect to IC18 pin 15
- C connect to IC18 pin 10
- D connect to IC18 pin 9

— in SB650

Load connect to IC33 pin 6 in SB650.

Clock connect to IC6 pin 11 in SB650.

Ground connect to Ground in SB650.

Those who have an SB650 can refer to their unit's manual for more information. Those without will find an almost identical circuit described in AR not long ago (reference 2). (Even the same IC types, numbering and pin numbers!)

If you plan to use an altogether different counter, similar points no doubt can be found; however the following criteria must be met —

(1) BCD data lines connected to LSD BCD require positive logic, TTL level and polarity, connected as follows: Data line A to the least significant bit, B to the next least, and so on.

(2) Load requires a TTL level positive pulse at the completion of each counter cycle.

(3) Clock requires a TTL level continuous square wave some 100 times that

of the counter cycle rate, either synchronous or asynchronous. (This may be developed by a suitable astable such as an LM 555.)

If your unit aids the drift instead of correcting it, transpose the connections between ICs (h) and (j), and (i) and (j).

If your transceiver always drifts in the one direction, more control range in that direction may be obtained by reprogramming the digital "512" hard-wired into the three 74193s to 768 or 256 as appropriate.

ADDITIONAL COMMENTS

Because this is a new approach to an old problem, all the possibilities of this circuit have not been worked out. For instance, a complete final frequency read-out is not required for successful operation of this circuit. If your BFO and first local oscillator are crystal oscillators it would be acceptable to count the frequency of just the VFO.

Access to the least significant digit is all that is required. If you don't have a counter you don't even have to build a display as such — all that is required is a count of the LSD and a single 4 bit up counter such as 7490 fed from your VFO and gated on for any constant period of time. The actual value or meaning of the digit is unimportant so long as it gives an indication of frequency drift to the required resolution.

Of course, when using this frequency stabiliser, the use of a clarifier or incremental tuning is not possible as the circuit interprets this as drift and correct accordingly. However, the circuit could be modified to allow for a second latch to replace IC (b) whenever the clarifier was used. The clarifier itself would be a pot switched to replace the resistor marked *.

All that is needed to trouble shoot this unit is a VOM and a thorough understanding of how the unit is intended to operate. Key test points are as follows:

IC (c) pin 6 — always a "high" in Reset and Tune modes, dips momentarily in Lock mode each counter cycle only if actual LSD is different from required LSD.

IC (g) pin 6 (Unused) always a "high" in Reset and Tune modes; in Lock mode stays low (with one kick up each counter cycle) only if actual LSD is different from required LSD.

To test the A/D converter, connect the VOM to IC (m) pin 6 and feed the Clock into IC (j) pin 5 (disconnect other lead). The voltage should smoothly rise over entire range, falling back to minimum again. This movement should be smooth with no backwards steps (check connections and values of the R/2R network) and no flat spots at either end of the range (check IC (m) feedback resistor and offset resistor marked *).

To check operation with the transceiver, lock on to some convenient frequency where a heterodyne with your calibrator may be heard (e.g. 14.1 MHz). Now tune the VFO about 400 Hz high and allow the unit to do its work. Repeat over and over until the heterodyne suddenly disappears. Now switch to Reset and read the counter which will show the range available from centre. Repeat this procedure this time tuning 400 Hz low. These tests will determine the total range of control. Be alert for any abnormal jumps in the heterodyne or any flat spots where control is lost, as these faults point to a problem in the A/D converter.

ACKNOWLEDGEMENTS

Although the original concept of the described circuit is my own, I am greatly indebted to Howard Harvey VK5ZBE for his solution to the Rollover Ambiguity problem, the A/D converter, and his helpful comments during the development stage. I also thank Michael Phillips who made a number of valuable suggestions pertaining to the final manuscript.

REFERENCES

1. "Better Performance for your Heath SB650", J. F. Ingham, AR August 1976.
2. "A More Versatile Station Frequency Counter", D. J. McWilliam, AR November 1976. (Incidentally, the modifications described in 1 are also applicable to the unit described in 2.)

A DIRECT READING INDUCTANCE AND CAPACITANCE METER

Greg Brown VK3YGB

18 Hedderwick Street, Essendon 3040

A recent article (by A. Willcox, in "Television" of May 1976) described a direct-reading capacitance meter based on energy-storage considerations. The present author has extended this idea to measure both inductance and capacitance, and describes in detail the resulting test instrument.

Willcox's circuit operated by repetitively charging the unknown capacitor to a fixed voltage, then allowing it to discharge through the metering circuit. Provided that the fixed repetition period is long compared with the time-constant of capacitor and meter, the average current is propor-

tional to the capacitance. The energy stored in a capacitance is $\frac{1}{2}CV^2$ and in an inductance $\frac{1}{2}LI^2$, so there appeared good reasons why the measurement concept could be extended to inductance, using the same oscillator and metering circuit, but charging the inductor with a fixed current.

The idea was soon tried, and proved to be practicable. A current is passed through the inductor to be measured, and allowed to stabilise. This current and the inductance value determine the stored energy. If the current flow is now diverted from the charging circuit into the metering circuit, it decays to zero with a time con-




View of Bridge.

The instrument wiring is largely contained on a PCB, measuring 3.6 cm x 19.7 cm, which is housed in a 16.5 cm x 11.7 cm x 5.0 cm instrument case. Power is provided by six penlight cells and a LED indicator has been included to remind the operator the unit is on. This indicator has found many uses in battery powered equipment and consists of a complementary pair of transistors connected in an astable circuit. The benefit gained by using this



Capacitance FSD	S1 Position	S2 Position	S4 Position	Inductance RSD	S1 Position	S2 Position	S4 Position
50 pF	5	5	x 1	5.0 uH	5	5	x 1
100 pF	5	10	x 1	10 uH	5	10	x 1
500 pF	4	5	x 1	50 uH	4	5	x 1
1.0 nF	4	10	x 1	100 uH	4	10	x 1
5.0 nF	3	5	x 1	500 uH	3	5	x 1
10 nF	3	10	x 1	1.0 mH	3	10	x 1
50 nF	2	5	x 1	5.0 mH	2	5	x 1
100 nF	2	10	x 1	10 mH	2	10	x 1
500 nF	1	5	x 1	50 mH	1	5	x 1
1.0 uF	1	10	x 1	100 mH	1	10	x 1
5.0 uF	1	5	x 10				
10 uF	1	10	x 10				






FIGURE 3: Battery saver circuit.




FIGURE 4: Board lay-out.




FIGURE 5: Printed circuit board — copper side.

circuit is that both transistors turn on together and their total current is passed through the LED. Average current drain is 0.5 mA, a small price to pay for power on indication. The indicator is wired on a separate PCB.

INDUCTOR MEASUREMENTS

When measuring inductors errors may arise due to approaching the self-resonant frequency. For measurements at not greater than 80 per cent of the self-resonant frequency

$$\text{Apparent Inductance} = \frac{L}{(1 - m^2)}$$

where $m = \frac{\text{total frequency}}{\text{self-resonant frequency}}$

If m is less than 0.1 the correction is negligible.

In practice errors have only been apparent when measuring multi-layer coils of single section. An error of + 8% is typical for a coil of 15 mH wound with 770 turns of 18 B & S in a single section of 21 layers. Inductors of this construction are generally only suitable for low frequency applications. ■

QSP

RADIO FIELD DAY AT THE BLIND CITIZENS' COMMUNITY CENTRE

A field day and barbecue to demonstrate a number of aspects of amateur radio was held at the Kooyong Blind Citizens' Community Centre on Sunday, 4th December.

Special emphasis was given towards providing an understanding of the potential this recreation activity has for people with a slight disability. A number of pieces of equipment were demonstrated, and were afterwards available for interested people to handle and examine.

Some of the specific pieces of equipment on display included:

- general coverage HF transceivers;
- VHF equipment covering the 2 metre band for local communication;
- Exhibits of general radio components;
- A talking calculator which was modified to work in conjunction with a digital volt meter;
- Demonstration of aerials;
- All band communications receiver;
- Morse code equipment with automatic dot memory.

A number of qualified operators gave their valuable assistance to make the day a success, and we thank them for this. They included — Rob Faravonie VK3ANI, Bob Byers (who is totally blind) VK3BHF, Dr. Gerald Under VK3AOU, Bob Young VK3BIC, Bill Mudie VK3XS, Graham Scott VK3ZR, David Ditchfield VK3YSK and Collin Pomory VK3BLE.

It is hoped this field day will be the forerunner of other such activities, and may lead the formation of a club which can assist visually handicapped people to become more involved with this field.

Anyone wanting further information can contact Peter Rickards or David Ditchfield at the Association for the Blind, Kooragang, Phone 20 8701.

SELF-REGULATORY

The editorial in QST for Nov. '77 looks at the changes in their FCC amateur radio regulations from a period of over-regulation especially for repeaters and operation some years ago to the present policy of seeing amateurs generally. This, because of the acceptance that amateurs need to be self-regulatory and self-policing. The example is quoted of the traditional image that amateur frequencies were available for use by all amateurs to the present situation of channellisation on VHF and UHF. This means that amateurs themselves must enter the spectrum management field in respect of their own bands and see to it that self-regulation and self-policy actually work.

HOW VICOM HAVE WRAPPED UP THE HAM BUSINESS

No gimmicks, no free trips to the moon — just good honest service from experienced and licensed Amateur Radio Operators with an interest in the customer. VICOM have comprehensive service facilities with the latest in sophisticated test equipment operated by trained technicians. Call VICOM today for quality equipment backed by ethical business!



accessories

ROTATORS

- ART3000C heavy duty with control box \$199.00
ART0000 super heavy duty \$478.00
AR22XL light duty model \$109.00

LOW PASS FILTERS

- FD30M 32MHz Fc, 1Kw max, 3 stages \$30.00
FD30LS 32MHz Fc, 200w max, 3 stages \$20.00

NOISE BRIDGE

- Omega TE701, up to 100MHz \$40.00

- CS201 2 position, high power up to 500MHz \$22.00
CS401 4 position commercial quality \$47.00

2 METRE ANTENNAS

- ARX-2 Rings Ranger gain antenna \$49.00
Lundinow 2m mobile whip \$35.00
Scaler 3/4 wave whip, 2 metres \$6.50
Scaler wave whip, 2 metres \$16.70
AS210BN twin 10el beam, 18dB gain \$119.00

CONVERTERS

- 144MHz, uses 28MHz IF \$45.00
432MHz, uses 28MHz IF \$50.00
1296MHz, uses 28MHz IF \$59.00

- QM70 high power, 70w pep max, 2 metres \$119.00

PARABOLIC DISH

- PBA-1200 70cm/1.2GHz complete \$349.00

TRAP DIPOLES

- Mdy VN 80-10m trap dipole \$99.00
AL48DXN 40 & 80m trap dipole \$59.00

TRAP VERTICALS

- V4J 40-10m, 5.2m high, no guys \$95.00
V5J 80-10m, 6.2m high, no guys \$129.00

HY-GAIN ANTENNAS

- Hy-Quad 10/15/20m, 2el \$299.00
204BA 4el monobander, 20m \$249.00
203BA 3el monobander, 20m \$190.00
1A4V/1WB trap vertical 40 thru 10 \$99.00
18AVT/1WB trap vertical 80 thru 10 \$139.00
TH3MK3 10/15/20 3el beam \$269.00
TH3J 10/15/20 3el beam \$199.00
TH6DX THunderbird \$345.00

JAYBEAM FOR VHF/UHF

- 80/70cm 8el w/ 70cm, 15.5dBd gain \$99.00
48/70cm 4el w/ 70cm, 15.5dBd gain \$76.00
PBM18/70 18el 70cm, 14.3dBd gain \$69.00
DB/70cm twin 8el, 70cm, 12.3dBd \$69.00
10V/2m 10el, 2m, 11.4dBd gain \$77.00
PBM/2C phasing harness \$17.00

BALUNS

- AS-BL for beams \$31.00
BL50A 50 ohm 4Kw for dipoles \$25.00
BL70A 70 ohm 4Kw for dipoles \$26.00

MORSE KEYS

- HK702 deluxe key with marble base \$35.00
HK706 economy key \$19.00
HK706 operators key \$20.00
MK701 manipulator (side-swiper) \$38.00
EK103W electronic keyer \$159.00

MICROPHONES

- VM-1 noise-cancelling, dynamic, low Z \$8.90
VM-2 desk mic, dynamic with pre-amp \$29.80

6m ANTENNA

- SS-56 6m 3el beam (NAGARA) \$118.00

Prices and specifications subject to change without notice.

HAM HEADQUARTERS

ICOM QUALITY PORTABLES FOR 6 & 2

ICOM IC-215 2m FM transceiver

- 2 meter FM • 3 W PEP • 15 channels, 12 by selector, 3 by function switch
- Dual power level, 3 W for long distance, 0.5 W for local
- Dial illumination for night use
- Power pilot lamp
- Frequency range 146 to 148 MHz



ALL-MODE for TWO \$750

The IC211 2m fm transceiver from ICOM is the last word in digital all-mode state of the art transceivers. Fully synthesised in 100Hz or 5KHz steps, has dual tracking, optically coupled VFOs with 7 digit LED readout. One knob controls all frequencies. Modes fm, usb, lsb, cw. Internal 240vac and dc power supplies. Comes complete with VICOM 90 day warranty. List price \$750.

STATE OF THE ART

- IC202E 2m sbb portable transceiver \$219
IC502 6m sbb portable transceiver \$219
IC245 2m fm digital mobile transceiver \$450
IC215 2m fm portable with 9 chs, installed \$219

ACCESSORIES FOR THE PORTABLES

- IC202 in-car pack with charger \$57.00
ICM2 desk microphone \$54.00
IC50L 6m linear, 3w in, 10w out \$98.00
IC20L 2m linear, 3w in, 10w out \$98.00
Mobile brackets for portables \$17.00



the FAMOUS MACHINE!

IT'S CRYSTAL CLEAR! The Icom IC225 synthesized 2m FM mobile transceiver features programmable RIG for any frequency multiple of 25KHz from 146 thru 148 MHz. Your new IC225 comes complete with 90 day warranty, mic, mobile mounting bracket and instruction manual.

\$299

YAESU

- FT101E transceiver, 160 thru 10M \$899.00
FL2100B HF linear amplifier \$578.00
FRG7 communications receiver \$349.00
FT7 HF mobile transceiver \$569.00
FT901DM HF transceiver \$1575.00

HUSTLER

MOBILE WHIPS

All resonators are precision sound with optimised design for each band. Assembly 17.7 Ph stainless steel adjustable tip rod for lowest swr and band edge marker.

Standard Hustler Resonators: Power rating 400w sbb.

Model	Band	Price
RM10	10m	\$16.00
RM15	15m	\$16.00
RM20	20m	\$16.00
RM40	40m	\$20.50
RM80	80m	\$22.00

- M02 fold-over mast \$29.00
BM-1 bumper mount \$24.00

KENWOOD



KENWOOD TS-520S transceiver

- TS205 HF transceiver, digital \$1172.00
TS505 HF transceiver 160-10m \$747.00
TV502 2m transceiver \$280.00
TV506 6m transceiver \$249.00
TR3200 70cm fm transceiver \$317.00
TR7400 2m digital mobile transceiver \$483.00
TR7500 2m mobile synthesises transceiver \$399.00
MC50 desk microphone \$58.00
MC10 ptt hand microphone \$16.00
TL922 HF linear amplifier \$1099.00
AT200 matching antenna tuner \$169.00
SP820 matching speaker for TS205 \$58.00

VICOM


novice mods
done free!

Head Office and Mail Orders:

Direction: Russell J. Kelly
Peter D. Williams

vicom Ph (03) 699.6700
68 Eastern Road
Sth Melbourne Vic. 3205

Adelaide 43.7981 Canberra 82.3581 Perth 446.3232 Brisbane 38.4480 Hobart 43.6337



Dealer enquiries invited

AUSTRALIAN NATIONAL CONTESTS

FEBRUARY—SECOND WEEK-END

John Moyle Memorial National Field Day. This contest uses all bands and modes, and has a contest to suit just about everybody, whether portable, mobile or fixed. An ideal time to have a group or club outing, and operate as a multi-operator station.

AUGUST—SECOND OR THIRD WEEK-END

Remembrance Day Contest. The friendly contest, and the major Australian contest for everyone. All bands and modes may be used. This contest is between the Divisions of the WIA, with certificates awarded for the best scores in each section in each call area of VK, ZL and PZ.

OCTOBER—FIRST AND SECOND WEEK-ENDS

VK/ZL/Oceania DX Contest. This is the only international contest sponsored by Australia and New Zealand. All bands 1.8 to 28 MHz may be used. Phone on first week-end and CW on the second. The contest is run alternatively by VK and ZL.

DECEMBER THROUGH JANUARY

Ross Hull VHF/UHF Memorial Contest. VHF and UHF bands, single operator only. There are 7 day and 48 hour sections. Phone, CW and Open. Ideal for the Z and Y calls.

DIVISIONAL CONTESTS

The majority of Divisions have their own contests, both interstate and intrastate. Refer to "Amateur Radio" or Divisional broadcasts for further details.

MAJOR OVERSEAS CONTESTS

February: APRIL DX Contest, Phone first week-end, CW second week-end.

March: APRIL DX Contest, Phone first week-end, CW second week-end, BARTG Spring RTTY Contest. "CQ", WW, WPX, SS.

August: SARTG RTTY Contest. SEANET WW DX Contest. All Asian CW. European CW.

September: European Phone Contest.

October: RSGB 7 MHz CW. "CQ" WW DX Phone.

November: RSGB 7 MHz Phone. "CQ" WW DX CW.

There are many more contests, far too numerous to mention but when rules are available, they will appear in the Contest column of AR.

Your log will make any contest a success. ■

QSL CARDS—HOW TO QSL

QSL's are a vital requirement for most awards as before a certificate can be issued it is necessary that the applicant can show proof that he has contacted the stations claimed. The QSL card is still the only really acceptable way of doing this.

To have any value a QSL card must contain certain basic information about the QSO and if any of the following details are not included the recipient will be unable to use the card for award purposes.

The following information must be given—

(1) Your call sign shown prominently.

(2) The words "To Radio" confirming our QSO" or "This confirms QSO with" clearly showing the call sign of the station worked.

(3) The location of your station, including full postal address. Remember, some stations will not have a current Call Book and otherwise will not be able to send their QSL to you in many instances without this information.

(4) Date and time of QSO. ALWAYS use GMT.

(5) Band and Mode used. If it was a QSO using the same mode both ways, mark this clearly as many awards are endorsed for a particular band and/or mode.

(6) Signal report using the standard RST report system.

When ordering QSL cards from a printer, remember that the above details are essential regardless of any additional information you may wish to add. A convenient way of presenting this information is to use the following format:

YOUR CALL SIGN

YOUR QTH

To Radio confirming our two-way QSO on MHz Mode at hrs. GMT on /

Your signs here were R S T

It is recommended that a size of 5½ x 3½ inches should be used. This is a standard size fitting normal envelopes and conveniently handled by QSL Bureaux. If larger cards are used, they will require special envelopes and will not pack easily with other cards if sent in bulk.

If while writing out a QSL a mistake is made, do not make any attempt to alter it but write out a new card. Any card which has been altered is unacceptable for awards. ■

THE "Q" CODE AS USED BY RADIO AMATEURS

QRA What is the name of your station?
The name of my station is

QRG Will you tell me my exact frequency (or that of)?
Your exact frequency (or that of) is kHz (or MHz).

QRH Does my frequency vary?
Your frequency varies.

QRI Is my note good?
Your note varies.

QRK What is the intelligibility of my signals (or those of)?
The intelligibility of your signals (or those of) is (1-5).

QRL Are you busy?
I am busy. Please do not interfere.

QRM Are you being interfered with?
I am being interfered with (1-5; nil, slightly, moderately, severely, extremely).

QRN Are you troubled by static?
I am troubled by static (1-5).

QRO Shall I increase power?
Increase power.

QRQ Shall I send faster?
Send faster (..... words per minute).

QRS Shall I send more slowly?
Send more slowly (..... words per minute).

QRT Shall I stop sending?
Stop sending.

QRU Have you anything for me?
I have nothing for you.

QRV Are you ready?
I am ready.

QRW Shall I inform that you are calling him on kHz (or MHz)?
Please inform that you are calling him on kHz (or MHz).

QRX When will you call me again?
I will call you again at hours (on kHz) (or MHz).

QRZ Who is calling me?
You are being called by (on kHz) (or MHz).

QSA What is the strength of my signals (or those of)?
The strength of your signals (or those of) is (1-5).

QSB Are my signals fading?
Your signals are fading.

QSL Can you acknowledge receipt?
I am acknowledging receipt.

QSO Can you communicate with direct (or by relay)?
I can communicate with direct (or by relay through).

QSP Will you relay to?
I will relay to

QSV Shall I send a series of V's on this frequency (or kHz) (or MHz)?
Send a series of V's on this frequency (or kHz) (or MHz).

QSW Will you send on kHz (or MHz)?
I am going to send on kHz (or MHz).

QSX Will you listen to (call sign) kHz (or MHz)?
I am listening to (call sign) on kHz (or MHz).

QSY Shall I change to transmission on another frequency?
Change to transmission on another frequency (or on kHz) (or MHz).

QSZ Shall I send each word or group more than once?
Send each word or group twice (or times).

QTC How many messages have you to send?
I have messages for you (or).

QTH What is your location?
My location is

QUM May I resume normal working?
Normal working may be resumed.

DISTRESS CALLS

The letters "SOS" used in telegraphy and the word "MAYDAY" used in telephony indicates that the sending station is threatened by grave and imminent danger and requests immediate assistance.

Any licensee hearing such a call must cease transmissions and listen for details on the frequency used. He should answer the transmissions, if he can provided he does not interfere with another station answering the call. All relevant information

should then be conveyed as quickly as possible to the police or other appropriate Government Department.

When a distress call is not fully justified the letters "XXX" in telegraphy or "PAN" in telephony indicate a state of urgency and the same procedure is followed as for distress signals. As with distress, all such calls are repeated three times.

Licensees are advised that in certain circum-

stances false distress calls have been initiated in recent years and it is imperative therefore to note or record all possible information which can be of use to the relief services.

International distress and safety frequencies are 500 kHz for telegraphy, 2182 kHz for telephony, 4.433 MHz for survival craft, 121.5 MHz aeronautical (plus others), 156.8 MHz for maritime mobile and 243 MHz survival. ■

A VISIT TO CHINA

Gil Sones VK3AUI
30 Moore Street, Box Hill, 3129

At the beginning of September, a party of 20 Australian tourists left Kowloon by train for the Chinese border. In this party there were two amateurs, Lionel VK3NM and Gil VK3AUI.

When the train reached the border town of Lo Wu everyone was required to get off. After exit formalities we crossed the bridge to the Chinese town of Shum Chun, where the immigration, health and customs formalities were carried out.

After these formalities the guides and interpreters assigned to the tour welcomed us. The welcome speech was accompanied by tea and cigarettes. This formal speech was to become very familiar as visitors are always welcomed and briefed at each place visited.

Then lunch was served in a dining hall and we received a lesson in the use of chopsticks. Very necessary as we were to use chopsticks for the next two weeks.

After lunch the tour proceeded by train to Kwangchow (Canton) and the start of the tour. Throughout the tour visits to places of interest were arranged and everyone was treated as a guest. Suggestions for specific interest items were noted and arranged whenever possible.

Photography was freely allowed except from aircraft during flights. No restrictions were placed at any other time on photography.

The tour, which was of fourteen days' duration, visited the towns of Kwangchow, Kweilin, Changsha, Shaoshan and Wuhan. These towns gave a considerable cross-section of China as well as showing some areas of scenic interest.

Visits were arranged to factories, schools, a commune, hospitals, a university and places of scenic interest.

Also performances of plays, operas and concerts were included whenever they were available. The subject of these were usually revolutionary themes and they were played to packed houses.

The number of people doing manual labour is staggering and the amount of work done is very high. Mechanical aids are appearing but have not yet taken over in many cases.

Transport relies heavily on buses in the towns and people with handcarts for short distance goods transport. For longer distances trucks, tractors and trailers are used.

Between cities the train and the canal and river systems are used extensively. The railway system is heavily reliant on steam trains which are fuelled with coal.

Personal transport is by foot or by bicycle; there are 300 million bicycles in China and the traffic is little short of chaotic. The bicycles are quite dear at 200 Yuan or \$100 Australian, which is four months salary for an average wage earner.



Wreaths at monument to Chairman Mao in Changsha on the first anniversary of his death.



Aqueduct in the country between Shaoshan and Changsha with children swimming in it.

On the subject of money, the unit is the Yuan, which is approximately 50 cents Australian. All transactions must be in Yuan, unlike Russia, where goods are sold to tourists in western currency. The Yuan is divided into Jiao and Fen. There are 10 Fen to a Jiao and 10 Jiao to a Yuan. Both Yuan and Jiao are notes and the Fen are coins. It is quite novel to have a note which is worth 5 cents Australian.

Since all money to be spent must be converted at the bank to Yuan and only some travellers' cheques are negotiable, it is very wise to check up before you go there. In general bank notes are freely convertible but some of the popular varieties of travellers' cheques are either totally unacceptable or only occasionally acceptable. Information is available from China Travel Service in Hong Kong. The problem is not very great though, as prices are low and expenditure is really only on souvenirs.

Whilst travelling the communications systems and the broadcasting system were observed even though specific visits were not arranged.

The communications systems used were of interest. The phone lines were often of aerial construction, with both open wire lines and catenary cables. The cities had automatic telephones but trunks were all manually connected. The quantity of trunk lines was not great and the guides often had to book calls to make forward arrangements.

Local broadcast stations take Radio Peking off air and rebroadcast as well as

using local programming. The broadcast stations cover the country. Foreign broadcasts are hard to copy as the QRM also covers the country very effectively and appears to emanate from a myriad of sources.

TV and FM broadcasting is in all major towns often using antennae placed in the middle of the town on a building. However, most TV sets are community owned due to the price of receivers which is 200 to 400 Yuan (\$A100 to \$A200). Wages are only 30 Yuan to 100 Yuan a month with an average monthly wage of 50 Yuan (\$A25). This leaves only enough to save up for a bike and a few other luxuries and leaves TV a bad last.

Radio sets are more widespread but are dear with a 7 transistor model costing approximately 60 Yuan or \$A30. The supply of radio parts is extensive with the more common parts freely available. Radio shops are often part of department stores or one half of a combined bicycle and radio shop. The radio shop sometimes has a small repair department.

Radio shops are full of people buying parts. Some of these people are probably hobbyists whilst others would be repairers of radio and electronic equipment.

The parts range from the basic resistors, capacitors, transistors, valves, transformers and loudspeakers right up to large transmitting type valves. Valve types 805 and 832 were on sale as well as some other larger unidentified types. These are probably for PA use or for industrial use.

To obtain some souvenirs I set out to purchase some small components in one shop and had no trouble in conveying my wishes to the assistant. Very soon the shop was full of interested shoppers anxious to see the fun. A chap from the repair department hurried forward and tried to guide my purchases along useful lines. He was anxious that I should obtain enough of the right parts to build something useful. Eventually, after much selection of the bits, I thanked the staff, paid the bill and left with my souvenirs.

Much to my astonishment only a few doors away was a disposals shop full of old CRO's, industrial electronic bits and a pile of command type condensers, large transmitting condensers, filter condensers and valves such as 832's, 805's and 833's. These were a most unexpected find in the middle of China at Wuhan. However, the bulk of them prevented me buying any as souvenirs.

By this time I had a large crowd following and I headed back to the hotel. This was another noticeable feature as people have not seen Westerners and tend to follow you just to see what you look like. They are very friendly and will help you find their way if you can communicate where you want to go.

Finally after two weeks touring China the party returned to Hong Kong and the West. During those two weeks we had been shown as much of China and what is being done there as was possible in a short time. ■

A CALL TO HELP THE CITIZENS RADIO SERVICE

Amateur radio operators should take part in the Citizens Radio Service. This was the surprise proposal of Posts and Telecommunications Department administrative officer Mr. David Large, to the recent WIA Queensland Convention.

The suggestion came in his keynote address on the CRS, the Amateur Radio Service and the proposed Radio Communication Act.

"Perhaps the greatest benefit of the CRS to the ARS is intangible but it is a real benefit which I hope the WIA will exploit," he said.

"There are many CBers who have an interest in radio technology.

"These people form a large pool of future amateurs.

"Their interest and knowledge at the moment is minimal.

"It must annoy amateurs that so much inaccurate information is broadcast over CRS channels as facts.

"I would hope to see all amateurs taking a part in the CRS.

"This is seen by us as one way of injecting some professionalism into that service, not only technical expertise but operating techniques.

"By doing this, I would hope that many of the CBers would be encouraged to discover what radio is all about, to find out the pleasures through a hobby of amateur radio, which, properly controlled, allows contact with many people with many backgrounds in many countries."

Mr. Large said the decision to introduce the CRS was the most significant policy change in radio frequency management since 1948 when private VHF services were introduced.

Policies in force for 50 years had been challenged and found wanting.

Proposals for changes like that made by the WIA came at an opportune time.

Department philosophies, procedures and staffing were being reviewed.

The Radio Communication Act would be introduced next year replacing the Wireless Telegraphy Act of 1905.

Mr. Large said there was no doubt that UHF was the answer to the CB demand technically, and he believed, in the long term, economically.

Five years' parallel service was necessary for development and production of UHF equipment, particularly by Australian manufacturers.

Mr. Large said: "The interim period was not designed to allow for the massive development of HF services.

"Already the high standards of quality to be demanded from January 1, 1978, have been challenged but the Government's decision is clear.

"I cannot see any possibility of major amendments."

This was endorsed last month by Senator John Knight, who, speaking for the Minister Mr. Robinson, said: "In 1982, operators of HF equipment will only be allowed to continue under the auspices of the amateur radio service.

"Five years is sufficient time for people to obtain qualifications as amateur radio operators."

Mr. Large said: "That speech should be of some significance to everyone here."

Mr. Large said he was concerned existing regulations appeared to relate to controls over the amateur service which were inappropriate to 1977.

"Part of this is restrictions on examinations and qualifications for entry to the amateur service.

"There is a general move in the community towards greater reliance on self regulation in all forms of social activity.

D. Marshall VK4ZAF
23 Karowa Street, The Gap, Qld.

"This will have an application to the Amateur Radio Service."

In commenting on the WIA proposals, he said: "The department is generally sympathetic with the broad thrust of the proposals."

"Generally, though with some modifications, I feel agreement will follow logically."

"If the Government is prepared to allow the ordinary citizen with no technical qualifications to use radio virtually without any restrictions, then the proposals of an organisation composed of technically qualified members who operate under a high standard of ethics should be acceptable."

"The proposals about a simpler examination and licensing system will be considered during a department review."

"You can be assured that any suggestion leading to more efficient management falls on receptive ears."

"Simply, drafting of the new Act gives the opportunity to completely review the regulations affecting the ARS."

"I should make clear the devotion the department has to protect the rights of the amateur operator."

"We well recognise the difficulty for the amateur service by people who deliberately pirated into the 11 m band."

"The department is adamant that this should not occur again."

"Senator Knight in his recent speech said: 'There is concern about advertise-

ments in CB publications about the sale of equipment designed for the amateur service only. The Minister wishes it to be made quite clear to everyone concerned the Government will not stand by and allow pirating activities into other authorised services.'

"It is the Government's view that strong action should be taken to ensure that other authorised services are protected and that licensed operators in the CRS comply with regulations."

"It has been said that the loss of the 11 m band disadvantaged amateurs."

"Superficially, this appears to be so. However, this decision will provide long term benefits."

"One important benefit is that this exercise has brought the WIA and the department closer together."

"It has led to a more sympathetic approach to the WIA's role and position which will be reflected in the new Act and regulations."

"At the same time, the challenge to the Amateur Service by the CBER must force the WIA to look carefully at its own service."

"There is a belief that its present aims and objectives need reviewing."

"If this takes place, then I'm sure it will be beneficial."

Mr. Large said that in the past there had been suggestions that conserving the spec-

trum was synonymous with ensuring it wasn't fully used.

This view had resulted in an attitude of regulatory enforcement rather than management.

As a result, there had been stress placed on restrictive operator regulations within the services rather than management through technology.

"I believe that more stress has to be given to the control of the radio technology employed."

"This does not detract from the need to have enforcement provisions, but there has to be a better understanding of the department's objectives of management."

"It will be necessary in the new Act to put beyond doubt the Minister's power of control over all types of radio emission."

"This will allow for measures to deal with all forms of harmful interference to radio services."

"From this will flow the ability to set standards for radio equipment."

"It will be necessary to devise legislation procedure to control the use of unlicensed radio transmitting equipment and to increase the penalties."

Mr. Large said this would not be easy as it impinged on other legislation and practices."

It might be possible to determine the licensing of retailers through a tier system according to the types of equipment they sold. This seemed to be the answer. ■

MOBILING AROUND AUSTRALIA — SOME INTERESTING POINTS ON MOBILING OUR CONTINENT

Arthur Brown VK2IK

Well, we must see our own country the next time we go travelling."

These were the conclusions of YXL

Phyl and myself as we sat in our

exchange flat in Surrey, England,

pondering on our next tour. It was

needing the end of our 12 months

(1975) stay in Britain during which

time we had exchanged homes with

a young teaching couple who were

on "teacher exchange" in Sydney.

From our base in Old Coudon we

had toured in our campervan around

7,000 miles of Europe, 5,000 miles of

Scandinavia and 8,000 miles of Britain.

The latter two as G3TMO/M, but

thereby hangs another tale.

PREPARATIONS FOR VEHICLE AND RADIOS

Having caravanned for years, and in the light of our 1975 experiences with the campervan, we figured that a well insulated Motor Home would be just the thing for touring Australia. Thus it was that by April 1977 we had obtained a Ford Transit Motor-home, had installed 2 and 6 Mx MR6 FM transceivers and a Sommerkamp TS288A SSB transceiver. Suitable mobile whips were checked out 10 to 160 Mx. English "G" whips 6 ft. long (previously used in

Britain), 2 Mx and 6 Mx quarter wave whips and a range of home brew centre loaded 12 ft. whips to cover 10 to 160 Mx. In addition an extra section was carried to extend the 20 Mx whip to a full 16 ft. for stationary mobile operation. This latter whip was frequently used when the going became tough and conversely the 6 ft. helical was good for mobile use when signals were strong. There was at least 3 S points between these two antennas in favour of the 16 ft. whip.

The trip we planned would take 16 weeks with a daily average of 120 miles or 200 km. This subsequently worked out as planned to a distance of 21,000 km. We drafted out a schedule of places, stop-over points, mail collection post offices and all the other data that would make the journey interesting from a scenic and historical point of view. In the months before we left the vehicle and spares had been organised and a hand throttle with a quick release mechanism was designed and fitted. This was a great boon as it relieved the leg fatigue normally encountered, and, in conjunction with a vacuum gauge also fitted, considerably reduced fuel consumption. In several preliminary journeys 14 m.p.g. was obtained, however, on the trip it worked out at 16 m.p.g.

Every endeavour was also made to eliminate electrical noises that intruded into the transceivers. Suppressors had been installed at all anticipated noisy spots, including a flywire mesh clipped over the ignition harness area. Still there was an S4 noise on most bands originating from the alternator regulator when mobile. No manner of filtering would clear it. Aubrey VK6XY, whilst we were mobile near Albany, W.A., came up with the answer, which was to install an electronic regulator in lieu of the vibrating reed type. This we did at Fremantle and it worked the trick with noise down to S2. A further reduction to S1 was achieved by the inclusion of a 0.05 MFD across the alternator field rectifiers. A larger value sent the regulator "beserk" into a two minute cycle of "hunting" with panel meters showing high then low as the charging rate changed. Noise levels were not constant and it was found that the addition of an earthing conductive rubber "car-sickness" strap installed at Darwin reduced the tyre static encountered on smooth bitumen surfaces.

TRAVELLERS NET

Prior to commencing the trip I had met up with Doug VK3YK, Keith VK6KC, Vic VK6NL and Harry VK6ZZ on the "Travellers

Net". This was to be a great source of interest and assurance if aid was needed. Throughout the entire trip, almost daily, we were able to QSO on 14.106 MHz at 0300 GMT. Other travellers there were on the net and they shared our pleasure in like manner. Other fixed stations occasionally joined the net, many of whom we were able to meet at their QTH. Not so Keith VK6KC — he is accessible only by boat or helicopter at the pearling fleet base at Kurie Bay, north of Broome.


ROUND AUSTRALIA TRIP

Our journey took us west to Adelaide via Menindee, Wentworth and Renmark, thence north via Pt. Augusta to the Flinders Ranges. Port Lincoln preceded our run to Ceduna, where I was able to see over the Satellite Tracking Station. The trip across the Nullabor on the new road with scenic lookouts on to the Great Australian Bight was more interesting than what we had been led to believe. The growth of small shrubs and salt bushes adjacent to the road gave the impression that landscape gardeners had been busy most of the way. Technically, it was interesting to see the site of the old Telegraph Station at Eucla on the WA side of the border. Unfortunately, the building, once the place of great activity as a relay link in the trans-Australia Telegraph of 1877 is slowly being inundated with sand and destroyed by vandals. Further west was also to be seen the buildings of Balladonia, another relay station now privately occupied and displaying discouraging notices for visitors. Around these buildings are remnants of the old telegraph lines going off across the plains to nowhere. In their place nowadays are the dishes of the microwave broadband bearers to be seen at regular intervals across the land.

It was our pleasure to meet some of the VK6's at Kalgoorlie and to see the historic mining sites of the Golden Mile at Coolgardie. Down south to Esperance and across to Albany and an escorted tour of the Canning Factory by Aubrey VK6XY and a visit to Vic VK6NL at Denmark was most enjoyable. We were impressed to see the giant Karri trees of the Pemberton area — what wonderful towers they would be for amateur radio!

All around the coastline through Perth, Geraldton, Carnarvon and to Wyndham we visited scenic spots and VK6s. At Exmouth I saw the relics of the old 200 MHz radar station, of particular interest to me as the equipment had been made in Sydney during the early 1940s. Others similar to it had been shipped around the Pacific for early warning of hostile aircraft. Not far away were the 13 masts of the US Naval Communications Station, the tallest being 1,271 ft.

From the cyclone tower of Onslow we finalised our plans to visit the mining towns of Tom Price and Wittenoom. This was a journey of 390 km on gravel and dust with no garages in between. The scenery was most rewarding, especially the gorges in the Hamersley Ranges and we consider that this area was one of the most colourful and rugged, perhaps more so than Central Australia.



Giant ant hills (termites) in Hamersley Ranges near Joffe Falls, W.A.

In a barge with other sightseers we traversed the Fitzroy River and admired the spectacular Geikie Gorge and saw numerous Johnston freshwater crocodiles. The Ranger assured us that, although the majority of crocodiles to be seen were about 6 ft. in length, there were a number of much larger ones about. In fact, he could look across the river each morning at cuppa time and see one old croc, sunning himself and this, he assured us, would be 200 years old and 16 ft. long. This information he gladly put across the "Travellers Net" for me for the benefit of some members who doubted that freshwater crocs could attain this length. Later at Kununurra we found an interesting side-light on crocs in a brochure to quote "If by mistake you catch a freshwater crocodile, be careful you don't hurt him as they are protected". This is true and is not a comical suggestion as some have been killed by careless fishermen.

Fitzroy Crossing the "town" near Geikie, was a sight to behold. The surroundings littered by innumerable drink cans and bottles the one and only galvanised iron building served as hotel, store and petrol station. The store and petrol sections shut down at 12.30-1.30 p.m. but we finally obtained fuel at 2.30 p.m. We had no option but to wait as the next fuel was at Halls Creek, 300 km away. One interesting feature of the Northern Australia landscape is the prevalence of the "Upside-down", or Boab trees, varying in size with their enormous pulpy trunks. The biggest we saw was at Broome and measured 13 ft. in diameter.

Wyndham proved a surprise to us. We visualised flat country and mangrove swamps. True, there were mangroves, but there were also handsome mountains and a great lookout bluff, the Bastion of 1,100 ft., rewarded us with extensive views over Cambridge Gulf. At the modern Wyndham Hospital we surprised the nursing daughter

of Con Murphy VK6PM, by asking her to come to the van to have a chat with her father in Perth. We had QSO'd him coming into town and had arranged a later sked.

At Kununurra and Lake Argyle we were impressed by the beauty of the river and size of the lakes. In parts the scenery of hills and water reminded us of the Norwegian Fjords. The Ord River irrigation project was also well worth the visit to see the lush crops of sorghum.

Katherine at the junction of the East West and North South roads had its Gorge on the Katherine River where scenes of the film "Jedda" had been filmed years earlier. The "Jedda" Rock was an impressive bluff part way along the gorge. At the camp ground nearby very friendly emus scavenged around the caravan sites and a pair of Bower Birds with apparent unconcern of the cars on the near approach road, darted in and out of their bower and colourful display of bright objects they had gathered.

A 350 km run to Darwin brought us to the northernmost city which is gradually losing some of the scars of its 1974 Christmas Day battering. The broadcast band is much occupied by Indonesian stations and the ABC competes for air space, which made us realise that Darwin is much nearer to Indonesia than any other Australian city. In fact, it was much this story from Port Hedland across to Darwin. In this whole region broadcast stations were difficult to receive and short wave reception of Radio Australia or BBC had to be used to keep up with current events. In Darwin I had the pleasure of meeting the local VK8's at their club rooms in the emergency centre concrete block-house.

Many relics and reminders of war-time Darwin are to be found, including along the Stuart Highway, the landing strips adjacent to the road. A visit along the Arnhem Highway was worthwhile as we

were able to view some of the water buffalo and at Humpty Doo to see the many variety of water birds that caused the ultimate failure of the dream to grow crops of rice.

On the run south it was good to camp at Mataranka Homestead, to swim in the hot spring and later to see the grave sites of the Eley Station characters of "We of the Never Never". A little further south, after Daly Waters, we stopped at the monument to commemorate the valiant efforts of Sir Charles Todd and his co-workers in building the overland telegraph line a century ago. What privations these teams went through just to get a single wire from Port Augusta to Darwin. In modern times, here we were in a mobile home with the ability to make radio contact easily all around Australia and with a little more effort to many parts of the world. In fact, the Stuart Highway has many points of interest communication wise as it virtually follows the route of the telegraph line and place names are synonymous with the telegraph relay stations. At these places operators received and transmitted the messages along the line.

The overland telegraph line, completed in 1872, followed the route pioneered 10 years earlier in 1862 by John McDouall Stuart who, under heroic conditions, trekked through the unknown centre from Adelaide to what is now Darwin. A monument to him may be seen in the streets of Darwin.

At Alice Springs the original telegraph station and the Springs in the Todd River are being developed as a museum and recreational area. To be seen also by the observant travellers are many sections still in use of the 6,000 Oppenheimers iron poles installed in 1873 to combat the hungry jaws of termites. These ate away the wooden poles soon after their installation.

In a later era, the 1920-30s, reminders past and present are very much in evidence of the work of another pioneer. I refer to the Rev. John Flynn — "Flynny of the Inland". A monument to his memory is to be seen at Three Ways, north of Tennant Creek. At Alice Springs is the Flynn Memorial Church and a few kilometres to the west of town his grave site surmounted by one of the "Devil's Marbles" is in an appropriate setting. A living memory to him is the network of 13 Royal Flying Doctor radio bases spread around Australia, in many cases staffed by active radio amateurs. We were able to visit 8 of these during the tour.

It was a pleasure to meet the local Alice Springs VK8's at their club and to get a lot of helpful clues on seeing the area and on negotiating the "Track" down south.

The Stuart Highway from Alice to the S.A. border is an excellent road, however, the road west of Ayers Rock, particularly from Curtin Springs Homestead to Ayers Rock, and the Olgas, would be just about the worst and most used road in Australia. Thousands of tourists are inflicted with a corrugated unstabilised red sand road which no manner of grading will improve.



John G8LIF, Peter G3WCJ, Arthur VK2IK, Jack VK6EJ, Geraldton, W.A.

Buts, cars and caravans all suffer alike, and quite a few breakdowns were encountered. The Rock and the Olgas were all that the brochures showed, especially the sunrise and sunset scenes.

On now into South Australia after over-nighting at Kulgera. What a road! Corrugations, bulldust and holes. Sure the road is wide enough and clearly defined but the hazards are difficult to avoid. The only way is to drive with extreme caution. We found that by reducing tyre pressure and not exceeding 60 km per hour that we came through unscathed. Not so cautious were others who evidently taking it too fast produced the hexagonal and octagonal wheels which littered the highway. Unluckily also was the semi-trailer driver from Adelaide who piled up near Maria Bore, 300 km north of Coober Pedy. His fuel tank had fatigued off the chassis and fell under the wheels. After a couple of days at the crash site we resumed the journey to Coober Pedy, a most interesting spot and, after Woomera, a more or less normal journey home via Adelaide and Broken Hill. Queensland was not included in our itinerary as we had previously toured up the east coast of Australia as far as Cairns.

WARNING FOR TRAVELLERS

Several comments are worth noting for future travellers. Bob VK6CJ, of Carnarvon, an owner-driver of a road train, warned us! Give the trains a wide berth and priority on one track roads, as a foot of movement of the prime mover will cause a 4 ft. waggle to the tail of the third trailer! It tests the nerves and skill to pass these going in opposite directions, especially on a curve and you DON'T pass them except uphill going the same way.

Animals on the road are a frequent hazard, especially at night and must be given credit for being unpredictable. The main problems are kangaroos, emus, cattle and sheep in about that order. Fortunately we missed them all, but there were some

narrow shaves. Although we didn't fit bull-bars, these could be an advantage. We did, however fit a windscreens mesh which saved the screen several times.

In planning a trip such as ours, it is more economical to travel anticlockwise around Australia as this is the direction of prevailing winds. For timing reasons we were committed for clockwise travel which made our fuel costs higher than it would have been. ■

QSP

CASUALTY

In mid-April 1977 Dr. Glen Eschtruth, 9G5GE/KBMZG was murdered in the Kapanga area of Zaire by the invaders into the southern part of that country. From a report in Worldradio Aug. 77.

MARCONI 75th ANNIVERSARY STATION

From ARRL comes the news of a special event station KM1CIC from 14th to 22nd January operative on all bands and modes from the original Marconi station location in South Wellfleet, Mass. Another special station to be operated by RSGB will be located at Poldu, England, during the same period. QSL to KM1CIC via WIGAY.

NETHERLANDS CONTROLS

Radio Communication Nov. 77 quotes an extract from a notice issued by the Radio Central Service of the Netherlands P. and T. Service which basically advises that as a licence is required for all radio transmitting equipment a new registration system now operates from 1.7.1977. A personal registration certificate is required to be kept with the station and all transmitters, transceivers, transverters and linear amplifiers must have a registration sticker attached to them. This new system forms part of the licence conditions. The police can seize any unregistered equipment.

FAX

The UK permits the use of facsimile signals on 7, 14, 21, 28 and 144 MHz bands. Radio Communications Nov. 77 says the interest in this mode of picture transmission is increasing and BARTG would like to hear from anybody using it.

EME

"The WAC Certificate has been received to confirm that VK2AMW has Worked All Countries on the 70 cm band. Without a doubt the first WAC on UHF (or VHF for that matter) for any station in this part of the world". The Illawarra "Propagator" for Nov. 77.



EMONA electronics

CBC BANK BUILDING, HAYMARKET PHONE: 212 4815
Room 208/661 GEORGE STREET, SYDNEY. AH: 398 6378

MAIL ORDERS: Box K21, Haymarket
NSW, 2000, Australia

WRITE, PHONE OR CALL IN!

NEW-NEW-NEW

National **RJX SERIES**



RJX-S1011

RJX-1011

RJX-V1011

ALSO AVAILABLE: • MIZUHO BCL antenna tuners, preselectors, marker generators • KATSUMI electronic keyers • SENCOR DVM • DRAKE TVI filters • OSKERBLOCK SWR-200 & SWR-300 meters.



ORDER YOUR ROBOT MODEL 400 SSTV CONVERTER NOW!

With the Robot 400 you just plug it into your transceiver, connect a TV monitor or your home set with the optional Robot RF adapter kit, tune to 14.230, and you're operating SSTV.

Go RTTY — EMONA's silent way!




New Model 150 RTTY KEYBOARD

Features:
4 speeds (60, 66, 75, 100 wpm)
Built-in AFSK with 3 shifts (170, 425, 850 Hz)
Automatic CR & LF at end of 64 or 72 character line
Built-in low shift CW ID provision

New Model 75 RTTY TO VIDEO CONVERTER

Features:
4 speeds (60, 66, 75, 100 wpm)
Built-in T.U. with 3 shifts (170, 425, 850 Hz)
32 character x 16 line video output with scrolling
Connects directly to receiver audio & video monitor



NEW Model DX-555 Counter-Generator

Generator:
440 kHz to 30 MHz in 3 ranges.
Output displayed on counter and available at jack on rear panel 600 Hz modulation for AM receivers.

Counter:
5 digit display, 7 digit readout capability, 10 Hz to over 30 MHz (250 MHz with prescaler). Input level 20m Vrms to 5 Vrms (Prescaler 200m Vrms to 2 Vrms). Base oscillator beats directly against WWV.

NEW COUNTER-GENERATOR

Two vital pieces of test equipment in one.



NEW: Medium-Sized Ham Antenna Rotor — FU 400.

Constructed for long trouble-free operation. 200 kg vertical weight capacity. Extra heavy duty disc brake that prevents wind-milling.

A Unique New SSB/CW Transceiver For Amateur Communications

There is no substitute for quality, performance, or the satisfaction of owning the very best. Hence, the incomparable National RJX-1011 amateur transceiver. The RJX-1011 covers all amateur bands 1.5-30 MHz (160-10 metres). It utilizes advanced Phase-Lock-Loop circuitry with dual gate MOS FETs at all critical RF amplifier and mixer stages. There's a rotating dial for easy band-scanning and an electronic frequency counter with digital readout and a memory display that remembers frequencies at the flip of a switch. And that's just the beginning. Matching speaker unit RJX-S1011 and complete external VFO RJX-V1011 also available.

For further information and specifications write, phone or call in!

LINEAR AMPLIFIERS

SCS: HF3-100L2, 3-30 MHz bi-linear amplifier.

SCS: 2M10-80L2, 144-148 MHz, FM/SSB linear amplifier.

METRON: 1K1000, all solid state, 1 kW amateur band linear amplifier — lightweight, compact and rugged.

YAESU MUSEN: FL-2100B, 80-10m linear amplifier.

ANTENNAS:

HUSTLER: 4-BTV — vertical trap antenna.

HUSTLER: Mobile vertical trap antenna (80-10m).

CUSHCRAFT: ATB-34, 4 element beam, 10-15-20m

WILSON'S SYSTEM ONE: TRIBAND ANTENNA — A DXer's delight, operating 20 m on a full 26 ft. boom with 4 elements on 20-15, and 5 elements on 10. Gain 10 dB!

RF PREAMPLIFIERS FOR 3-30 MHz BAND:

Model SX-59 for use with transceivers.

SPECIFICATIONS:

Frequency range 3-30 MHz in 3 bands;

3-7, 7-14, 14-30 MHz

Gain 20 dB nom. (at 7 MHz), front

panel variable control

Attenuator — 20 dB attenuation select-

able from front panel control.

Imped. 50 or 70 ohm systems, UHF connectors on rear panel.

Switching requirements: requires external relay contact switching when used with transceivers. Remote contacts readily available from most amateur HF transceivers, including TS-510, TS-511, TS-520, TS-820, FT-101, FT-401, FT-200 and FT-201.



AMATEUR BAND TRANSCEIVERS:

NEW — NATIONAL: RJX1011 — Unique SSB/CW 160-10m transceiver with digital readout and matching speaker and external VFO.

TRIO KENWOOD: TS520S — SSB/CW, 160-10 metres, with optional digital readout.

TRIO KENWOOD: TS820S, 160-10 metres digital readout.

TRIO KENWOOD: TS820, 160-10 metres.

TRIO KENWOOD: TS700A — 144-148 MHz all mode transceiver.

TRIO KENWOOD: TS600A — 50-54 MHz all mode transceiver.

TRIO KENWOOD: TR-7400A — 144-148 MHz FM transceiver.

YAESU MUSEN: FT101E — 160-10 metres, AM, SSB, CW transceiver.

YAESU MUSEN: FT301 series, 160-10m AM, SSB, CW transceiver.

RECEIVERS:



DRAKE: SSR-1 Wadley Loop receiver.

TRIO KENWOOD: R300 general coverage BCL receiver.

YAESU MUSEN: FRG-7 general coverage

age Rx, Wadley Loop System.

NATIONAL: DR48 (RF4800) — general coverage, digital dial, communications and BCL receiver.

ALL AMATEUR RADIO EQUIPMENT IS AVAILABLE ON
10% DEPOSIT TO APPROVED BUYERS!

Check EMONA'S most COMPETITIVE Prices!



EMONA electronics

CBC BANK BUILDING, HAYMARKET PHONE: 212 4815
Room 208/661 GEORGE STREET, A.H.: 399 9061
SYDNEY, NSW 398 6378

MAIL ORDERS: Box K21, Haymarket
NSW, 2000, Australia

WRITE, PHONE OR CALL IN!

FROM **FDK** OF JAPAN COMES THE LATEST MILITARY TECHNOLOGY AT AMATEUR PRICES, THE

Bigear VHF-UHF TRANSCEIVERS!

Type 1 —

2m FM SSB CW PLL SYNTHESIZED MOBILE BASE TRANSCEIVER

- 144 - 148 MHz, PLL digital synthesizer system
FM: 800 channels (5 kHz step)
SSB: 400 channels (10 kHz step) plus VXO system (± 7 kHz)
- AC 117/240V, DC 13.8V, two-step power supply
- Digital display system (using a large-sized LED) provides reading up to six figures

Type 2 — 2m FM PLL SYNTHESIZED MOBILE TRANSCEIVER

- 144 - 148 MHz, PLL digital synthesizer system (800 channels)
- A large-sized LED, digital display system provides readings up to six figures
- Easy-operating separate and selective mechanism displayed by the frequency unit for wider operation
- Transmitting output: 25W/1W, two-step selector switch



WRITE OR CALL FOR FURTHER SPECS!



LUNAR 2 METRE LINEAR AMPLIFIER - 2M80P

- 10W Input — 80W Output nom.
- Low Power Input Yields nom. 10 dB gain
- Covers entire Amateur Band w/o Tuning
- Built-in Receive Preamplifier
- Automatic T-R Switching or Hard Keying
- Remote Control Head Avail. Separately
- Exceeds FCC R&O 20777 Requirements of —60 dB
- Variable T-R Delay for SSB/CW use
- Preamp & Power Amp Independently Controllable
- Preamp nom. 11 dB gain 2½ dB Overall NF
- Functionally Designed Package

Models available for the 148-174 MHz bands



LUNAR PREAMPS

Originally developed by Chip Angle, the Angle-linear receiving preamplifiers meet the most demanding needs where low noise is important.

VHF ANTENNAS:

- HUSTLER: G6-144A, 6 dB gain base colinear.
HUSTLER: CGT-144, 5.2 dB gain mobile colinear trunk-lip mt.
HUSTLER: BBLT-144, 5/8 mobile with trunk lip mount/spring
CUSHCRAFT: RINGO ARX-2
CUSHCRAFT: A147-20T, 20 element twist.
CUSHCRAFT: A144-11 11 element

OSKERBLOCK SWR-300

UNIVERSAL SWR
METER FOR HF,
VHF and UHF!

INTRODUCING *Dentron*

LINEAR AMPLIFIERS:

- DENTRON RADIO CO.: MLA-2500, 160-10m linear amplifier.
DENTRON RADIO CO.: MLA-1200 — 80-10m linear amplifier.
DENTRON RADIO: 160-10L Superamp, 160-10m linear amplifier.

ANTENNA TUNERS:

- DENTRON MT-3000A DENTRON 160-10AT DENTRON 80-10AT

The MT-2000A

The Dentron MT-2000A antenna tuner, an economical full power tuner designed to handle virtually any type of antenna, whether it be a vertical, beam, quad, dipole, or long wire. The sleek styling and low profile of the MT-2000A is certainly beautiful, but be assured that isn't all you're buying. The MT-2000A is designed and engineered using heavy duty all-metal cabinetry and high quality American components throughout. When you consider the MT-2000A's unique features — front panel coax bypass switching, front panel lighting protection antenna grounding switch, 3 kW PEP handling capability and built-in 3 core balun for balanced feed line, we're sure you'll decide to buy American and stay with Dentron.



The Jr. MONITOR

Call it what you will — antenna tuner, transmatch, match-box, or matching network, the JR. MONITOR has it all wrapped up in one neat 3½ in. w. x 2½ in. h. x 6 in. d. all metal cabinet. Think of the unlimited possibilities you'll have for experimenting with dozens of antennas! For instance, the Dentron All Band Doublet fed with balanced feed line hooked to the JR. MONITOR covers 1.8-30 MHz... or try this mobile suggestion: 108 in. mobile whip fed with coax to the JR. MONITOR located under the dash will give you 10-40 mile mobile coverage and no coils to change! Order Today.



DENTRON MLA-2500

Dentron Radio has packed all the features a linear amplifier should have into their new MLA-2500. Any Ham who works it can tell you the MLA-2500 really was built to make amateur radio more fun.

DENTRON ANTENNAS:

- SKYMASTER — 10, 15, 20, 40m VERTICAL.
SKYCLAW — TUNEABLE MONO BAND 160-40m
EX-1 IDEAL VERTICAL FOR PHASING.

- WRITE OR CALL FOR SPECIFICATIONS.
- CHECK OUR MOST SENSIBLE PRICES.

**WE ARE AUSTRALIA-WIDE
DISTRIBUTORS OF
DENTRON PRODUCTS**

CHIRNSIDE ELECTRONICS

DIRECTOR: FRED SWART - VK3NBI For personal attention.

Featuring Yaesu Muse FT-7
Mini Mobile Transceiver as well as ideal
Noise Transceiver.
80-10 Metre operation. VFO controlled
20 Watt DC input. Noise blanker and
facilities for fixed channel operation.

OUR PRICE: \$560

YAESU



Complete with
mic, mobile mount and cables.

FT-101E

Complete AC-DC Transceiver with
Built-in RF processor. The rig comes
complete with mic and cables.
200 PEP SSB, 150 Watt CW, and 80
Watt AM plus lots of other features.

OUR PRICE: \$876



FT-901DM

This rig has absolutely everything.
Just what you always wanted and more.

Ring or write for brochure.

OUR PRICE: \$1499



YO-100
Matching monitor scope
for FT-101E as well as
other equipment

OUR PRICE: \$279

FT-301S

Ideal Novice Transceiver.
20 watt DC input. All solid state. All modes
SSB, CW, AM, and FSK.



OUR PRICE: \$749

(Includes AM board and VOX Cal. board).

DON'T BE TRAPPED WITHOUT THESE
EXTRAS.



MATCHING POWER SUPPLY

FP-301 - PRICE \$179

DEALER ENQUIRIES WELCOME

FL-2100B

1200 watt Linear Amplifier.
You too can get to the legal limit for only
\$548. The FL-2100B operates on 80 thru
10 Meters with dual cooling fan.

OUR PRICE: \$558



FRG-7

General Coverage Communications Receiver
from 5 MHz to 30 MHz.
Uses Wadley Loop System (drift cancellation
circuit).
Guarantees excellent stability.

OUR PRICE: \$338



\$49

YD-844

YO-301

Matching monitor scope for 301 series.
OUR PRICE: \$379



Country clients especially welcome.
Enquire about our free freight plan
on certain items.



FT-301D Deluxe digital transceiver.
OUR PRICE: \$1225

FT-301 Fully solid state transceiver
200 watt PEP input.
OUR PRICE: \$1039



YP-150

Dummy Load Watt Meter.
OUR PRICE: \$108



APPOINTED YAESU DISTRIBUTOR.
(INTRODUCTORY PRICES ONLY)



All prices include Sales Tax. Freight and Insurance extra.
Prices and specifications are subject to change without notice.

CHIRNSIDE ELECTRONICS. 26 Edwards Road, Lilydale, 3140. Phone: (03) 726 7553.

ALL SETS COME WITH ENGLISH INSTRUCTION MANUALS AND SPARE PARTS BACK-UP SERVICE.
90 day limited warranty on all equipment excluding final tubes or semiconductor.
OPEN ON SATURDAYS TILL 12 NOON



AMATEUR RADIO CENTER

23 WHITING STREET, ARTARMON, NSW 2064

TELEPHONE: (02) 439 1271



- Q.: THINK YOU WERE SUCCESSFUL IN THE LAST EXAM?
Q.: HAVING PROBLEMS TRANSLATING THEORY INTO PRACTICE?
Q.: CONFUSED BY THE CLAIMS OF MANUFACTURERS?

THEN COME AND TALK TO US!

We have a wide range of radio equipment suitable for your operating requirements. We have the know-how to assist you in setting up a new station or upgrading your existing equipment whether you QTH is: A CITY FLAT — A SUB-URBAN HOME — ACRES OF COUNTRY SPACE.
Whatever your lifestyle, you can enjoy ham radio.

SPECIAL — POWER SUPPLIES

138/3	3A	13.8V	Reg. Supply	P.O.A.
138/5	5A	13.8V	Reg. Supply	\$55.00
138/10	10A	13.8V	Reg. Supply	P.O.A.
138/20	20A	13.8V	Reg. Supply	P.O.A.

These power supplies are ruggedly designed for Australian conditions. All ratings are continuous. Filtering is through computer grade capacitors.
WE ALSO MANUFACTURE TO YOUR SPECIFICATIONS.

GILCO AMATEUR RADIO CENTER

23 WHITING STREET, ARTARMON, N.S.W. 2064

Prop.: JACK GILLHAM VK2DG

SOCIAL RESPONSIBILITY: We reserve the right to refuse sale of transmitting equipment to unqualified persons.

YAESU



hy-gain
ANTENNAS



Two years ago, after more than a dozen years of retail selling of amateur equipment, I decided it was time to retire from a seven days a week - 52 weeks a year activity and gave, free of charge, my retail business away while continuing, in a more leisurely manner, to import the same merchandise and sell it on a wholesale basis.

Recent developments, affecting profit margins and other aspects of the business, have made me decide to return to retail sales. Business is invited on my same old basis of cash with orders at the best prices obtainable elsewhere. There is plenty of stock available.

Antenna rotators will be sold only for 28V AC operation to defeat a threatening colossal overhead due to action of the Electricity Authority of N.S.W. There are laws that require all devices, producing what they call Extra-Low Voltage from 240V AC, including rotator control/indicator boxes, to be submitted for approval by the Authority. There is nothing wrong with that; users have to be protected against substandard and sometimes lethal equipment. But the outrageous charges for testing fees, which can be repeated if equipment does not meet some exaggerated standards, can easily be \$1,000.- or more for a simple rotator control box. The fee for an appliance plug with moulded cord, for instance, is \$510.-!!! For sales of a few dozen rotators of one type, this would increase the cost to the consumer to such a degree that it is better to eliminate the 240V AC supply and feed them with 28V AC from sources easily available in most ham stations.

Sorry, no HY-GAIN antennas available anymore. Hy-GAIN went bankrupt early this year and their factory is closed by the banks there, waiting for a 25 million dollar buyer for the lot! I have had a visit from Mike Jtaal, manager of KLM ELECTRONICS, makers of famous mono-band beams, and they will soon let me know what they can produce to fill the gap created by the disappearance of HY-GAIN beams from the market.

KENWOOD TS-520S 10-160M SSB/CW transceivers	\$650.-
KENWOOD TS-820S 10-160M SSB/CW transceivers w/inbuilt digital readout	\$1,000.-
KENWOOD DG-5 digital display unit for TS-520S	\$175.-
KENWOOD TR-7400A 2M 25W FM 12V DC transceivers	\$400.-
KENWOOD TV-506 6M transverter	\$175.-

YAESU MUSEN FRG-7 all band Wadley loop receivers	\$300.-
Other Yaesu Musen products on order.	

FDK MULTI-800D PLL 800 channels 2M transceivers in 5KHz steps	
12V DC 1-25W adjustable output with digital readout	\$325.-

FDK DD-800 bright remote digital display for the 800D for mobile use	\$40.-
--	--------

FDK QUARTZ 16 24 channel 10W 12V DC 2M transceivers with crystals	
for repeaters 1 to 8 incl. and channels 40 & 50	\$175.-

ICOM IC-202 2M SSB portable transceivers - a few left only for	\$175.-
--	---------

KEN KR-400 antenna rotators with 28V AC control/indicator box	\$100.-
---	---------

KEN KR-500 same as KR-400 for vertical plane beam rotation	\$125.-
--	---------

Amphenol type coax connectors, many types: PL-259 large or small,

for RG-8U or RG-58U, SO-239 all 75¢ each.

Right angle and T-connectors \$1.50 each.

ATTENTION NOVICE LICENCEES: 24 channels 5KHz apart, 28.480 to 28.595

AM/USB transceivers, 10W PEP with clarifier on receive and transmit,

virtually continuous coverage of the 10M DX band portion 12V DC \$150.-

The above prices are on a cash with order basis, subject to change without prior notice; remember our dollar's value is going down almost by the week, now only worth 60% of what it was 3½ years ago against the Japanese Yen on the Tokyo market!!!

Airfreight, rail- or road-transport charges are extra, full risk insurance is free.

Arie Bles, VK2AVA, proprietor

Roy Lopez, VK2BRL, manager

THE MAN BEHIND THE MICROPHONE

As the front cover shows, Jim Davis VK7NOW, has one of the best looking amateur stations in Australia. The equipment line-up includes Kenwood TS520S, Yaesu FT101E, FT200, FT75B, Icom IC22A, six antennas, including an 80m inverted V and a tri-band HF beam. Any of five HF antennas can be selected by coaxial switch.

Jim, 65 and now retired (?), was first interested in radio in the 1920s but only took up the hobby seriously four years ago. He has fitted the shack with acoustic tiles on the ceiling, air-conditioning in the wall and carpet on the floor. Both cassette and open reel tape record/playback facilities are available for any QSO. A 60 watt hi fi amplifier with two five cubic ft enclosures is used for better audio when warranted.

Not only does the equipment look attractive, it is used efficiently by the owner. Jim was the top Novice scorer in the phone section of the 1977 RD contest. This was his first attempt so watch out this year!

Jim is an enthusiastic exponent of the use and virtues of RF clipping, especially for the ORP operator.

An October issue of "The Advocate" carried an article by Burnie journalist and CB operator Mike Lawson. This described a visit to Jim's shack and gave a fine explanation of amateur radio and where and how to get a licence. A considerable volume of CBers have seen Jim in action at the console and a dozen are reported to be so impressed that they are now studying for their Novice licence.

What next? Well the console is being enlarged to accommodate a new Robot 400 scan converter and sundry SSTV gear. Give Jim a call and find out what else is in that expanding console.

Short contributions with a photograph are invited for this segment.—Ed. ■

RAOTC DINNER 1978

Bob Cunningham VK3ML

The Radio Amateur Old Timers' Club of Australia has now reached a membership of 200. In addition to VK members the club enyoys membership from USA, Great Britain and Holland, etc.

The Annual Dinner of the club was staged at the Sciences Club, Clunies Ross House, 191 Royal Parade, Parkville, Melbourne, on Thursday, 5th May. A record number of members turned up for this function, amounting to just on 100. In the chair was Dr. Bill Bulement VK3AD. It was very pleasing to note those attending, including quite a number of VK2 members, in addition to an amateur from the Netherlands PA0ALO.

The Master of Ceremonies for the evening was Max Hull VK3ZS, who carried out his duties in a truly professional fashion and was able to keep the function going at a high level of activity.

Letters were read conveying wishes for the success of the dinner from a similar Old Timers' Club in the Netherlands and from the Old Timers' Club of New Zealand. The guest speaker for the evening was Bill Jenvy VK2ZO, a retired officer from the Overseas Telecommunications Commission. It was Bill's father, Walter Jenvy, who was Chief Electrical Engineer to the Victorian Post Office in 1901, and who was at that time operating his own experimental wireless station at Red Bluff, near Elwood, under the call sign of BJ. Walter was questioned by the Victorian Government to establish the station at Queenscliff for the purpose of transmitting a welcoming message to the then Duke of York on board the s.s. "Ophir" as it approached and entered Port Phillip Bay. The Melbourne "Argus" newspaper published a report on April 11th, 1901, on the feasibility tests carried out by Walter Jenvy prior to the actual event. As it finally transpired s.s. "Ophir" did not carry a wireless but the escort cruiser H.M.S. "St. George" did and two-way communication with Queenscliff and later Red Bluff was carried out over a distance of up to 30 miles.

To support his remarks, Bill Jenvy arranged with the Sciences Museum in Melbourne to make available the Morse Code transcriptions as they occurred on this occasion together with a coherent set of parts of the equipment used in those days. We are indebted to the Museum for this loan.

Later in the evening PA0ALO was asked to address the members in which he included an invitation to any member visiting the Netherlands to contact their kindred association for hospitality which he felt sure would be warmly provided.

At the conclusion of the dinner, it was moved by Bob Anderson VK3WY that the current President and Committee be re-elected for the coming year. The President, Bill Bulement, wished to nominate Bob Cunningham VK3ML as a Patron to the club in recognition of his services in being the founder of the RAOTC. Both these motions were carried with acclamation.

It is anticipated that the Sixth Annual Dinner will be held in the same location at about the same time in 1979. All members were requested to make every endeavour to increase the membership of the club, which is open to any amateur in any part of the world who has held an Amateur Operator's Licence for 25 years. The Membership Secretary of RAOTC is Harry Cliff VK3HC, whose address is Box 50, Point Lonsdale, Victoria. ■

QSP

Applications are now being received from responsible CBers living within the Maroonah district.


All applicants will be screened through Police Headquarters and a yearly subscription of \$15 will be payable on acceptance into PACER. Insurance cover is included in the subscription.

APPLICATION FORMS ARE NOW AVAILABLE AT THE ENQUIRIES DESK AT POLICE DISTRICT HEADQUARTERS IN NUNAWADING (OPEN 24 HOURS).

Applicants should be a minimum age of 21.

IONOSPHERIC PREDICTIONS

Len Poynter VK3ZGP/NAC



LEGEND
 FROM WESTERN AUSTRALIA
 FROM EASTERN AUSTRALIA
 BETTER THAN 50% OF THE MONTH, BUT NOT EVERYDAY
 LESS THAN 50% OF THE MONTH
 ALL TIMES UNIVERSAL UTC (GMT).

PREDICTIONS COURTESY IPS, SYDNEY

VHF-UHF AN EXPANDING WORLD

Eric Jamieson, VK5LP
Forreston, 2233

AMATEUR BAND BEACONS

VK0	VK0MA, Mawson	53.100
VK1	VK1RTA, Canberra	144.475
VK2	VK2W1, Sydney	52.450
	VK2W1, Sydney	144.010
VK3	VK2RHR, Mittagong	144.120
VK4	VK4RTL, Townsville	144.700
VK5	VK5RRT, Mt. Newbould	52.440
	VK5RBB, Brisbane	144.480
	VK5VF, Mount Lofty	53.300
	VK5VF, Mount Lofty	144.800
VK6	VK6RTV, Perth	52.300
	VK6RTV, Kalgoorlie	52.500
	VK6RTV, Albany	52.950
	VK6RTV, Albany	144.500
	VK6RTV, Perth	145.000
VK7	VK7RNT, Launceston	52.400
	VK7RXT, Ulverstone *	144.900
	VK7RXT, Ulverstone *	144.975
VK8	VK8VF, Darwin	52.200
JA	JAZQV, Nagasaki	52.500
KG6	KG6JDX, Guam	50.110
KH6	KH6QJ, Hawaii	50.110
ZL1	ZL1VHF, Auckland	145.100
	ZL1VHF, Waikato	145.150
ZL2	ZL2MHF, Upper Hutt	28.170
	ZL2VHF, Palmerston North	52.500
	ZL2VHF, Wellington	145.200
	ZL2VHF, Palmerston North	145.250
ZL3	ZL3VHF, Christchurch	145.300
ZL4	ZL4VHF, Dunedin	145.400

* Re-entered on listing.

† Note frequency change.

Tony VK7AX writes to confirm the installation and operation of the new VK7 beacons on 144.900 and 144.975 MHz from Ulverstone, and these are listed herewith. As reported last month, Dave VK5SK had already reported hearing these beacons on 28/2 so now we have the final confirmation.

Also noted in the beacon listings this month is a change to the frequency of operation of KHEQEI to 50.110 — the operator of this beacon listens from time to time on 50.104 — if you are hearing this beacon listen carefully and you will find at times the call changes from VVV de KHEQEI to CQ CQ CQ de KHEQEI — that's the a to give a call on 50.104 MHz! Of course you VK readers wouldn't do that, would you?

VHF DX FROM DARWIN

Gram HXKGB has forwarded three letters full of interesting information this month, and the following extracts will be of interest to you.

Gram has sent me a copy of the QSL received from Tell JHTEW for the first VK-JA 14.4 MHz contact on 24-7-78 (reported last month) and Tell runs 20 watts input from a TS700G2 to a pair of 10 element crossed yagis 15m high. He is 15 years old, so what a thrill for such a young operator.

Now let us have a look at what March produced for Gram.

"Saturday, 4-3-78: 0507Z KH6H1 5 x 6 to 5 x 9 +20, 50.103 to 52.103 split frequency working. 1118Z to 1355Z: JA1, 2, 3, 4, 5, 6, 9 and 0 for 19 stations worked. Also 1145 to 1415Z worked KG6JH, KG6JDX and KG6DX. At 1226Z worked JHTEW on 14.4110 at 4 x 1/5 x 2. The KH6 opening was for about an hour. KH6IA was also heard and the beacon KHEQEI was 30 dB over 9 at times. I also heard the KH6s working VK4MS, VK4RO, VK4TL and VK6VV. The guys in KG6 worked into VK4 and VK6ZFQ in the evening for the first time. P29 was worked in Japan in the evening as was VK6Z.

"Sunday, 5-3-78: 1200 to 1343Z to JA only on 6 metres, 26 stations worked from JA1 to 6 inclusive plus JAB8. No signals on 2 metres.

"Monday, 6-3-78: 1026 to 1415Z six metres worked JA1 to 7 plus JA9 with 43 contacts

altogether. 1250 to 1415Z worked KG6JH, KG6JDX and KG6DX, all 5 x 8. The six metre openings were widespread, JA to VK4, VK6, VK8, P29, KG6 to the same areas. On 14.4110 at 1054Z worked JH400K 4 x 3/4 x 1; 1115Z JH6BVG 5 x 6/5 x 9; and 1145Z JH6SFL 5 x 1/5 x 5.

"Tuesday, 7-3-78: 1035 to 1337Z on 6 metres worked 21 stations in JA1, JA2, JA4, JA5 and JH6 areas. 1322 to 1342Z worked KG6JH, KG6DX. On 14.4110 at 1142Z worked JH6TW 5 x 1/5 x 1; 1151 JH8AYU 1/5 x 3/5 x 3; 1159 worked JH6FWK 5 x 3/5 x 3. Again we had widespread six metre opening. JA to P29, VK4, VK6 and VK8. KG6 to VK4, VK8 and VK8.

"Wednesday, 8-3-78: I was QRT for most of the evening but Brian VK8VV worked the following on six metres: JA4H1, JA4SDY, JA4EPN, JA4FB1, JH4XTN, JH6RGP, JH6TGD, JH6BEN. Signals were up to 57. On six metres 1230Z worked JA2BZY, JA1RUJ, JH6TEW, KG6JH, KG6 JDX and KG6DZ. At 1233Z HLWRI broke into the group and both Brian VK8VV and myself worked him. He is now listening nightly for us on 2 metres! 1335Z JA3ET1, 1339 JA2FOX and 1342Z JH4XU1 on six metres. JAs worked VK2, 3, 4, 6 and 8 and P29 today.

"Thursday, 9-3-78: 1210Z to 1311Z on 6 metres worked JH6TEW, JA3ET1, JG1VCZ and JH1AUW. On 14.4110 at 1218 worked JA6CL 5 x 3/4 x 1; at 1225 worked JH6IFF 5 x 4/5 x 1. Brian was QRT this night until 1440Z when he worked KG6JH on 6 at 5 x 9+.

"Friday, 10-3-78: Brian VK8VV worked Cliff KH6SJ1 1500Z, 0532Z on 5 x 9 and signals were all over the place. On 6 metres signals were fading and very scratchy. Cliff worked 3D3CM on six on 9-3-78 which confirms activity in Fiji. On six metres 1120 to 1255Z worked JA2, JA3, JA4 and JH6 for 7 contacts. On 14.4110 at 1142Z worked JA6QFH 5 x 5/5 x 2; and worked him again at 1220Z 4 x 1/4 x 1. JAs worked VK4s at 6520Z on six metres.

"Saturday, 11-3-78: I was QRT until 1240Z. Brian VK8VV worked 16 JAs on two metres between 1100 and 1215Z. 5 x 9 reports were common, call areas JA4 and JA6 only. At 1240Z I worked KG6JH, KG6JDX and KG6DX all at 5 x 9. Joe KG6JDX runs about 200 watts on 6 metres. This is definitely looking for contacts. Gerry KG6JH reported solar flux figures as follows: 9-3-78 186; 10-3-78 180. These are very high.

"Sunday, 12-3-78: At 1033Z JAs contacted on six metres. QSY to 2 metres at 1050Z, at 1100Z JAs broke VK8VV and myself with a 5 x 9 dopple! Brian worked 13 stations on 2 metres and I worked 22 stations in the JA4, JA5 and JA6 call areas between 1100 and 1208Z, signals 5 x 9 both ways! I am not using my receive as it has a bit of insertion loss on receive, is a bit inconvenient to operate and all the JAs run 20 watts PEP anyway. My equipment for all these contacts has simply been FT101E, FT700 transverter, 10 m. yagi. On six metres I worked 2 metre episode worked JA1 to 4, JA5 and JA9 for 15 contacts, 1300Z worked G6JH, KG6JDX and KG6DX. At 1320Z worked Richie VK4RR at Mackay on backscatter 5 x 3/4 x 1. The JAs were working as far south as Rockhampton in the evening and the KG6s worked many VKs. There was a brief afternoon opening to VK4AO too.

"Monday, 13-3-78: 1102Z KG6JH; 1150Z JH6TEW; 1155Z VK4IKY/KG6; 1158Z KG6JDX. A quiet day.

"Tuesday, 14-3-78: Again on six metres, 1155Z JH6TEW ad- at 1220Z JA2BEY . . . and now the scenario pauses for a lunch break until . . .

"Friday, 17-3-78: On six metres 1105 to 1300Z 12 contacts to JA1, 2, 3, 4, 6 and 8.

"Saturday, 18-3-78: Six metres 1945 to 1402Z JA1, 2, 3, 4, 6, 7, 9, 6, plus HLWRI and KG6DX, for a total of 21 stations. On 14.4110 worked 1128 and 1137Z JH6FWK 5 x 4, JA6DZ 5 x 2, JA6BCW 5 x 4, JH3BZK 5 x 6, JR6DQO 5 x 1, JH6TEW 5 x 2 and JR6JH1 5 x 3.

"Sunday, 19-3-78: 0325 to 0354Z KHEQEI 5 x 9, KH6H1 5 x 9, KH6J51 5 x 8, KH6J1 5 x 7 and KH6IAA 5 x 7. Between 1127 and 1353 worked JA4s and KG6 in the call areas JA1 to 7 plus JA9 and JA9. These on six metres. Between 1128 and 1232Z worked JH6JH1, JH4DOR, JHTEW, JH6AWT, JR6DPU and JA6QFH on two metres.

"Monday, 20-3-78: 1252 to 1259Z JH6TEW, JA1RUJ and KG6JDX on six metres. On two metres worked a total of 30 stations in the call areas of JA4, JA6, JH6 and JH6. JH5GUE: I gave him 5 x 9 + 10, he gave me 5 x 9 + 20 dB!

"Wednesday, 22-3-78: 1020 to 1245Z four JA stations plus KG6JH. Quiet day!

"Thursday, 23-3-78: JA1, 2, 4, 5, 6 plus KG6JH for 12 stations on six metres. On 14.4110 between 1149 and 1312Z worked 27 stations in the call areas JA4, JA4, JA5, JA6, JH6 and JH6. JA5UXF was operating 1/6 so it is not really any change in call areas from 4 and 6 as previously worked.

"Friday, 24-3-78: On six metres between 0400 and 0420Z worked WA8UW/KH6 and KH6J51. Between 1021 and 1402Z worked 29 stations in JA1 to 6, JA10, KG6JH and KG6DX. On 2 metres between 1037 and 1224Z worked a total of 43 stations in the Japanese 4 and 6 call areas (makes your mouth water . . . 5LP).

"Saturday 25-3-78: On six metres between 0945 and 1300Z worked 12 JAs in call areas 1, 3, 4, 5, 6 and 7 plus HLWRI and KG7DX. On 2 metres between 1110 and 1242Z worked a total of 34 stations again the call areas of JA4 and JA6.

"Sunday, 26-3-78: Quiet day, worked KH6J51 at 0313Z!

"Monday, 27-3-78: On six metres 0400 to 0500Z worked WA8UW/KH6, KH6IAA and KH6J51. From 0952 to 1050Z worked JASTEW, JA6DZ, JA6DZ and HLWRI. As you can see, conditions are improving have been good but no new countries on six and no new call areas on two metres. Signals on two have peaked to 59+ at times both ways and signals from JA on six metres have been to 59+ 30 dB."

And that's where the "diary" ends for the moment. I made almost like a book. I have included quite a lot of detail, particularly for the two metre contacts because some people will scrutinize the times and call areas closely to try and obtain some answers to the questions obviously posed — how many times in the past have such contacts been missed for want of a 144 MHz Wry? Why do some two call areas on 2 metres? What form of propagation is making the contacts possible? Why are the signals not being heard in Guam? Are they limited to a strict north-south path with a definite cut-off distance? Are they dependent on six metres being open as well? etc. etc.

Gram also includes a number of "extracts" from his log book in which readers will be interested.

"On 1-3-78 XE1EG heard New Zealand TV on 50.750 2115 to 2245Z. On 3-3-78 JA worked KH6IA, KH6H1 and KH6J1 0410 to 0545Z. KHE worked CNle and Argentina. JASCMO worked CE3OK 0300Z. JA worked VK4RO 0300Z.

"On 4-3-78 JA heard KH6QEI weakly, JA worked VK4RO 0500 to 0700Z. On 25-7-78 the WJRA beacon was heard in Japan in JA3 area. KG6DX reports 3D3CM active on six. KG6JDX runs 250 watts on 2 metres. On 2 metres only 2 x 3-78 VK4VU and VK6B both heard the KH6QEI beacon at 10 dB over 9. 13-3-78, JAs working VK4MS and P29HV, KG6 only hearing VK8. 14-3-78, 3D3CM worked JA 0900Z.

"16-3-78: Chatted with AI KH6IAA on 10 metres and he passed on the following information: Opening on six metres KH6 to LU on 15-3-78. He works 3D3CM nightly, KH6IAA is located on Hilo Island and runs a TS550 to a FTV650 using an outboard power supply. He has been heard on 10 metres, but JA2BZY reported VK4VY at 1158Z, and VK4RO, VK4GS and VK4XLX at 0830Z.

"17-3-78: UA0NLN and RA0LFI in Vladivostok operate on 2 metres and are looking for VKs on 14.4110 at 1300Z. 18-3-78: KG6DX worked VS8BE in Hong Kong on 14-3 on 52.025 on SSB. VS8BE Lyell advised he had his Henry 6N2 going and says from April he will have 52.025 CW only and 52.025 SSB only. KG6DX was quite good and VK4RO this day — KG6 to VK4 is quite common nowadays.

"19-3-78: KH6SJ worked LU7FA and LU3HFU this day. Opening to VK included VK6GB, VK8VV and VK4RO, the latter being audible in Darwin on backscatter but too weak to copy. KG6JH is

hearing TVQO and ZL TV regularly. FOBOR will be QRT for six months from 23-3-78. JAs working K9PNT/DU2 on six this evening but I couldn't hear him on 50.175. 20-3-78: KG6JDX reports that P29HV is hearing JAs on two metres but very weakly. KG6JH heard TVQO at 0000Z today (very early). JAs worked 3D2CM again today. Active stations on six metres in Hawaii are KH8HI, KH8JSI, KH8IAA, KH8JL, KH8BZF and WAGUS/ROB.

23-2-78: JAs hearing P29ZWW, VK4G5 and VK4RO in the evening. VK4RO to KH8IAA at 0452Z. KG6JH working JAs at 1000Z. Gerry KG6JH reported that his latest HR report predicts a sunspot peak of 153 in February 1980 (i.e. smoothed number) and that this cycle looks like being as good as cycle 18. Prediction for February 1978 was 64.4 but turned out to be 90! Joe KG6DX reports that sunspot counts of 170 relate to an F2 opening to 50 MHz and 180 to an F2 opening to 52 Hz. With a smoothed number of 153 we can expect MANY days of MUF above 52 MHz. Gerry KG6JH says the furthest south he has worked is to VK4ZNC near Brisbane.

"23-3-78: JAs contact 3D2CM at 0645Z. KHJHJ to P29HV at 59+.

24-3-78: WAGUB/KH6, Myron, runs a FT620 to a Ringo Kennedy in Costa Rica. A KJL 80 was linear. Location 25 miles north of Honolulu. KH8JSI works KH7IAA on backscatter. JST is on Oahu and 1AA on Hilo about 200 miles away. VK1RK worked six JAs on six metres on 19-3-78. JAs working P29ZWW and VK4DO at 1020Z, also VK4MS. KG6JH works VK4AAL, also reports hearing TVQO at 0002Z. Beacon WAGURA on 50.091 per operation 100 21 hours, also 6Y5 Jamaica beacon is on 50.050 MHz (ex-KG6DY).

"25-3-78: KH8HI works KG6JH 5 x 7 at 0545Z. KG6 hears TV "sync" signals on 50.7 from the south-east, maybe Russia/China on backscatter, but might be something else! JAs heard weakly in P29 on 20-3 and 24-3 on 2 metres. KH8HI working LU (Argentina) on 23-3.

26-3-78: KH6s work PY2CSS and PY5WB on six 0230 to 0341Z. PY2CSS QTH is Sao Paulo and PY5WB 400 km away. KH6s work VK4MS and VK4RO.

"27-3-78: KH6s worked LU on six days during March. In T120Z in Costa Rica at 151500. Heard VK4RO calling KH6 on backscatter to 5 x 5 on CW and SSB. WAGUB/KH6 works VK4TL on 52.110 at 0430Z. HL9WI hearing signals on 2 metres.

It's been quite an interesting week. I think conditions are changing. We will probably have to wait about six weeks for USA contacts because I think an Es hop between KH6 and the mainland is necessary."

Graham reports generally conditions have been very good. I would regard that as an understatement. . . SLPJ and I are looking to W for contacts, but no one seems to have any knowledge of beacons there. Graham also remarked that if I was in Darwin during March he could assure me of contacts to JA on six metres AND two metres, plus a long chat to KG6 — currently the paths are more reliable than HF!

On behalf of the VHF fraternity I feel we owe a vote of thanks to Graham for taking the trouble to keep us in the loop. Information from W is not the earth. Even if we are not working the exotic stations at least it keeps the more interested and reliable stations in the south on the air and looking to the north — I never ever previously really thought seriously about two metre contacts to Darwin or further north — I do now and so do others! I may take the opportunity to visit active Darwin at least will be worked from VK5 on 2 metres in due course! Again, many thanks, Graham, for a job well done.

New VK4ZNC advises working JAs on six metres almost every afternoon since mid-February to time of writing, 15-3-78, working all areas except JA6, and only one JA5. On 12-3-78 at 1206Z he worked KG6JDX and KG6JH in JA at 52.103 after the band had been open to JA most of the afternoon. He was on the two metre stations run about 1 Kw and Nev 400 watts PEP from a pair of 4CX250Bs driven from his FT620 transverter. North Queenslanders also were working Gum

at the same time with stronger signals. Thanks for writing, Nev, you have probably worked KH6 by now!

A letter also comes from Rod VK4ZRO outlining activities in the Brisbane area, and has worked JAs on six metres on 19-2, 25-2, 26-2, 1-3, 3-3, 4-3, 7-3, 8-3, 10-3, 12-3 and 14-3. Interesting to note the rare JAs were worked on 7-3 and 8-3, and 12-3. On 12-3 0400 to 1200Z all JAs worked, being the first class 2 TEP heard. On 14-3 0330 to 1100Z all JAs again, but with Class 1 TEP (i.e. no flutter, doppler shift, etc.). Also no KG6! Some good QSOs have been made using only 200 mW.

Rod reports two metres is not being overlooked and confirms the contact with VK3AUR on 13-11-77 at 1200Z on 144.1 SSB 5 x 2 both ways. On 15-1-78 1000Z heard VK3AWD? 144.1, also the VK3RTJ beacon. On 15-1-78 he worked VK6ZGF in Alice Springs (reported previously) and on 22-1-78 0830Z VK4ZSH "partially" worked P29ZWW over a distance of 1300 miles on Ch 40 FM. Rod is also interested in 6 and 2 metre metro scatter? Any takers? It appears also that FK6AB is on 6 metres with an IC502 to a pair of 614Bs. Thanks, Rod.

Included with Rod's letter was a copy of a letter sent to Ray KZ24Ms of SMIRK, and there are a few interesting bits of information in there.

"WBVSUVW worked Geoff XE1GE on backscatter on 28-2-78. Geoff had previously worked LU, PY and ZP9 on 24-2 so was on the alert. The contact with WBVSUVW was around 2145Z, and XE1GE heard the KH8EQI beacon at the same time. At the same time he had to sit there for an hour and a half listening to ZL TV audio on 50.701!

"KH8IAA on 2-3-78 worked six stations plus C1, followed by JA. On 3-3-78 he worked ZL and VK TV and VK beacons from 0500 to 0700Z but no contacts. The northern hemisphere stations are predicting that with the solar flux rising so well conditions may soon rival those of 20 years ago!"

To change the area somewhat, Ken VK6ZFO writes from Koolan Island, which is 80 miles due north of Derby and just off the mainland. The letter was dated 19-3-78 and reported on that day Ken had just finished listening to the KH8EQI beacon at 83, but no contacts eventuated. From 26-2 until 19-3 Ken worked more than 170 JAs plus KG6JH, KG6DX and KG6JDX. On some days many JAs are there but he doesn't bother to work them!

Ken has 2 metres SSB but to date has not heard any J signals. Ch. 2 TV from Perth is an occasional customer, but last October they were able to watch TV RI from Jakarta every night in colour from station open to close using only a 2 element antenna. No results have come from trying to work WY on 2 metres, however. To keep 144 SSB going Ken works daily to 0630FM on 144.1 using a 200 watt country, and to Keith VK6W 60 miles distant. Ken's gear consists of FT620 into a 3 element yagi for 6 metres. Two metres a home brew solid state transverter with 25W PEP drive via the FT620 into a 5 el. yagi. 2 metres FM: Philips 1680 25 watts 146.000 also repeaters 2, 4, 6 and 8. On 432 MHz he uses the FT701B which drives a Mitec transverter with 10 watts PEP into a 4 element yagi.

Ken advises he is in an ideal location with YB (Indonesia), an all water path. The TV station he runs is CKR7, located on the highest spot on 1700m, 670 feet a.s.l. The ocean is only three-quarters of a mile away, giving splendid ocean views. They have a 110 foot tower for the TV station, so Ken has views of the coast almost some of his own antennae! Thanks for writing.

Geoff VK3AMK writes confirming much of the information already included from Graham VK6GB. However, he has some interesting news on JH5TEV, the first JA to work VK6GB. Geoff reports that Tell is a 15-year-old high school student, both father and mother are amateurs, his 13-year-old brother works 6 metres and his 11-year-old sister is sitting for the exams in May! Tell's English is excellent and he says he now learning Spanish so he can work South Americans! Tell is now very keen to work a VKs to clinch the world record 2 metre contact — that's good news . . . SLP.

Tell also passed on to Geoff information regarding DYPeddon on 29-4 to 3-5 to V56 and CR9, operation on 15, 10 and 6 metres. V56 on 50.110 and CR9AJ on 50.200, but will QSY to 52 for VKs! So we will wait news of what contacts were made.

Steve VK3OT sent a copy of a letter received from Dave WPGCI, who indicates many operators in USA are completely unaware that VK allocation is 2 MHz higher on six metres than they operate. WPGCI uses a TR-6 giving 160 watts of SSB and 240 watts CW, giving him 47 US States and has heard the KH8EQI beacon strongly. He has ordered extra crystals to give him 52.000 to 52.500 capability and will pass the word around via "73" of our 2 MHz disability.

Of course it is the old story — we do have a 2 MHz disability offset from the rest of the active 6 metre world, and it extends beyond purely the band offset. For those in the north to work us they need to tune higher in frequency which means their high gain good antennas will perform in performance to a fraction of what is usual. With a high SWR. We are not quite so badly situated for antenna performance as we operate lower in frequency in 'E' and 'F', as you all know, the yagi antenna drops off in performance at a slower rate on the low frequency side of resonance than the high frequency side. But my own normal antenna element wide spaced yagi on 52 MHz loses some 6 to 8 dB of gain by tuning down 2 MHz so signals need to be that much stronger before contacts are possible. We can only hope the work Graham VK6GB in Darwin is doing will continue to alert more stations overseas of our problems and give a chance for those overseas to get extra crystals installed.

Just to check the subject a bit I was appalled to read in the Moonbounce Report for March 1978 in "The Propagator" of the serious damage done to the Dapto EME Installations. Damage was first discovered on 8-2-78, buildings had been entered, windows smashed and items in all rooms either smashed or stolen. Fire extinguishers had been discharged over equipment, paint thrown around and equipment damaged. The fire was caused by a fire and a fire had been lit in one room, but fortunately had not caught the building alight. The padlock had been removed off the steel security locker which houses the EME equipment, and items of gear either stolen or damaged. Quantities of wiring and cabling had been ripped out.

Temporary repairs were attempted to try and get on the air to meet their obligations to stations overseas on 11-2 but to no avail. A week later the buildings were again entered and even more serious damage resulted from the intrusion. Under the circumstances no further repairs were attempted.

On 2-3-78 an inspection was made with representatives from the University and it was decided security could no longer be offered at the present site, so after eight years the Dapto Moonbounce Project, as such, had been destroyed. So now a practicability study is being undertaken to see if the 30 foot dish can be moved to a safer site.

I feel sure those who care will join me in expressing disgust as well as disappointment that there are individuals who will stoop to such depths of conduct and the consequences of their actions caused to those who have been so dedicated to the project. May we wish you, Lyle VK2A/U and Charlie VK2ZEN, the mainstays of the project, the hope that the project can be undertaken elsewhere in the future, under safer conditions. In the meantime, we all say thank you for a task well done, and the opportunity and the contact we have had with your stations to work VK on 432 MHz EME — without your efforts this would not have been possible — may be some small reward for your efforts. We salute you and your helping group.

Before finishing up for this month, 144 MHz across the southern climes still provides interesting contacts. VK6 at Albany to VK5 pops up every now and again, as does also 432 MHz. On 5-3-78 Col VK5ROD and myself VK5LU observed 146.002 which beamed to Albat in the west, backscatter signals from VK3Y1I. To check, I turned the beam to the direct path but no sign of the VK3. Going back to the west and he was there again. Col remarked he had always been of the opinion that

backscatter was possible on 2 metres but very few if any people believed him. However, this time he was very pleased to have my confirmation of the phenomenon. After a period VK3YII did become audible very weakly on the direct path.

A brief opening between JA and VK5 on 27-3 at 0315Z. VK5Z2Z worked JE1, JH7 and JAB for about 10 minutes with signals to 5 x 9. That's a fairly typical to JA from this area.

The notes have contained a lot of interesting information during the past few months, thanks to my very good correspondents. I wonder how much longer it will go on. Is this just a taste of things to come with the solar count increasing significantly? I would like to think so. The March/April period could bring some surprises, perhaps I can report them to you next month.

In the meantime, let us close with the thought for the month: "If we really want to stop organized crime, all we have to do is form a government department to run it, then stand back while it is choked to death by red tape!"

The Voice in the Hills.

AMATEUR SATELLITES

Bob Arnold

VK3ZBB

Another milestone in satellite history has been passed with the successful launching of AMSAT OSCAR D which became known as AOB once it became operational. Launch was precisely at the predicted time of 1754Z on the 5th March and a section from the launch vehicle took place one hour twenty-five minutes after lift-off. Several enthusiasts in Australia listened to the launch which was broadcast on the 20 metre band and although reception was poor, sufficient intelligence was received to indicate that things were going well, and we had the great thrill of hearing the Mode J beacon as the satellite passed over Melbourne on its second orbit.

Since that time many orbits have been logged, sufficient to give reasonably accurate parameters for local times of acquisition. The satellite became stable much more quickly than was anticipated and before the end of the first day the ten metre antenna was deployed making it possible to re-receive the Mode A beacon on subsequent passes. The satellite was taken over by ARRL on the 20th March and we understand the Mode of operation will now be scheduled for Mode A on Mondays to Fridays inclusive and Mode J on Saturdays and Sundays.

The orbital parameters of AOB are quite close to those predicted, the most recent being orbit time 103.299 minutes, incremental shift per orbit 25.8075° West.

The calendar of first equatorial crossings given at the end of these notes is as accurate as can be expected at this early stage, and a tolerance of a minute or so may be necessary. It has been ascertained that the times of acquisition in Melbourne are similar to the times for OSCAR 7, i.e. to the equatorial crossing time add the time of the appropriate number of orbits (four, five or six) multiplied by 103 minutes and again add approximately 92 minutes for S-N passes and 60 minutes for N-S passes.

To acknowledge the indebtedness of Australian amateurs to the small band of AMSAT volunteers connected with the launch of AOB, I have sent the following letter to Joe Kasser, Editor of AMSAT Newsletter:—

On behalf of Australian amateurs, congratulations to the team who so ably constructed AOB and arranged for its launch.

We were all most impressed with the timing of the operation and were thrilled to hear the 435.095 beacon as AOB came over Australia on its second orbit at 0601 local time. Subsequently, at least one of our enthusiastic group has heard the Mode A

or Mode J beacon on most passes in sight of Australia and in the last few days communications have commenced through the satellite.

Communications on Mode A are better than through OSCAR 7 and we are looking forward to the Easter period when we shall have the first opportunity to work on Mode J.

Again, congratulations to all concerned for a job well done; they deserve every encouragement from amateurs in the Southern Hemisphere.

Joe Kasser G3CZC, together with Perry Klein WSPK, published a considerable amount of information on AOB in the AMSAT Newsletter. This has been edited and is reproduced for the information of local enthusiasts. You will appreciate that with the launch having been effected, reference to OSCAR D should now read AOB.

INTRODUCTION

AOB was built over the last two years by radio amateurs in the United States, Canada, West Germany and Japan, and is also the first spacecraft in which AMSAT, Project OSCAR and the ARRL have joined together in building flight hardware.

AMSAT-OSCAR D carries transponders for two modes of operation. There is a conventional 145.9 MHz/29.4 MHz Mode A transponder, and a new 145.9 MHz/435.1 MHz Mode J transponder, a similar frequency combination that was pioneered by the OSCAR IV spacecraft in 1966. Six channels of telemetry are provided to monitor the onboard status of the spacecraft. The spacecraft makes extensive use of parts left over from the AMSAT-OSCAR 7 and Phase III programme.

MISSION OBJECTIVES

The principal objective of the AMSAT-OSCAR D spacecraft is the educational uses of a low orbiting satellite. It is to provide a means for the use of such a satellite as an educational tool in schools or other educational institutions. Other objectives include the continuation of communications demonstrations by means of stations in the amateur-satellite community, the feasibility of using satellites with small amateur terminals of "bush" communication, emergency communications, communication between medical centres and isolated areas, aeronautical, maritime and land mobile communications, direct satellite-to-home voice "broadcasting" to simple amateur receivers, and other similar applications. Further objectives are to demonstrate the feasibility of techniques that enhance the usefulness of low orbits for these satellite applications, and to test the suitability of a new communications transponder frequency combination (Mode J) for small terminal users.

AMSAT-OSCAR D will permit the continuation of the education programme, which began with AMSAT-OSCAR 5, 6 and 7, over the next several years. The AMSAT-OSCAR D anticipatory lifetime. OSCAR satellites have begun to play an important role in a new approach to science education. Used as remote laboratory tools, these satellites represent a pioneering utilization of an active space system in the classroom. Since the launch of the first satellites twenty years ago, satellites have had very dramatic impact on education. Using inexpensive ground terminals for OSCAR satellites in schools, students can gain first-hand experience in space science. This type of direct, active involvement has relevance to the study of communications, astronomy, engineering, physics, mathematics and meteorology. The OSCAR ground terminals puts at the disposal of the instructor and student an active satellite system as a resource for demonstration and experimentation.

SPACECRAFT DESCRIPTION

AMSAT-OSCAR D is a communications satellite in the AMSAT Phase II (low-orbit) series, designed to operate with small stations in the amateur-satellite service on a non-commercial basis. The spacecraft contains two communications transponders and command and telemetry systems. The spacecraft is solar powered, weighs 60 pounds, and is a 15-inch rectangular solid 13 inches high. Its anticipated useful operating lifetime is three years.

Two types of communications transponders are aboard the spacecraft. Normally, only one transponder will be operated at a time because of spacecraft battery constraints.

TWO-TO-TEN TRANSPONDER — "MODE A"

Note: Bold letters are inferior letters.

The Mode A transponder is a two-to-ten metre unit similar to the one on AMSAT-OSCAR 7 and with the same frequency passband (input frequency passband of the 145.85-145.9 MHz, and output frequency passband between 29.40 and 29.45 MHz). The 29.40 MHz beacon provides telemetry data in Morse code at a frequency of 29.402 MHz. Approximately —95 dBm is required at the transponder input terminals for an output of one watt. This corresponds to an effective radiated power from the ground of 80 watts for a distance to the satellite of 1,200 miles and a polarization mismatch of 3 dB. The transponder translation frequency (input frequency minus output frequency) is 116.458 MHz. Thus, the relationship between the uplink (fu) and downlink (fd) is as follows:

$$fd = fu - 116.458 \pm \text{Doppler}$$

where both fd and fu are in MHz.

(For example, an uplink signal at 145.900 MHz will produce a downlink signal from the transponder on 29.442 MHz \pm Doppler.) As in the two-to-ten metre transponder in AMSAT-OSCAR 5 and 7, the passband is not inverted, and upper-sideband uplink signals become upper-sideband downlink signals. Output power is 1 to 2 watts.

Note that the downlink frequency will be slightly different (8 kHz) to that of the equivalent AMSAT-OSCAR 7 Mode A transponder that has an equivalent frequency relationship of

$$fd = fu - 116.450 \pm \text{Doppler}$$

TWO-METRE TO 70CM TRANSPONDER — "MODE J"

The second transponder, constructed by members of the Japan AMSAT Association in Tokyo, uses a two-metre input, 70 centimetre output combination which has not yet been flown in the AMSAT Phase II series. Note that a similar combination was used in the short-lived OSCAR IV spacecraft in 1966.

This transponder, designated Mode J, operates with an input frequency passband of 145.90-146.0 MHz, and an output frequency passband of 435.10-435.20 MHz. Power output is about 1-2 watts PEP, and the output passband is inverted, i.e., upper-sideband uplink signals become lower-sideband downlink signals. The transponder translation frequency (input frequency plus output frequency) is 581.1 MHz \pm Doppler. Uplink sensitivity for one watt output is —105 dBm, corresponding to an elip from the ground of 8° watts for a distance to the satellite of 1200 miles. Note the greatly improved sensitivity of this mode, and keep your power down. A 100 milliwatt beacon carries telemetry at frequency of 435.095 MHz.

The relationship between the uplink (fu) and downlink (fd) is as follows:

$$fd = 581.1 \text{ MHz} - fu \pm \text{Doppler}$$

where both fd and fu are in MHz.

ANTENNA SYSTEM

Both the Mode A and Mode J transponders use the same receiving antenna, a cantilevered turnstile comprised of four 19-inch lengths of 1/2-inch carpenter's rule fed by a hybrid and matching network so as to feed circular polarization. One port of the hybrid feeds the Mode A receiver, such that left-hand circular polarization is required by users in the Northern hemisphere, and right-hand circular polarization in the Southern hemisphere. A second port of the hybrid is connected to the Mode J receiver such that right-hand circular polarization is required in the Northern hemisphere, and left-hand circular polarization in the Southern hemisphere. The antenna gain should approach 5 dB in the —Z direction (i.e., toward the bottom of the satellite).

The Mode A ten-metre downlink antenna is a linearly-polarized dipole, oriented perpendicular to the stabilization magnets in the spacecraft as in AMSAT-OSCAR 5 (but unlike AMSAT-OSCAR 7, which has the ten-metre antenna parallel to the axis of the magnets).

The Mode J 435 MHz downlink antenna is a simple monopole, linearly polarized, and located on the top of the spacecraft. Note that its location may result in some radiation shielding at high Southern hemisphere latitudes.

* Sensitivity may decrease by a factor of 10 (10 dB) under different conditions of battery at certain times as much as 80 watts may be required.

TELECOMMAND SYSTEM

A five-function telecommand system of a new design is carried out on AMSAT-OSCAR D. The system is based on the best features of the AMSAT-OSCAR 6 and 7 telecommand systems, and is designed to be virtually immune from noise and interference. The command functions are:

Mode "A" Select (two-to-ten metre transponder ON).

Mode "J" Select (2m-to-70cm transponder ON).

Mode "D" Select (Recharge mode; both transponders OFF).

Ten-metre Antenna Deployment.

Ten-metre Antenna Reset.

TELEMETRY SYSTEM

Note: Bad letters are inferior letters.

Ch. 1 — Total Solar Array Current
IT = 7.15(101-N) mA.
IT = 7.15(101 - N) mA.

Ch. 2 — Battery Charge-Discharge Current
IBat = 57(N-50) mA.
IBat = 57(N - 50) mA.

Ch. 3 — Battery Voltage
VB = 0.1N + 8.25 volt.

Ch. 4 — Baseplate Temperature
Tb = 35.5 - 1.48N (°C).

Ch. 5 — Battery Temperature
TBat = 35.5 - 1.48N (°C).

Ch. 6 — RF Power Out. — Mode J
PJT = 23N milliwatts

A sample telemetry frame would be:

120 255 360 451 620 HI 120

Note that, unlike AMSAT-OSCAR 6 and 7, AMSAT-OSCAR D has only one parameter per line (AMSAT-OSCAR 6 and AMSAT-OSCAR 7 had 4). As a result, a complete telemetry frame is sent in approximately 20 seconds.

POWER SYSTEM

The spacecraft contains solar panels on its four sides (along the +X, -X, +Y and -Y axes), and on the top (+Z axis). No panels are contained on the bottom (-Z axis), since this is where the spacecraft attaches to the launch vehicle. The solar cells, combined with a 12-cell, six-ampere-hour rechargeable nickel-cadmium battery should be adequate to power the spacecraft with a positive power budget in Mode A for several years even considering solar cell degradation in the radiation environment. The power drain in Mode J, however, is somewhat larger, and so the Mode J transponder probably cannot be operated continuously.

A battery charge regulator is also contained which converts from the 28-30 volt solar array voltage to the 14-16 volts required by the battery. It also tapers the charge rate so that the battery trickle-charges as the battery approaches full charge (as indicated by the battery voltage).

STABILIZATION SYSTEM

Four permanent magnets located inside the spacecraft and aligned along the Z axis provide stabilization, as in AMSAT-OSCARs 6 and 7. The polarity of the magnets is such that the top (+Z axis) of the spacecraft always points toward the magnetic North Pole of the earth. Hysteresis permalloy damping rods mounted behind the +X, -X, +Y and -Y solar panels are designed to reduce the spin of the spacecraft about the Z axis, functioning in a manner similar to a shorted transformer turn as it cuts the lines of flux of the earth's magnetic field. The permalloy rods are left over from AMSAT-OSCAR 7, which successfully used the same type of stabilization system.

TELECOMMAND VERIFICATION PROCEDURES

AMSAT-OSCAR D's telecommand and telemetry systems have been designed to provide two means to easily verify whether the spacecraft is accepting commands. First, when the telecommand system has been enabled and is ready to accept a command, the Morse code telemetry will be interrupted (time) and the telecommand carrier will be heard on the beacon frequency. The beacon will revert back to Morse code when the telecommand system is no longer enabled.

The second method of telecommand verification is to use the "Ten-metre Antenna Deployment" command. This will cause a series of keying pulses to be heard on the telemetry beacon in place of the Morse code telemetry if the command has been accepted. The "Ten-metre Antenna Reset" command should be sent soon thereafter in order to restore the beacon to the Morse code telemetry mode.

TELEMETRY INTERPRETATION

The most important telemetry channel that will affect operations decisions is channel 3 (battery voltage). In Mode A the spacecraft should maintain a positive power budget so that there should not be a net discharge of the battery over an orbit average. Mode J operation, however, requires somewhat more power, which may result in a net discharge of the battery, especially under conditions of high transponder loading, and therefore it will be necessary for telemetry and telecommand stations to keep a close watch on the battery voltage so that action can be taken as necessary to command the spacecraft into Mode D (the recharge mode) before the battery discharges too far. Three cut-off levels are specified below:

Red Level "A": 1.2 volts/cell Ch. 3 = 61 counts.
Red Level "B": (1.1 volts/cell) Ch. 3 = 50 counts.
Red Level "C": (1.0 volts/cell) Ch. 3 = 38 counts.
Red Level "A" should be used during the first year or so of the spacecraft's life as the cut-off point below which telecommand stations should command the satellite into Mode D for recharging. Later in the spacecraft's life as the battery discharge characteristic curve changes, Red Level "B" should be used, and Red Level "C" should be used if there is evidence of deterioration of the battery, or if it is desired to recondition the battery.

Channel 1 (solar array current) provides an indication of whether the spacecraft is in the sun or eclipse (it should read in the nineties in counts when in eclipse). Fluctuation in ch. 1 telemetry is the best indicator of the rate of spin of the spacecraft, along with observations of fading, particularly of the 435 MHz Mode J downlink signal from the cluster-wave 335 MHz monopole antenna.

Channel 2 (battery charge-discharge current) gives information on whether the battery is charging or discharging. A reading larger than 50 counts indicates that the battery is charging, while a reading of less than 50 counts means the battery is discharging. There is a two-second integration time associated with the current telemetered on this channel. The total power drain of the spacecraft can be determined by observing channel 2 while the spacecraft is in darkness (as indicated by channel 1, which should read in the nineties in darkness).

Telemetry channels 4 and 5 (baseplate temperature and battery temperature) should generally track within a few degrees (except perhaps in the first day or so after launch when the spacecraft has not yet established a thermal equilibrium). Experience from AMSAT-OSCARs 6 and 7 indicate that the battery can overcharge and overheat during periods of the year when the spacecraft sees the most sunlight. If this is the case, channel 5 may exceed channel 4 in temperature by 10 degrees or more (Centigrade), and action should be taken to reduce this overheating. This can be accomplished by keeping the spacecraft in Mode J to consume any extra charge current from the battery.

Channel 6 is a measure of the Mode J transponder 435 MHz RF power output. Associated with the telemetered readings is an integration time of 2.5 seconds, so that it is average power rather than peak power. The Mode A transponder power consumption (largely determined by the PA current) can be measured by observing channel 2 telemetry as noted above.

OPERATING SCHEDULE

Since the prime mission of the AMSAT-OSCAR D spacecraft is to use the Mode A transponder for the ARRL OSCAR educational programme in schools, the spacecraft may be left in Mode A during weekdays (Mondays through Fridays, US time) and put in Mode J on weekends. Additionally, if not an excessive burden on the telecommand stations, evening orbits in the Western Hemisphere (morning orbits in the Eastern Hemisphere)

sphere) can be switched to Mode J, battery permitting. In any case, all operation in Mode J will require careful monitoring of the battery charge level (as indicated from channel 3 telemetry, battery voltage). The power budget may not support the Mode J transponder for full-time, continuous operation in this mode over an entire week-end.

AMSAT-OSCAR D will operate in a 560 statute mile orbit, i.e., at just over half the altitude of the 910 statute mile orbit of AMSAT-OSCAR 7. Thus communication ranges will be different. The usable time on an overhead pass will be about 18 minutes instead of the 22 minutes provided by AMSAT-OSCAR 7 and the horizon range will be 240 miles instead of the 240 miles of AMSAT-OSCAR 7. This means, for example, that transatlantic communications will still be possible but not as often as with AMSAT-OSCAR 7.

Keeping track of this satellite is going to be much simpler than for AMSAT-OSCAR 7. It will come into range at the same time each day (more or less); the overhead descending node pass is planned for 9.30 a.m. local time.

OSCAR PREDICTIONS — JUNE 1978 — A07

Orbit	Mode	Date	Time Z	Long.
12603	B	01	0115	70.7
12615	A	02	0014	6.1
12628	B	03	0108	74.7
12640	B	04	0008	59.8
12653	A	05	0102	73.2
12675	B	06	0001	58.9
12686	B	07	0056	71.0
12691	A	08	0150	85.2
13003	B	09	0049	70.1
13016	B	10	0144	73.6
13038	A	11	0043	68.5
13041	B	12	0137	82.1
13053	B	13	0037	66.9
13066	A	14	0131	80.5
13078	B	15	0030	65.4
13091	B	16	0124	78.9
13103	A	17	0024	63.8
13116	B	18	0118	77.4
13128	B	19	0017	62.2
13141	A	20	0112	75.8
13153	B	21	0011	60.7
13166	A	22	0105	74.3
13178	B	23	0005	59.7
13191	B	24	0059	72.7
13203	A	25	0153	86.3
13216	B	26	0053	71.1
13228	A	27	0147	84.7
13241	B	28	0046	66.6
13253	A	29	0141	83.2
13266	B	30	0040	68.0

ORBITAL PREDICTIONS — MAY 1978 — A08

Orbit	Date	Time Z	Long.
629	01	0152	62.9
630	02	0152	62.9
631	03	0137	65.5
632	04	0142	66.9
633	05	0004	42.45
634	06	0009	43.8
635	07	0015	45.1
636	08	0020	46.5
637	09	0025	47.9
638	10	0030	49.1
639	11	0035	50.5
640	12	0040	51.8
641	13	0045	53.1
642	14	0050	54.5
643	15	0055	55.8
644	16	0101	57.2
645	17	0106	58.5
646	18	0111	59.8
647	19	0116	61.2
648	20	0121	62.5
649	21	0126	63.9
650	22	0131	65.2
651	23	0136	66.6
652	24	0141	67.9
653	25	0003	43.4
654	26	0008	44.8
655	27	0013	46.1
656	28	0019	47.4
657	29	0024	48.8
658	30	0029	50.1
659	31	0034	51.5

Period 103.232 minutes.
Longitude increments 25.81°.

$(P)^n = k(RT)$. ICOM IC701 PUTS NEW DIMENSIONS INTO THE PERFORMANCE FORMULA !!

where R = Reliability, T = Technical innovativeness, K = World-wide acceptance figure.



IC701 state of the art


HF TRANSCEIVER

Let's look at the "T" factor!! Remember the days when separate liners and converters for each band was the ultimate transmitter and receiver performance? You get it with the IC701 1978 style.


Transmitter: Broadband final, no tuning required, uses separate final low pass filters on each band, fed from a pair of bulky transistors in class B. Optimised separate driver circuits with temperature compensation in the driver stages enable a power output of around 100 watts pep on all bands and modes. Japanese domestic version has reduced power on some bands and also different frequency ranges.

Receiver: The same final low pass tank circuits are used for the input circuits on receive. Separate RF amplifiers using dual gate MOSFET amplifiers pass the signals to a Schottky diode double balanced mixer giving a first IF of 9.0115 MHz. This gain of the receiver is optimised on all bands giving a sensitivity figure of 0.25µV for a SN/10dB on any band. As it is to be expected, the cross modulation performance using this type of mixer is exceptional and superior to competitive transceivers.


The system used for **bandpass tuning** is unique to the IC701: The receiver IF system uses two filters —




FL1 centre freq. is 9.0115 with a bandwidth of ± 1.15 KHz. FL2 centre frequency is 10.75MHz with a bandwidth of ± 1.2 KHz. The VFO has a centre frequency of 19.760MHz which can be varied by the front panel control ± 1.5 KHz. The following diagrams show how signals pass through the system when Band Pass control (VXO) is at centre position —



When VXO (Band Pass tune) is clockwise the signals from FL1 are mixed to the new frequencies of 10.7500 to 10.7527 MHz by the VXO on a freq. of 19.7630MHz. The resultant frequencies if plotted on the FL2 filter bandwidth would look like this —



Remember, dotted shape is the filter shape of FL2 and solid line is mixed output signals from FL1. Then, since the upper frequency passband limit of the 10.75MHz filter, FL2 is 10.7512, not all the signals will be passed by the filter. Conversely, when the passband control is in the fully counter clockwise position the VXO is on a frequency of 19.76MHz. The diagram now looks like this —



The 10.75MHz signals from the mixer IC3 will be from 10.7497 to 10.7473MHz. As the passband of the filter is 10.7512 to 10.7488MHz not all the signals will be passed. Again the passband has been narrowed to 900Hz and offset to the opposite side of the centre frequency of the crystal filter. Try an example: Suppose you are receiving a signal whose input to the mixer IC3 is 9.0115 and QRM is on 9.0125 i.e. 1KHz away. With the BP control at centre both signals will be heard as the resultant signals will be 10.750 and 10.749MHz and both are within the passband of the filter.

By turning the BP control a resultant frequency of 10.748 MHz is reached which puts the 9.0125MHz signal outside the passband of the filter.

The signal you want on 9.0115 when mixed with the VXO at IC4 becomes the original 9.0115MHz signal. Sit down with the figures and you can see why this type of BP tuning is so unique.

The big "T" is endless.

A VFO with optical tuning, no variable capacitors are used by ICOM under agreement with Collins Radio USA.


Separate VCO for each band is used only to reduce spurious and birds. A fan for the finals that only works if you run for extended periods on RTTY or key down conditions. If a danger point temperature is reached the fan doubles its speed and the digital display flashes to tell you to quit transmitting!

Two VFOs are built-in for split band working. No need for an external VFO.

Narrow CW filter and desk mic (condenser electret type) are all part of the package.

The built-in speech processor uses the 9.0115MHz filter in the passband tuning circuit. Compression control on the front panel controls the drive level and hence the amount of compression.

The same control also acts as power output control on CW and RTTY. Since we all photograph these beauties from the front you would not notice the 24 pin accessory socket on the rear panel. Voltages and functions available at this point enable remote control facilities to be added, but before you get out the design tools, ICOM have thoughtfully provided a remote control head as an optional accessory. Size is about that of a calculator and has its own CPU, digital readout and control buttons. You can select frequencies, change bands, scan and when connected to the 2m IC211, set up duplex channels as well!



The IC701 can be interconnected with the IC211 for Oscar work with due allowance being made for doppler shift.

The day of microprocessor interface with an HF transceiver has arrived. While the others are still flogging around with valves ICOM have produced a state of the art HF transceiver.

And the IC701 is supported by VICOM who have been factory briefed on the service and alignment procedures.

Bring a new dimension to your HF operating — the new ICOM IC701.

THE ULTIMATE!

Distributed by:

VICOM

GROUP OF COMPANIES

88 EASTERN RD.
STH. MELBOURNE, VIC. 3205
PH: (03) 899.6700 Telex AA30566

Perth
Adelaide
Gold Coast

446.3232
43.7981
32.2644

Canberra 82.3881
Brisbane 38.4480
Hobart 83.6337



TO COMPLEMENT OUR USUAL RANGE OF CRYSTALS

BRIGHT STAR CRYSTALS PTY. LTD.

35 EILEEN ROAD, CLAYTON, VIC., 3168. Phone: 546-5076 (Area Code 03)

CAN SUPPLY A RANGE OF —



- OSCILLATORS
- WIDE-BAND AMPLIFIERS
- TTL & CMOS
DECADE COUNTERS
- ELECTRONIC CRYSTAL
OVENS

INTERSTATE AGENTS:

Adelaide: ROGERS ELECTRONICS — Phone 42 6666
Brisbane: FRED HOE & SONS PTY. LTD. — Phone 47 4311
Perth: COMMUNICATION SYSTEMS — Phone 76 2566
Hobart: DIAMOND INSTRUMENTS — Phone 47 9077

All Mail to be addressed to: P.O. BOX 42, SPRINGVALE, 3171

ALPHA

LINEAR HF POWER AMPLIFIERS

1-30 MEGAHERTZ

MODEL 77SX - \$5,500.00

MODEL 77D - \$4,500.00

MODEL 374 - \$1,895.00

MODEL 76P - \$1,795.00

MODEL 76 - \$1,495.00

Enquiries:

JAMES GOODGER VK2JO

AUSTRALIAN SOUND AND SIGNAL RESEARCH

G.P.O. BOX 5076,
SYDNEY 2001
(02) 36 7756

THE NEW TS 520S



A NEW STANDARD IN ECONOMY TRANSCEIVERS

Full coverage 1.8 to 29.7 MHz * Outstanding Receiver Sensitivity and Minimum Cross Modulation * Vernier Tuning for Plate Control * Highly effective Noise Blanker * New Improved Speech Processor * RF Attenuator * Easy connection to Phone Patch * Fully compatible for optional 6-Digit Read-out * Price: TS 520S **\$685**

KENWOOD TS 820S HF TRANSCEIVER

The pacesetter, provides superior performance, versatility and features found in no other Transceiver **\$1100**

ON SPECIAL

KENWOOD TR 7400A VHF TRANSCEIVERS. Price **\$395.**

YAESU FT 301D HF DIGITAL, 200 watt. Price **\$985.**

SHURE MICROPHONES, Model 444, especially suited for SSB, ex stock. Price **\$58**

ICOM MODEL IC — 211

Price **\$750**

YAESU MODELS FT 101E

Price **\$850**

FL — 2100B Linear

Price **\$565**

FT 7

Price **\$570**

FT 901 DM

Price **\$1575**

ALL PRICES SUBJECT TO CHANGE WITHOUT NOTICE

ONWARDS forwarding. Please add sufficient for freight or postage, excess will be refunded.

Amateur Electronic Imports

P.O. BOX 160, KOGARAH. N.S.W. 2217
TELEPHONE: (02) 547-1467
CABLE: "AMATEURIMPORT, SYDNEY"



See You Upstairs!

NEW RELEASE

MMT432/144'S' Transverter, featuring 2 switchable ranges. 432 — 434
434 — 436 MHz, input frequency 144 to 146 MHz.

Get away from the maddening crowd below. The MMT432/144'S' 434 Linear Transverter will get you there. This solid state linear made transverter allows you to operate your 144 MHz SSB, AM, FM or CW units at 432 MHz up where there still aren't a lot of people. Amateur Electronic Imports is the exclusive Australian distributor for this precision British made unit from Microwave Modules, Ltd.

NEW RELEASE for OSCAR 8 down link — 70CM converter model MMC434/28, coverage 434 to 436 MHz. PRICE \$51

TRANSVERTERS Model MMT432/28 S, coverage 432 to 436 Price \$245
TRANSVERTER Model MMT144/28 coverage 144 to 146 MHz Price \$185

Our extensive range includes: Converters MMC432/28—432/144 Price \$51
144/28 Price \$45, 144/28LO and 52/28LO Price \$49, MMC1296 and
1296/144 Price \$65, Varactor Tripler MMV1296 Price \$74, 500 MHz
counter MMD050/500 Price \$175, MMT Power supply \$94.

SPECIFICATIONS:

Frequency coverage: 432—436 MHz.
Input frequency range: 144—146 MHz.
DC power requirements: 11-13 volts
(12 volts nominal).
Current consumption: 250 mA quiescent
2.1 Amps peak.
RF connectors: 50 ohm BNC sockets
Power connector: 5 pin DIN socket
Size: 187 x 120 x 53 mm
Weight: 900 grams. PRICE \$295

All prices subject to change without notice.

Onwards forwarding please add sufficient for freight or postage. Excess will be refunded.

Amateur Electronic Imports

P.O. BOX 160, KOGARAH, N.S.W. 2217
TELEPHONE: (02) 547-1467
CABLE: "AMATEURIMPORT, SYDNEY"



"SHURE"

(MADE IN USA)

Communications Microphone

MODEL 401A
High Impedance

Price \$31.50

(Posted anywhere)

Model 401 Series hand-held communications microphones are compact size, CONTROLLED MAGNETIC units designed for clear, crisp, natural voice response of high intelligibility.

CLEAN TRANSMISSION IS

"SHURE"

WITH THIS MICROPHONE

WILLIAM WILLIS & Co. Pty. Ltd.

MANUFACTURERS AND IMPORTERS

77 CANTERBURY ROAD, CANTERBURY, VIC. 3216
PHONE 836 0707

AMATEURS' PARADISE

SAVE ON FREIGHT CHARGES —

BUY FROM QUEENSLAND'S STOCKIST

All the LATEST KENWOOD RANGE in stock — Also ICOM IC202, IC215, IC502 — YAESU FRG7 — KYOKUTOS — MIKES — CLOCKS — HF & VHF ANTENNAS — BALUNS — ROTATORS — NZ & VK CALL BOOKS — WORLD MAPS, etc. etc.

Mail your Order and we will send by return — well packed.

SALES BACKED BY EXPERT WARRANTY SERVICE.

Telephone: (075) 32 2644

121 NERANG STREET, SOUTHPORT, QUEENSLAND 4215
(Opp. Southport Hospital)

CHIRNSIDE ELECTRONICS

DIRECTOR: FRED SWART — VK3NBI For personal attention.



KENWOOD TS-520S
HF 160 through to 10 Metres Transceiver.
PRICE: \$689 complete with mic.

FREQUENCY COUNTERS
DX-5550 220 MHz counter including signal generator from 0.4 to 30 MHz.
Five digit LED display.
Switchable MHz to KHz.
OUR PRICE: \$198

* Special this month:

Mini Mic Compressor Modules complete with hook up wire and level control. Provides 46 DB of compression.
Size approx. 1" x 1" x 1".
OUR PRICE: \$18.00 this month only. Post free.

A WHOLE RANGE OF ACCESSORIES AVAILABLE FROM CHIRNSIDE ELECTRONICS INCLUDING SWR METERS, MIC COMPRESSORS, COAX, COAX SWITCHES AND PLUGS, MORSE KEYS.

HIDAKA

TRAPPED VERTICAL ANTENNAS for 10 thru 80 Meters

Diamond KB-105 \$109
including radial traps.
Hidaka VS-41/80KR \$110
Complete radial kit to suit
VS-41 \$32

BEAM ANTENNAS

Hidaka VS-22 duo-band 15/10m.
OUR PRICE: \$169
Hidaka VS-33 20/15/10m.
OUR PRICE: \$259



Plus others available including trapped dipoles.
Please enquire.

TWIN METER SWR METERS.
Asahi Brand ME-11X. \$25

ROTATORS BY EMOTATOR



Model 103LX \$135
502CXX \$199
1102MXX \$309

6 core cable to suit rotators \$1 per metre.

Universal antenna couplers

Extremely important, especially with modern all-solid state transceivers, is the maintenance of a very low SWR to avoid destruction of costly high-power P.A. transistors. An antenna coupler enables precise adjustment with almost any antenna.



HC 500A — 160-10m, up to 500W pep \$112

Country clients especially welcome.
Ring about our free Freight Plan on certain items.

All prices include Sales Tax, Freight and Insurance extra.
Prices and specifications are subject to change without notice.

CHIRNSIDE ELECTRONICS, 26 Edwards Road, Lilydale, 3140. Phone (03) 726 7353

All sets come with English instruction manuals and spare parts back up service.

OPEN ON SATURDAYS TILL 12 NOON.

AROUND THE TRADE

NEW BULGIN TERMINALS

Two new 4 mm terminals have been added to the already extensive Bulgin range. Designated TL10 and TL11, they are matched in appearance and design. The TL10 is insulated from the panel by moulded bushes, and the TL11 is live to the panel. Nominal current rating for both terminals is 15 amps. They feature a 2.3 mm cross hole and a deeply ridged screw-down knob, moulded in red or black Polypropylene. The top of each terminal also accepts a standard 4 mm test plug. All metal is nickel plated brass.

The Bulgin company operates a direct mailing list for all their new developments in plugs, sockets, lamp holders, fuse holders, connectors, and similar accessories, many of which are ideal for original equipment manufacturers. Details from R. H. Cunningham Pty. Ltd., PO Box 4533, Melbourne 3001.



CHANGE OF ADDRESS

Vicom International Pty. Limited have moved to new premises in South Melbourne as part of an expansion program into specialist communications electronics. The new address is 58 Eastern Road, Phone 699 6700.



MAGAZINE INDEX

Syd Clark, VK3ASC

QJ November 1977

XJ32Z/1 St. Paul Island DXpedition; Machine Arithmétique de Pascal; World Administrative Radio Conference (WARC 79); QJ WW DX Contest All-time CW and USA; The "Multi-V"; A Multi-Band Antenna; MFJ-8043 Electronic Keyer; The L1 Zapper Versatile LV Supply; MFJ-16010ST Super Antenna Tuner; QRP: A Solid State VFO for 7-14 MHz; Quads and Multi-Element Quads; An RTTY Primer, Pt. 2; Amateur Radio Station Installation Tips.

QJ December 1977

DXpedition to Nepal, 9N1MM/7; A Bulk Nicad Recharger; Results of the 1977 QJ WW WPX SSB Contest; Vacuum Relay QSK in a Commercially Equipped Station, Part 1; Put a Tape Recorder to Work in Your Shack; SSTV in Romania; Using

Your Tower as an Antenna; Solid State VFO Transmitter for 7-14 MHz; Interesting Antennas from Overseas; Getting the Most Out of Test Equipment; Amateur Radio Station Tips, Part 3; Geographical Limits for QJ Award Certificates; Story of the Month, Frank M. Koval W8RSW.

CQ January 1978

Navigating to 80 metre DX; The 22nd Annual CQ WW WPX/SSB Contest; Pictures from Last Year's WPX/SSB Contest; A Contact Printer for Printed Circuit Boards; A 4-Picogram; The RF-150 Digital Frequency Display; A Single Wire Antenna for 160, 80 and 40 Metres: A Message from the Publisher; The Kenwood TR-2200A, 2 Metre Portable Transceiver; A Marathon Heard, Not Run; Improved Selectivity for the Regency HR-2 Transceiver; An Auto-Circuit Breadboarder; Delight; More HW-8; Gloc; Gaucho Hat Antennas and Much More; Scan Station of the Month, W6WDL; Receiver Considerations for the Novice; Okino Torishima; Short Skip Charts for Jan. and Feb. 1978

HAM RADIO October 1977

Two Metre Stripline Kilowatt; Improving the Accuracy of Your Frequency Meter; S-Line Syllabic VOY System; 10-GHz Hybrid-Tee Mixer; Calculator Aided Circuit Analysis; High Performance 20 Metre Receiver; Repeater Kerschunk Eliminator; Low-Cost Power Supply; Microprocessors: Data Converters.

HAM RADIO November 1977

High Performance General-Coverage Communications Receiver; Noise Emitter Design; Calculating Preamp Gain from Noise Figure Measurements; Effects of Noise in Receiving Systems; Direct-Conversion Receiver; 20 Metre Receiver with Digital Readout; Crystal Controlled Harmonic Generator; Improved Receiver Selectivity and Main Control; Receiver Spurious Response and Its Cures; High Dynamic Range Active Mixer.

HAM RADIO December 1977

Problems and Cures for Present Day Receivers; IF Filter Converter; How to Choose TL Sub-series; 500 watt Power Supply; Voice Operated Gate; Low Power RF Wattmeter; Drift Correction Circuit for Free-Running Oscillators; Active Bandpass Filters; Phase Locked Receiving Converter.

BREAK-IN December 1977

VHF Antenna Measuring; Base Loaded Verticals; The HF Polished Gem; Wellington Branch 50 Aerial Turn Mark 1 for Balanced Aerials; A Kiwi HF; How to Handle a "Break-In" Received "Break-In"; Treatment; The Beginning.

SHORTWAVE October 1977

A Four-Band Versatile Vertical; The Polidru Story; Trees as Radiators; Unusual DX; A Simple HF/VHF/UHF Gate Dip Oscillator and Wavemeter.

SHORTWAVE November 1977

VHF Bands (Band-planning); The Datong UC/1 Up Converter; The GM3RFR Broomstick Antenna; Time Out Warning Circuits; QRP Scene 1977; Testing a Museum Piece.

RADIO COMMUNICATION January 1978

An Experimental Self-Tutor for Morse Code Using the SN74S387 PROM; A Simple Admittance Bridge; 12V to 18V Converter for the Pye Bantam; Yaesu FT301; Starting on OSCAR — Some Common Problems.

3 June 1977

Two Metre Scanner; Try the Mini-Tuner; High Frequency Utility Converter; RTTY Scrambled Memory; Build the CW Filter; The London BW Tuner; The WBB Story; Ten Watts on 2; UHF SWR Indicator; At Last a 10m Band Plan; Event Timer with a Memory; Sheet Metal Brake; The Easy Ammeter; Try a Cordcut Vertical; The IC-PC Connection; An RS232 PROM Programmer; Practical PS Design; FRG-7 Impressions; SSTV Meets the SWTP 6800; Aim Your Antenna with a Micro; Regulated Nicad Charger; Complete Repeater Control System; Transmission 'Ina Primer; Things Remembered; Digital Barcode Hunting; More Channels for the IC-225; Try a Scar'd-Talkie; Current Save Counter; Instant QSO Recall System; New PC Techniques Unleashed; How to Use ICs; Uncle Sam's Surplus List.

73 August 1977

Dual Rhombic for VHF-UHF; Microwaveguide Details; Centred Specials; Rely on Your Receiver; Build a Double Bazooka; Dirt Cheap Directional Array; Instant PS Regulation; Take Cover; Introducing the Intenna; The Zappy Vertical; A Cure for Antenna Self-Destruct; Quick Antenna Insulators; Raising a Tower; Remote Rain Gauge; Super Loop Antenna; Rock Bottom 2m Antenna; Antenna

Gain Facts; The BJK Array Revisited; Tower Installation Techniques; An Ultimate Invisible Antenna; Mountain Top Special Antenna; Firey Ender; Build a Vacation Special; Apartment Antenna Specials; Build a Unique Timer; Cooling Your Relays; A Look at Soviet Test Gear; Surplus Goodies are Still Around; The Touchtone Connection; Build a Phone Exchange; Build a Brute Power Supply; Drake Touchtone Review; Morse Radio Telephone Conversion; Solder Soldier; When the Lights Go Out; Ten-Tec Models; 100 Computer Logger; Troubleshooting a Micro; Super DVM; Build a KW Linear; Build a \$2 Drill; Unique Power Supply Tester; Instant Spares; Light Up Your Bench; Hang Ten; Using the Atlas Transceiver; PC Layout Tips; Radio Equipment Insurance; Information Management System; CW Keycode Improvements; Heath HW-2021 Review; The First Step; All about SCTS; Rotary Autopatch Dialler.

CONTESTS

Kevin Phillips, VK3AUG
Box 57, East Melbourne, 3002

CONTEST CALENDAR

May	6/8	Vermont QSO Party
	13/14	USSR "CQ-M" Contest
	20/20	YL SSBers QSO Party
	20/22	Kansas QSO Party
	27/28	Francophones Countries Contest
June	4	Townsville Pacific Festival Contest
	2/5	CHC/FHC/HTH QSO Party
	17/18	West Virginia QSO Party
July	15/16	Sunshine State—Jack Files Memorial Contest (VK4 only)

TOWNSVILLE PACIFIC FESTIVAL CONTEST 1978

This contest is promoted in conjunction with the Townsville Pacific Festival, and aims to increase activity on all Amateur Bands by stations in Australia, New Zealand, Pacific Islands and all countries bounding the Pacific Ocean.

Rules:

- Time of Contest: The contest is run for 8 days, from 0001 GMT Saturday, 27th May, to 2359 GMT Sunday, 4th June, 1978.
- Sections: A. Transmitting all bands — Phone only. B. Transmitting all bands — CW only. C. Transmitting all bands — Open. D. Transmitting VHF and UHF — VK only. E. Receiving all band — Open.
- Logs: These are to show the section entered and points claimed for each contact. This is most important, as if points claim is not completed only 1 point per contact will be allowed. VHF logs must show distance in kilometres between stations.
- Contacts: A. CW to CW contacts count as double score. B. One (1) contact per band per mcds a day only. C. No cross band contacts. D. Repeater contacts do not score.
- Awards: Perpetual Trophy is held by TARC, and it will be inscribed with the name of the winner, who will receive a smaller trophy. Overseas stations (excluding VK, P29, ZL) with the highest score will receive a "Pacific Festival" medalion. Section winners will be awarded a certificate. Commemorative QSL cards will be issued.
- Scoring — HF stations.
Scoring table — VK, ZL, P29 stations.
VK —

	1	2	3	4	5	6	7	8	P29	ZL	0
VK9	7	7	7	7	7	7	7	7	7	7	7
VK1	—	1	1	2	3	4	4	5	5	3	7
VK2	1	—	2	1	2	4	3	4	5	3	7
VK3	1	2	—	3	2	4	1	6	4	3	7
VK4	2	1	3	—	4	6	5	2	1	4	7
VK5	3	2	4	6	—	1	3	4	5	4	7
VK6	4	4	6	6	1	—	1	5	2	7	7
VK7	2	1	3	3	4	5	—	6	3	7	7
VK9	4	4	6	2	4	1	6	—	2	4	7
P29/P											
VK9	5	5	4	1	5	5	5	2	—	6	7
ZL	3	3	3	4	4	6	3	5	8	—	7

VK, ZL, P29 to other Pacific seaboard countries and islands — 1 point.

BONUS POINTS — Except VK4 stations: 15 points for contact with VK4WIT. 9 points for contacts with other Townsville stations.

BONUS POINTS — VK4 stations: 1 point per contact for working VK4WIT or other Townsville stations. (Intrastate contacts not otherwise permitted for scoring).

BONUS POINTS — Overseas stations, excluding ZL, P29: 3 points for contact with any VK station.

5 points for contact with any VK Club station. 9 points for contact with any Townsville station. 15 points for contact with any VK4WIT.

ALL STATIONS

150 metres — 5 bonus points per contact. RTTY and TV — 10 bonus points per contact. CW/CW — double points.

Scoring — VHF/UHF stations:

0-50 km — 1 point.
50-100 km — 2 points.
100-200 km — 3 points.
200-400 km — 4 points.
400 km and over — 5 points.

BONUS POINTS

VHF/UHF stations only — other than Townsville stations — Contacts with your local club station add 15 points only if your club station has contacted VK4WIT in preceding 24 hours (contact number must be recorded).

Townsville stations receive one point per contact only.

7. Identification: All station identify for the ease of scoring, e.g. (Phone) VK4WIT Townsville; (CW) VK4WIT/TVL.

Send logs to—

Townsville Pacific Festival Contest,
VK4WIT — CHC No. 6568,
PO Box 964,
TOWNSVILLE 4810,
Australia.

Closing date of entries: 23rd July, 1978.

LETTERS TO THE EDITOR

Any opinion expressed under this heading is the individual opinion of the writer and does not necessarily coincide with that of the publishers.

The Editor,

Dear Sir,
I do not readily rush into print but I do support the letters of Steve Gregory VK3OT, although I do say this, I think in South Australia we are better off in this regard. Most of our suppliers are old hands and genuine. It's the new ones that are out to make a quick buck, especially on CB gear, which doesn't interest me anyway. It is astonishing the way prices have escalated in the last two years.

I can understand the reason for your comments. I have been in the retail game and I readily appreciate both sides of the game, but believe it pays to shop around these days unless you don't mind being "taken" or have a large roll which eases the problem.

73s.

Cam Patterson VK5XR.

The Editor,

30/3/78

Dear Sir,

I was sorry to see that the letter from Jim Davis VK7NOW had been published without a footnote correcting the error he has made; which may have caused others who may be erecting a G5RV aerial unnecessary trouble.

In paragraphs 5 and 6 he claims that the textbooks and AR are wrong in giving 29 ft. 6 in. as the length of the ribbon stub. He then asserts that the correct length of 300 ohm ribbon is 32 ft. 6 in., on the strength of "hearsay evidence".

The footnote should have referred him to the article in AR in which the author G5RV states, "If 300 ohm ribbon is used allowance must be made for the velocity factor of this type of twin lead". Depending on the dielectric used for the ribbon,

the velocity factor can vary from 0.85 down to 0.65 for PVC. For the stub to be exactly 29 ft. 6 in., the velocity factor is 0.8675. For the stub to be 32 ft. 6 in., a velocity factor of 0.956 is needed, so no doubt ZL2AGU is using the TV ribbon made of two separate insulated wires held apart with spacers every six inches along the line, a very efficient stub.

Using ribbon made of solid PVC the stub length would only be 20 ft. 5 in. long.

I very much doubt that my friend Louis said that the textbooks and AR are wrong, a professional engineer with, to my knowledge, more than forty years experience dealing with aerials and installations.

Yours faithfully,
Newtown Wade VK4QW.

Max Stark VK3APZ
8 Bardia Ave., Seaford.
10/3/78

The Editor,
Dear Sir,

PIRACY v. CB

In answer to the letter from Leonard J. Shaw, page 25 AR Jan. '78, I beg leave to answer his questions and comments. My ship, as he is, as it is, has always been open to anyone with a problem, CB or not. As an ex-Scoutmaster I have fostered interest through Jamboree on the Air with many youths only to see them rush away, subject to peer group pressure, and become "good buddies". I have repeatedly advised about regulations and licensing and where there has been apparent a genuine interest in radio from a "good buddy" I have recommended novice licensing as a relatively simple way to enjoy a fairly deep involvement in amateur radio. Generally Mr. Shaw, I have wasted my time and my breath because we live in an age when nobody will listen and everybody knows better.

I take exception to the fact that I "tar all CBers with the same tired old brush". I acknowledged the fact that there are numbers, after a first blinding in CB, working towards novice and full call signs. I also acknowledge the fact that there are undoubtedly some thousands of responsible CBers interested in using the CB band for its prime purpose, i.e. short range reliable communication for chit chat, general interest groups, clubs, mobilers, minor civil emergencies, maritime small craft communications and four-wheel drivers to name a few. But, Mr. Shaw, all these genuine CB communicators and communications are being frustrated by the sheer overwhelming number of illegal unlicensed uncaring unlicensed unskilled knob flickers who continue to rout people from 27 MHz despite licensing.

I made the mistake in my previous letter (AR Nov. '76) of quoting dates of pirate invasion of 2 metre FM repeaters. There is no need. The violation of 2 metre FM repeaters in Melbourne on week nights and all weekends is monotonous in its content, repetition and continuity. "CB repeater channel 2. Come back good buddy", is now commonplace. The use of the repeater to rebroadcast AM radio or tapes and records with resultant copyright infringement, notwithstanding illegal transmission, is also becoming as common as it is on 27 MHz. Amateur satellites could be next. Clearly radio inspection regulatory action is past being a requirement — it is a desperate need.

Observation of Post and Telecommunications recruitment as advertised in the Commonwealth Government Gazette is indicative (as with so many other Depts) that the emphasis is on clerical and administrative recruitment, not technical staff with the ability to police regulations i.e. track down and secure illegal transmissions. Further, if this illegal activity is not suppressed by the authority responsible the inevitable will probably happen. Vigilante groups of either frustrated amateurs or frustrated CBers will do their own leg work and confrontations could and most likely will occur, with resultant unpleasantness.

If there is a subscribing member of the WIA in regular receipt of AR who could not be bothered signing and returning the Ministerial Petition enclosed in December and January AR, then I suggest that he has no real interest in the future of amateur radio.

Thanks to the editorial staff and contributors who make AR such a readable publication. I thought the December issue was colossal.

N. W. Lavelle VK3AHB
4 Wembley Court,
Forest Hill, Vic. 3131

The Editor,
Dear Sir,

For reasons possibly known only to themselves, Alf Chandler VK3CL, and Ivor Stafford VK3XB, seem to have taken the letter I wrote last September (which appeared in AR for November '77) as an affront to the Intruder Watch.

To clarify the situation I shall restate the reason for my original letter.

I found (and find) it strange that the greatest interference ever experienced by amateur radio (the Russian "Woodpecker") had been almost totally ignored by all journals devoted to amateur radio. I find it hard to enthuse over future international frequency allocation conventions when a signatory to the current international agreements breaks those agreements and renders whole amateur bands unusable whenever it so desires.

In the case of AR, I do not believe that a single letter from an intruder Watch Co-ordinator, in the correspondence columns some eighteen months after the interference started constitutes adequate coverage of a subject of vital importance to members — just as I would consider myself inadequately served by the national news media if man's landing on the moon had been covered by a single letter in the correspondence column some eighteen months after the event.

To paraphrase a legal maxim, not only must associations endeavour to protect the interests of signatories to the current international agreements but also to protect those interests.

Mobile News (the journal of the Amateur Radio Mobile Society) of August '77 and Pat Hawker G3VA, in his column in Wireless World of October '77 have, in fact, brought the Russian interference to the attention of their readers.

I should like to thank and congratulate Ivor for his fine letter in February AR. Maybe you're right, Ivor. Maybe we can't force the authorities to act on our reports. Maybe we can't force the European Common Market to change the entry terms for our goods either, but I hope we do a little more than fill out the odd prescribed form. I'd prefer continued friendly persuasion to force anyone. Who knows? — we don't appear to have a lot to lose by trying.

The Editor,
Dear Sir,

With reference to the letter from Steve Gregory (VK3OT) in the March copy of Amateur Radio, it is felt that his accusations regarding the amateur radio retailers should not be allowed to go unchallenged.

He indicates that an increase in price of the PL-2100B is "nearly 50 per cent" (actually 44.5 per cent) since 1976, and yet in only the past one year:

- The Australian inflation rate was approximately 9 per cent.
- The effective increase in value of the Japanese yen against the Australian dollar was approximately 24 per cent.
- The cost of units supplied to Australian dealers from Japanese sources has risen almost 20 per cent.

The cumulative net effect of this is a 62 per cent rise in only one year!

Despite these enormous cost increases, Dick Smith Electronics has seen fit in many cases to actually reduce the price of certain Yaesu lines below the price they were selling for last year and those of you who read American magazines will notice that our prices are now comparable to the prices the American amateur has been enjoying for years (not forgetting US prices are all plus applicable sales tax).

This company is, and will continue, to supply the Australian amateur operator with the best quality equipment at the lowest possible prices, including full warranty protection.

Yours faithfully,
Dick Smith Electronics Pty. Ltd.
J. Dennis, Amateur Radio Manager.

ANNOUNCING — *Our Entry into the field of* AMATEUR EQUIPMENT



MICROLINK PTY. LTD.

OF FRANKSTON, VICTORIA

(Managing Director: LES JENKINS)

PRODUCTS AVAILABLE

- | | Price* | | Price* |
|--|----------|---|---------|
| 1. THE POPULAR ATV FET CONVERTER
for 70 cm or 50 cm operation | \$25.00 | 6. ANTENNAE — 70 cm & 50 cm: | |
| | | OPTION 1 — | |
| | | 13 dB1 Long Yagi, fully assembled and tested (length 2 metres) | \$45.00 |
| | | OPTION 2 — | |
| | | 16 dB1 Long Yagi, fully assembled and tested (length 3.6 metres) | \$55.00 |
| | | OPTION 3 — | |
| | | Stacked Arrays of above Antennae inc. feed harness and all mounting hardware | POA |
| 2. ATV EXCITER — 100 mW (70 cm) with provision for direct video modulation (including crystals) | \$55.00 | 7. LINEAR POWER AMPLIFIER — 40W & 80W PEP 70 cm, 5 dB gain, VSWR protected BNC input and type N output, connectors. No T/R switching provided unless requested | POA |
| 4. POWER AMPLIFIER & MODULATOR ASSEMBLY — 12W sync. tip (not inc. Heat Sink) | \$118.00 | 8. POWER SUPPLY, 13.8V 4 amp (S.E.C. approved). Robust! | \$65.00 |
| 5. 12W ATV TRANSMITTER — Complete, fully assembled and tested | \$250.00 | | |

Contemplating a Move to 1296 MHz?

AVAILABLE SOON!

1296 MHz CRYSTAL LOCKED CONVERTER, inc. low noise RF amplifier with option for all popular IF frequencies.

LOW LEVEL (10 mW) 1296 MHz EXCITER, inc. modulator and microphone amplifier (16 F3)

LOCAL OSCILLATOR ASSEMBLY FOR 1296 MHz APPLICATION (including drive level monitor output) — 5-10 mW output.

ULTRA LOW NOISE (1 dB) HIGH GAIN FET PRE-AMPLIFIER for 70 cm or 50 cm.

*ALL PRICES ARE INCLUSIVE OF SALES TAX AND SHIPPING COSTS IN AUSTRALIA.

MORE TO COME! WATCH YOUR NEXT ISSUE OF AR!

ENQUIRIES TO:

MICROLINK PTY. LTD.

12 ROSELLA STREET, FRANKSTON, VICTORIA 3199

TELEPHONE: MELBOURNE 781 3577
A.H.: 783 4069
544 7929
288 1857

TELEPHONE: SYDNEY 211 4549
A.H.: 398 2117

WIN A TRIP FOR TWO TO TOKYO

YES! Every purchaser of fabulous YAESU equipment receives an entry form in the Dick Smith — Yaesu 'Win a trip for two to Tokyo' competition. Buy Yaesu, use your head and you could be jetting your way to Tokyo...



FLYING QANTAS

AUSTRALIA'S AIRLINE TO THE WORLD.

You'll stay at a luxury Tokyo hotel, and visit the amateur's paradise — Akihabara. You'll be taken on a guided tour of the incredible Yaesu-Musen factory — the home of Yaesu. It's the amateur's dream of a lifetime — and it could come true for YOU!

TOTAL VALUE \$3000

Full details including conditions of entry are available at your nearest Dick Smith store or participating dealer. Contest closes July — so to be eligible call in now and find out how YOU could win this incredible trip.

Now, more than ever, it pays to buy Yaesu from Dick!

COMPARE DICK'S YAESU PRICES: Remember these include the latest Japanese price increases. Others may not — or not have stock. We have!

FT-101E No need for introductions — the favourite of millions around the world. 240V & 12V supply, complete with microphone. Cat D-2860 ... \$895.00
 FL-2100B The companion 1.2kW linear to the 101E. Plugs straight in, 240V operated. In-built metering. Cat D-2546 ... \$540.00
 YO-100 Monitor Scope for 101. Check YOUR transmission. Cat D-2862 ... \$330.00
 YD-844 Base microphone. Completes the Yaesu station. Cat C-1116 ... \$39.00
 YC-500S 500MHz digital frequency counter. Accurate, 240/12V. Cat D-2892 \$380.00
 FT-301 The all solid-state HF rig. 12 volt supply, ideal for mobile or base use. An outstanding amateur rig. 160 — 10 metres. Cat D-2870 ... \$995.00
 FP-301 240V power supply & speaker for FT301. Cat D-2872 ... \$170.00
 YO-301 Monitor Scope for 301. Matches style. Cat D-2882 ... \$355.00
 FT-301S Novice version FT301. 20W PEP, can be crystal locked. The ideal way for the novice operator to get onto the air. Cat D-2880 ... \$710.00
 FL-110 200 watt linear for the FT301S. Cat D-2884 ... \$210.00
 FT-7 The new HF mobile transceiver. 80 — 10m, 20 w. It's a great way to go mobile and a cheap base station, too. Brilliant set. 12V. Cat D-2866 ... \$515.00
 FT-227R 2 metre memorizer set. 800 channels, simplex or repeater. Mobile operation (12V) with 1 or 10W output (switchable). Cat D-2890 ... \$335.00
 FT901D This must be the ultimate. Beautiful HF set for all modes (even FM) runs off 240V, 6146 finals. Outstanding specifications. Cat D-2854 ... \$1275.00
 DC—DC converter: Use the 901D as a mobile. Cat D-2856 ... \$75.00
 FRG-7 Solid state communications receiver using Wadley Loop. 12/240V, superb stability, makes an ideal ham receiver too. Cat D-2850 ... \$350.00
 QTR-24 24 Hour Ham clock for instant time zone conversion. Cat X-1054 ... \$33.00

STOP PRESS! 'Getting to know OSCAR' as reviewed in the last issue of Amateur Radio is available from Dick Smith Electronics. Find out more about this fantastic method of communication. Supplies of this book are limited, so get your copy NOW! Getting to know OSCAR — Cat. B-2220 ... \$5.50

DON'T FORGET: Dick stocks just about everything the amateur operator could possibly want. Antennas antenna accessories antenna mounts meters CROs signal generators test equipment power supplies tools co-ax cables soldering irons and accessories printed circuit boards transformers instrument boxes and cases relays switches knobs — bezels heatshinks cable & wire IC coils — books converters wires & cables batteries etchants crystals and let's not forget the mundane things like resistors capacitors transistors diodes ICs SCRs Valves Inductors etc etc etc!

SAVE \$50+ ON AN ELECTRONIC KEYS



Most keys cost at least \$80 — PLUS the paddle. Here's one you can build for half that including the paddle. Battery operated, complete kit. Has oscillator built in. Incredible value, see design in E.A. March. (battery extra). Cat. K-3470

COMPLETE KIT INCLUDING PADDLE ONLY \$37.50

PADDLE ONLY: Want to make your own? The paddle is available as a separate item. Cat D-7103 ... \$17.50
MORSE CODE CASSETTES: Learn Morse the easy way. Graded steps to 15WPM. Cat D-7106 ... \$7.90

DICK SMITH ELECTRONICS



SHOP HOURS
 Mon-Fri 9am-5pm
 Sat 9am-12pm
 (Incl. public holidays)

bankcard
 welcome here

Order value
 \$1-\$29.99 \$1.00
 \$30-\$49.99 \$1.50
 \$50-\$99.99 \$2.00
 \$100 or more \$2.50

SYDNEY
 125 York St.
 City, Ph 29 1126

147 Hume Hwy,
 Chullora, Ph. 642 8922.
 We've moved!

SYDNEY
 162 Pacific Hwy.
 Green Hall, Ph 439 5311
 Ample parking at door

SYDNEY
 30 Green St.
 Pyramatta, Ph 683 1123
 1st floor, friendly store

MELBOURNE
 399 Lonsdale St.
 City, Ph 67 8626
 New range in town!

MELBOURNE
 656 Bridge Rd.
 Richmond, Ph 42 1614
 Easy access, huge stock

BRISBANE
 166 Logan Rd.
 Standa, Ph 291 6233
 Open 8-10AM

ADELAIDE
 203 Wright St.
 Standa, Ph 212 1962
 Now Open 9am-5pm

MAIL ORDER DEPARTMENT, PO Box 747, Cronulla, NSW 2065. Please call 439 5311. Print & Pack extra.

WE HAVE DEALERS RIGHT ACROSS AUSTRALIA THERE'S ONE NEAR YOU!

I'M DESPERATE AGAIN!



I've just discovered a pile of amateur radio equipment in the corner of the warehouse that everyone (including my lovely computer) had forgotten about. Nearly fired the computer — but that would break up a beautiful relationship . . .

To move this stock, I have decided to sell it off **NEAR, AND EVEN BELOW, COST.** That's right — I'm going to lose money — but I desperately need cash to buy new stock.

So you reap the benefit. Check the savings on the equipment listed. Then hot-foot it to your nearest Dick Smith store before you miss out. Remember some stock is definitely limited. Hurry!

SOME UNITS MAY BE SLIGHTLY SHOP SOILED — BUT WE WON'T CHARGE FOR THE DIRT!

D-3009: Multi quartz 16 2m transceiver
Comes with 1 set of rocks; 23ch capacity

Was \$228 Now \$199.50
SAVE \$28.50 while stocks last

D-3040: IC202 2m SSB & CW transceiver
144—145MHz, portable. 3watts

Was \$219.50 Now \$189.00
SAVE \$30.00 while stocks last

D-3100: TS700A AC/DC 2m, fm/ssb/cw
Outstanding value transceiver, 144—148

Was \$725.00 Now \$575.00
SAVE \$150.00 while stocks last

D-3110: SP-70 external speaker
Matches TS600 & TS700A. Classy!

Was \$48.60 Now \$32.00
SAVE \$16.60 while stocks last

D-3106: TS600A 6m version of above
10 watts, all modes 50 — 54MHz

Was \$699.00 Now \$565.00
SAVE \$134.00 while stocks last

D-3200: TR-3200 UHF transceiver
Go up to 432MHz: FM unit.

Was \$305.00 Now \$249.00
SAVE \$56.00 while stocks last

D-3211: Mobile mount — 2200/3200/1300
Keep your rig from sliding around the floor!

Was \$16.80 Now \$15.00
SAVE \$1.80 while stocks last

D-3210: TR2200 hand held fm, 2m
12 channels (1 suppl) 2W output.

Was \$192.00 Now \$179.00
SAVE \$13.00 while stocks last

D-3215: TR-7200 2m fm transceiver
22 channel (1 suppl) rugged construction

Was \$260.00 Now \$199.50
SAVE \$60.50 while stocks last

D-3400: TR-7400 2m fm synthesised
25 watts output, 800 channels

Was \$429.00 Now \$395.00
SAVE \$34.00 while stocks last

D-2807: Daiwa SR-9 2m receiver
tuneable, can be converted to other bands.

Was \$118.00 Now \$99.50
SAVE \$18.50 while stocks last

D-5500: HC-500 antenna tuner
500W max, perfect 1:1 match to any trans.

Was \$166.50 Now \$115.00
SAVE \$51.50 while stocks last

D-3502: TV-502 2 metre transverter
plug into 520, 820 & many others.

Was \$275.00 Now \$245.00
SAVE \$30.00 while stocks last

D-2114: CW FILTER YG-88C for TS820
500 Hz filter sharpens CW response.

Was \$64.00 Now \$49.00
SAVE \$15 while stocks last

D-5202: SP520 remote speaker for TS520
Matches TS-520 style. Looks good!

Was \$39.50 Now \$35.00
SAVE \$4.50 while stocks last

ROCK BOTTOM ROCK PRICES . . .

I must have rocks in my head to sell them at these ridiculous prices. Crazy!

D-6321 Rptr 1
D-6322 Rptr 2
D-6323 Rptr 3
D-6324 Rptr 4
D-6325 Rptr 5
D-6326 Rptr 6
D-6327 Rptr 7
D-6328 Rptr 8
D-6329 Rptr 9
D-6330 Simp 40
D-6335 Simp 50
D-6336 Simp 51

Suit Multi 7: should suit
TR2200A & 2200G (some
xtals may need re-trimming)
Tx xtls fit KP-202

Rx xtls fit Daiwa SR-9

WERE: \$9.00 NOW: \$4.75

SAVE \$4.25

\$4.75
Pair

D-6421 Rptr 1
D-6422 Rptr 2
D-6423 Rptr 3
D-6424 Rptr 4
D-6425 Rptr 5
D-6426 Rptr 6
D-6427 Rptr 7
D-6428 Rptr 8
D-6430 Rptr 10
D-6436 Simp 51
D-6438 Rptr 9

Suit Multi 16 & Multi 11,
receive xtal MAY fit
KP202.

Rx xtls fit all ICOM units
with trimmer adjustment

WERE: \$9.00 NOW \$4.75

SAVE \$4.25

\$4.75
Pair

D-6340 Chan 2
D-6340 Chan 8
D-6340 147.0 Rx
D-6340 145.9 Tx
D-6340 146.5 Rx

Fit IC-22; Rx xtls may fit
Multi 11 & Multi 16 with
trimming

\$4.75
Pair or each
as applies

D-6278 8.7515
D-6283 8.8830
D-6288 8.8800
D-6273 8.7300

Fit FT-101 series —
novice xtls

\$8.00
each

D-6182 28.2MHz

Experimental xtls, some can
be used for converting 'CB'
to novice frequency.

\$7.00
each

D-6290 35.895MHz

Originally for TS520 (S),
use as experimental xtls.

\$14.50
\$3.00
each

NOTE! Where it is suggested that crystals from one unit may fit another, this information is supplied on an advisory basis only, and cannot be guaranteed.

XXXX SPECIAL

APOLLO LINEAR



was \$299⁵⁰
now \$199⁵⁰

Cat D-2544.

The Firebird: 200 watts of
muscle on 40 to 10 metres
from just 3 watts of drive.
Features receive pre-amp &
rugged construction. 240V.

SAVE \$100⁰⁰

ONLY A FEW LEFT — BE QUICK FOR THIS ONE!

DICK SMITH ELECTRONICS



SHOP HOURS:
Mon-Fri: 9AM - 5:30PM
Sat: 10AM - 12 noon
Sundays: 10am - 4pm

bankcard
welcome here

Order online: **PAK Charge**
1300 274 444
1300 274 444
1300 274 444
1300 274 444

SYDNEY
125 York St.
City Ph 29 1126

147 Hume Hwy.
Oxley Ph 642 8922.
We've moved!

SYDNEY
162 Pacific Hwy.
Gore Hill Ph 439 5311
Ample parking at door

SYDNEY
30 Grove St.
Parramatta Ph 683 1133
1st floor, friendly staff!

MELBOURNE
790 Leicester St.
City Ph 67 9834
New right in town!

MELBOURNE
550 Brabour Rd.
Richmond Ph 42 1614
Easy access, huge stock

BRISBANE
165 Logan Rd.
Borinda Ph 291 0233
Opens 8:30AM

ADELAIDE
202 Wright St.
City Ph 212 1962
New Open Store!

MAIL ORDER DEPARTMENT PO Box 747, Cronin West, NSW 2065 Phone 439 5311 Post & Pack extra

WE HAVE DEALTHS RIGHT ACROSS AUSTRALIA THERE'S ONE NEAR YOU!

JOHN MOYLE MEMORIAL NATIONAL FIELD DAY CONTEST RESULTS — 1978

24 HOUR DIVISION

SECTION (a) — TX PHONE

VK4Z	2282
VK1X	1927
VK4AYL	937
VK1YQ	522
VK4AHO	190
VK4ABQ	140

SECTION (b) — TX CW

VK3XU	570
-------	-----

SECTION (c) — TX OPEN

VK5OR	1820
VK7TJ	1436
VK4AAR	1371
VK3AYL	683

SECTION (d) — TX MULTI-OPERATOR PHONE

VK3ATL	12852	16 ops.
VK4AAQ	4404	4 ops.
VK1ACA	4373	4 ops.
VK3BML	3888	10 ops.
VK5KT	3559	9 ops.
VK3ANR	3079	4 ops.
VK5LZ	2995	3 ops.
VK3XK	2911	5 ops.
VK2BXD	2605	4 ops.
VK3BGD	2459	4 ops.
VK7AX	752	2 ops.

SECTION (e) — TX MULTI-OPERATOR OPEN

VK3APC	7706	14 ops.
VK3ATM	7174	16 ops.
VK4WIT	5639	12 ops.
VK2WG	4825	8 ops.
VK1WI	3737	6 ops.
VK2ADZ	3594	6 ops.
VK5WC	3254	6 ops.
VK2AWF	3201	6 ops.
VK3DC	1858	6 ops.

SECTION (f) — TX VHF MOBILE/PORTABLE

VK1ACA	1844
VK3AVJ	1732
VK3BR	1744
VK7ZLB	363
VK4ADW	362
VK4ZJP	344
VK3AZO	292

VK4PV	282
VK4HS	120

SECTION (g) — HOME TX STATIONS

VK5QX	1465
VK3YB	1080
VK3BME	280
VK1NAO	275
VK3ZCB	220
VK7NFR	180

SECTION (h) — RECEIVING OPEN

S. W. Russell (VK3)	1715
E. W. Trebilcock L300042	120

6 HOUR DIVISION

SECTION (a) — TX PHONE

VK3BIR	1015
VK2AHV	801
VK4QH	776
VK1GM	679
VK4ADC	614
VK2JM	517
VK2ARZ	389
VK7HK	302
VK3EF	175

SECTION (b) — TX CW

NIL

SECTION (c) — TX OPEN

VK2EL	1054
VK3BIR	1045
VK1RC	802
VK3RV	679
VK3VF	638

SECTION (d) — TX MULTI-OPERATOR PHONE

VK4PJ	784	2 ops.
VK3ATO	591	3 ops.
VK4AMA/MM	577	2 ops.

SECTION (e) — TX MULTI-OPERATOR OPEN

VK3UV	1552	3 ops.
VK5KR	1276	6 ops.

SECTION (f) — TX VHF MOBILE/PORTABLE

VK3ZJS	779
VK4ZMG	564
VK4ZCB/2	515
VK4OT	316
VK3YGB	310

VK2EL	92
VK6ZHM	44

SECTION (g) — HOME TX STATIONS


VK2BVJ	600
VK3YLD	330
VK3KS	310
VK7RY	120
VK8TU	105

SECTION (h) — RECEIVING OPEN

R. W. Middleditch (VK3)	410
-------------------------	-----

CHECK LOGS

VK3AEU, VK3YAY, VK5QX, D. J. Forbes L30728.
These results are provisional, as leading scores are subject to further checks.




VK3AUI checking logs.

GEELONG AMATEUR RADIO CLUB VK3ATL OPERATED FROM MOUNT COWLEY IN THE OTWAY RANGES



Geelong ARC 15 Mx operator Daryl VK3AQR hopping in for his 'chop'.



Mike VK3ASQ was GARC's 6 and 2 Mx operator using an FT620B and FT221.

QSP

GOLD COAST HAMFEST

The Gold Coast Radio Club will hold a Hamfest on Saturday, 29th July. The venue will be a country property and in addition to the usual trade displays there will be a wide range of side shows and old-time dancing. The Hamfest will be used as a means of publicising amateur radio to the public and local organisations. The organiser is Ken Ayers VK4KD, 121 Nerang Street, Southport 4215.

ZL 10 METRE BEACON

The 10 metre beacon ZL2MHF situated on Mount Climie is now operating on a frequency of 28.23 MHz. In order that the propagation on the 10 metre band can be investigated it would be appreciated if signal reports of the beacon could be forwarded either by the Bureau or direct to the Secretary, NZART Branch 63, PO Box 40212, Upper Hutt, New Zealand.

LINEARS IN CANADA

According to Ham Radio Jan '78 point of sale control for linear amplifiers has been instituted by the Canadian Department of Communications. All buyers of linears must sign a special form which is forwarded to DOC for checking purposes.

PREFIXES

If you hear a prefix in the series HSA-HS2 this may be from an operator in newly Independent Bophuthatswana. No ITU confirmation was available.

ARE YOU REPORTING INTRUDERS TO THE INTRUDER WATCH CO-ORDINATOR? IF NOT — WHY NOT?

IARU NEWS

The next IARU Region 3 Conference will be held in Bangkok from Friday, 6th October, to Tuesday, 10th October, 1978. The host society will be the Radio Amateur Society of Thailand, under the capable leadership of President Kamcha Chotikul HSWIR and Secretary Edward Rose HSLIAF.

The WIA will be represented by the Federal President, David Wardlaw VK3ADW. David Rankin 9HTRM/VK3QV is Secretary of the R3 Association, and the Directors are Masami Saito JH3PJ, Michael Owen VK3KJ, Tom Clarkson ZL2AZ, and Tom Lian Hui 9V10D.

The latest member of the ITU is the Republic of San Marino. The membership now totals 153.

Two new members of the IARU Region 3 Association are the Papua New Guinea ARS and the Korean ARS Inc. The President of PNGARS is Smith P29J5 and of KARL is Mrs. Young-Hee a HM1YL.

A new member to IARU is the Royal Omani ARS, making the total 98. The Organisasi Amatir Radio Indonesia has applied for membership.

IARU Region 1 has three new members, Botswana ARS, The AR Association of Bahrain and the Sierra Leone ARS, making that Region's total 46 altogether. Three additional societies are expected to join Region 1 in the near future — The Turkish Radio Amatirleri Cemiyeti, the Royal Jordanian Radio Amateur Society and the Royal Omani ARS.

IARU Region 2 next conference is due to be held from 3rd to 8th September 1978 in Panama City and the Region 1 conference in Hungary will have been concluded when you read this. All these Regional conferences are triennial.

Acknowledgements for most of this to IARU Region 3 Newsletter No. 6.

INTRUDER WATCH

All Chandler, VK3LC

METRE BAND CLEARED OF FOREIGN BROADCASTS

Wouldn't it be wonderful to read the above one day? It could well come true if enough of us were to lodge formal complaints through the WIA Intruder Watch network, so that our P. and T. Department could initiate action at the international level in line with the other administrations who are already working on it.

This month would you please co-operate by letting me or your Divisional Co-ordinator have specific reports on the following broadcast stations:

7010—Radio Peking — best identified in English at 0630Z, 2055Z, 2208Z, but has been heard at 1630Z.

7065—Radio Tirana — identifies in English at 0630Z, 2055Z, 2208Z, but has been heard at 1630Z.

7070—Radio Republic Indonesia — identifies in English at 1200Z and 1300Z.
Intruder Watch Co-ordinator.
All Chandler VK3LC

In case you do not know your Divisional Co-ordinator, here is the list—

VK1AOP—Ted Pearce, 45 Carnegie Cres., Narrabeen, 2604.

VK2AFG—L. Weldon, 11 Raymond Ave., Northmead, 2152.

VK3XB—Ivor Stafford, 16 Byron St., Box Hill, 3128.

VK4XK—Murray McGregor, 6 Murray St., Red Hill, 4058.

VK5LG—Leith Cotton, 64 Werona Ave., Parkholme, 5043.

VK6WT—David Couch, 9 The Grove, Wembley, 8014.

VK7MX—Max Ives, PO Box 12, Devonport, 7310.

VK8HA—Henry Andersson, Box 1418, Darwin, 5794.

AWARDS COLUMN

Brian Austin, VK5CA

P.O. Box 7A, Craters SA, 5152

GENERAL RULES FOR THE ARI HF AWARDS (as received)

The following general rules apply to all HF awards issued by the Associazione Radiotecnica Italiana (ARI) and should be read together with the conditions which govern each individual certificate.

1. All enquiries should be addressed to the ARI HF Awards Manager, G. Nuccitelli I8KDB, via Fiume, 31-00127 Napoli, Italy, together with one IRC (2 IRC for airmail reply outside of Europe).

2. ARI HF Awards will be issued to any amateur who will submit to the manager—

A letter, dated and signed, with applicant's name, address and call. He must certify to have complied with all rules governing amateur radio service in his own country and to have kept fair play and good sportsmanship in operating towards the Award for which the application is claimed.

The complete list of QSLs, with call sign, date, frequency, reports, time and type of emission (CW, AM, SSB, RTTY).

QSL cards for checking.

10 IRC or \$1 for foreign applicants. The "Guglielmo Marconi Award" is free (only mail fee).

QSL cards must be submitted without corrections, erasures or additions and must be clearly readable. If the type of transmission is not shown, two figures (RST) count as Phone (AM, not SSB) and three (RST) as CW.

3. To get an award in a specific class, the candidate must show the corresponding data in clear manner.

4. Following decisions of IARU Region 1, all foreign applicants can avoid to send QSL cards by submitting a check list of the cards duly Amateur Radio Society. ARI HF Manager reserves the right to check, on request, one or more QSLs.

5. ARI HQ decisions are final.

6. Any falsification of cards will result in disqualification.

7. Application shall be sent to the address of ARI HF Award Manager as per point 1. It is suggested in order to safeguard your QSLs, etc., to send applications by registered mail. These rules apply from 1st January 1977.

CERTIFICATO DEL MEDITERRANEO (CDM)

1. The CDM is issued to those amateurs who can show confirmation of a two-way contact on the HF bands from 1-5-1952 with

(a) A fixed amateur station in at least 22 countries of the list (pay attention, in the list there is no peninsula Italy).

(b) At least 50 amateur stations of peninsula Italy (total 72 QSL).

2. The same station may be worked once only.

3. The CDM is issued in 2 classes:

(a) Mixed (AM, SSB, CW, RTTY).

(b) Phone only (AM, SSB).

4. The minimum reports considered are: RST 338 and R3 33.

List of countries:

Spain	Crete
Balearic Islands	Mount Athos
Ceuta and Melilla	Turkey
Morocco	Syria
France	Yugoslavia
Algeria	Albania
Corsica	Malta

Sardinia	Gibraltar
Sicily	Cyprus
Lebanon	Monaco
Egypt	Tunisia
Greece	Israel
Dodecanese Islands	Libya

CERTIFICATO DEL MEDITERRANEO/SWL (CDM/SWL)

1. The CDM/SWL is issued to those SWL who can show confirmation of a HRD since 1-1-1960 of 14 countries of the CDM list.

2. The award is not divided into classes.

"BACK TO DARWIN AWARD"

100 awards will be issued by the Darwin Amateur Radio Club for working Club Members in the greater Darwin area during the month of May 1978, which is the official "Back to Darwin" month of festivities which marks the completion of the rebuilding of Darwin after cyclone "Tracy" which devastated the city on Christmas Day 1974.

Requirements for the issue of the award:

VISITING AMATEURS:

Free visiting amateurs after working five club members in the greater Darwin area on VHF, HF, or eye-ball QSO with five club members.

All VKs stations outside one kilometre radius of Darwin, and all other VK, P29, and ZL stations contact five club members in the greater Darwin area on any band two CW or three phone contacts. Cost fifty cents or 6 IRCs.

DX STATIONS:

Work three CW and two phone club members in the greater Darwin area. Cost 15 IRCs.

LOGS:

Send a list of stations worked stating call sign, date, band, and time in Zulu. Do not send QSL cards.

SEND LIST TO:

Awards Manager, c/- Box 1418, Darwin, N.T. 5794.

20 YEARS AGO

Ron Fisher, VK3OM

APRIL 1958

"Is the Australian Amateur Abreast with Communication Progress", so asks the Editorial page of April 1958 Amateur Radio, Communication Progress is defined as general developments in the world of commercial and amateur communications. Perhaps the most interesting statement is reflected in the last paragraph of the Editorial. "Your Executive has assiduously pressed for issue of 'Novice' licence. Our reasons are not altogether selfish, a fact that is borne out by the support we have received from the licence services who realise that in an emergency the Amateur is a trained specialist capable of immediate assimilation into the communication branch".

Propagation Study on 3.5 and 7 MC. Hans Albrecht put forward some thoughts on long distance low frequency DX working. The Chordal-Hop theory suggested that the wave could be reflected along the ionospheric layer without touching the ground.

VKEEC's Amateur Television, part two, discussed the Vidicon Camera with complete details of its construction including details of the deflection coils and viewfinder.

Results of the 1957 VK-ZL DX Contest were announced. The all time winners on CW were VK's 2GW, 3DO, 4NL, 5KU, 6RU and 7UW. Australian top score was VK9KKX. In the phone section, VK's 2AOU, 3HL, 4TN, 5WP, 6RU, 7LZ and 9BW.

Frank O'Dwyer VK3OF reported in his VHF notes that six metres had been open to JA with signals peaking over 59. Also VK3's were picked up to KHS, in one instance using only 5 watts and a dipole. SWL, George Palmer of Williamstown, Victoria, had heard mobile police cars from Kansas on 45 MHz.

Two reports of alert amateur operators aiding emergency situations were published in April 1958. AR VK7AL picked up a distress signal from a motor cruiser off the New South Wales coast. The message was relayed to a freighter which located the vessel and towed it to port. In Queensland, amateur operator Dr. J. Kelly, no call sign mentioned, cleared a radio link being jammed by ZL amateurs operating on the frequency.



A big wave maker in the world of amateur radio . . . FT-101E HF transceiver



from Yaesu
and Bail — New shipment with more effective noise blanker
exclusive to Bail Electronic Services.

The success story of the export quality FT-101 must make world amateur radio history. First produced in 1970 the FT-101 has been refined and improved to make it better than best for your money. The latest FT-101E represents tried and proven performance and real value. You'd have to say it will be the best selling HF amateur transceiver in the world.

The FT-101E can be modified to suit novice requirements.

It comes complete with a **more effective noise blanker specified by, and exclusive to, Bail Electronic Services**; R.F. Speech Processor, Calibrator, matching Yaesu Hand Microphone, eight pole SSB filter, 12v DC-DC converter as well as **234v AC** operation with Australian approved 3 core cable and 3 pin plug, **factory produced English language handbook** (not a photo-copy!), spare plugs and connectors, etc.

Features:

- Built-in AC & DC power supplies
- Built-in RF-speech Processor for increased talk power (E model only)
- 260 Watts PEP SSB, 180 Watts CW, & 80 Watts AM
- Factory sealed, solid state VFO for optimum stability and accurate 1 kHz readout
- Effective Noise Blanker, threshold adjustable, for elimination of noise spikes
- Built-in, fully adjustable VOX
- Automatic break-in CW operation with sidetone
- Selectable 25 kHz and 100 kHz calibrator
- ± 5 kHz receiver clarifier w/separate ON/OFF switch
- Built-in WWV/JJY reception
- Heater switch to shut off final tubes for conservation of current drain
- Reliable easy to operate lever switch
- Adjustable carrier level for tune-up and novice operation
- Built-in speaker

- High-Q, permeability tuned, RF stages to provide the performance required even in base station operation
- Includes dynamic, hand-held type microphone
- Indicator lights for internal VFO and clarifier operation
- Eight pole SSB filter for unparalleled selectivity on today's crowded bands
- All-mode operation — SSB, CW, & AM
- Built-in internal crystal control provision and Dual VFO adaptor
- Complete line of compatible accessories for flexible station design

Price \$895.00 — 90 day warranty. Price includes sales tax. Freight and insurance extra. Prices and specifications subject to change without notice.

Write for new Yaesu Catalogue detailing this and other sets in the Yaesu range. Please include 40c postage.

JAS7778-48

bail ELECTRONIC SERVICES
FRED BAIL VK3YS
JIM BAIL VK3ABA

60 Shannon St., Box Hill North,
Vic., 3129. Ph. (03) 89 2213

Yaesu agents in Australia since 1963

Radio amateur equipment from B.E.S. also sold by —

W.A.	Radio Communication Services, H. R. PRIDE, 26 Lockhart St., Compo, 6152	Ph. 450 4379
	WILLIS TRADING CO., 429 Murray Street, Perth 6000	Ph. 21 7609
S.A.	FARMERS RADIO PTY. LTD., 20 Stanley St., Plympton 5038	Ph. 293 2155
TAS.	C. T. ELECTRONICS, 31 Westbury Rd., South Launceston 7200	Ph. 44 4773
	PRINS RADIO, 123 Argyle Street, Hobart 7000	Ph. 34 6912
N.S.W.	Aviation Tooling, STEPHEN KUHLE, 104 Robey St., Mascot 2020	Ph. 667 1650
	Amateur & Novice Comm. Supplies, W. E. BRODIE, 23 Dalray Street, Seven Hills 2147	Ph. 624 2691
	DIGITRONICS, 166 Parry St., Newcastle West 2302	Ph. 69 2040
	RIVERCOM, Sid Ward, 9 Copland St., Wagga Wagga 2650	Ph. 21 2125
QLD.	H. C. BARLOW, 92 Charles St., Aitkenvale, Townsville 4814	Ph. 78 8179
	MITCHELL RADIO CO., 58 Albion Rd., Albion 4010	Ph. 57 8830
A.C.T.	QUICKTRONIC, Jim Bland, Shop 11, Altree Crt., Phillip 2606	Ph. 81 2824
		82 2864

electronic imports

GFS FOR THE BEST AT LESS

GREG WHITER
VK3CA

THE ANSWER TO THE NOVICE'S DREAM AT A NOVICE'S PRICE

FT-7

FEATURES:

Modern compact styling for easy under-desk mounting.
Size 73mm x 80mm x 29mm.
95 to 10 metre operation.
VFO controlled.
Noise Blanker that really works.
Ideal for fixed channel operation.
Ideal for the shack or the mobile at a price that you can afford.
Only \$548 including mobile mount, microphone and cables.



Where do you get
as 80 to 10 metre trapped vertical
antenna complete with guy ropes
and radial traps for only \$1137
At GFS of course. *
KB-105 — \$113.



Sick of yelling your
head off at those rare
DX stations while others
are getting 5/9 reports
from them? Then get
with all The manufacturers
plate 14dB forward gain and 26dB
front to back ratio.



SO-20 — 20 metre Swiss Quad — \$255
SO-15 — 15 metre Swiss Quad — \$137
SO-10 — 10 metre Swiss Quad — \$128

ACCESSORIES FROM GFS

FS-301 HF In-line power and SWR
meter. 3 ranges: 50, 200, 1000W — \$49
FS-302 VHF In-line power and SWR
meter. 50, 170MHz — \$58
SWR-15 SWR Field strength meter 3.5 to
150MHz — \$15.50
SWR-200 DSKR Block SWR/POWER
meter — \$69
QTR-24 24 Hour World Clock — \$31.
SD-FB low loss double shielded foam
dielectric Coax, 2 dB loss per 100 ft.
at 100MHz. \$1.20 per metre.
LP-30 low pass filter, 50W power
capability. Ideal for novice use — \$9.50.
VS-1 mini mic compressor, 46dB of
compression — \$25.
MC-601 Katusmi mic compressor — \$45.

LOOK AT THESE PRICES AND COMPARE!!

FT-101E	160 10m x 200W TC	\$839
FT-301	160 10m x 200W	\$878
FT-301S	160 10m x 25W	\$848
FT-7	80 10m x 25W	\$548
TS-520S	160 10m x 25W	\$699
FL-2100B	80 10m x 25W	\$539
FL-110	160 10m x 25W	\$539
FRG-7	160 10m x 25W	\$325
YO-201	160 10m x 25W	\$375
YO-100	160 10m x 25W	\$263
YP-150	160 10m x 25W	\$97
FP-301	160 10m x 25W	\$163
FT-9010M	160 10m x 25W	\$1475

WHY PAY MORE?

TC = Tuning Circuit

Linear Amp

Series Monitor Scope

Dummy Load/Wattmeter

201 series 20Amps PS

160 10m x 25W TC

FAMOUS YAESU FT-101E TRANSCEIVER



Yaesu's latest model FT-101E
from GFS comes to you at a
price that is very hard to beat.

For Instant 250 watts PEP
operation on 160 through 10
metres just add 12 Volts DC
or 734 Volts AC.

The FT-101E's updated RF SPEECH PROCESSOR provides
that extra 'talk power' needed to cut through most of those bad
pile ups and heavy QRM. Only \$839

NEW! COMBINATION FREQUENCY COUNTER AND SIGNAL GENERATOR — OX 5550



Technical Data:
10Hz to 220MHz counter.
0.4 to 20 MHz generator.
600Hz tone oscillator.
2ms and 200ms gating time.
5 Digit LED display.
Switchable kHz and MHz.

Featuring a 220 MHz counter
upper limit and 30 MHz
generator upper limit.
Generator frequency is read
directly on the counter.

A MUST FOR EVERY
HAM SHACK.
\$213

OX 555 same as OX 5550
but with 30MHz counter.
Only \$175



FS-302 — \$58
50-170MHz

GFS — EXPERT SERVICE

MANY YEARS OF EXPERIENCE IN THE
AMATEUR RADIO AND COMMUNICATIONS
SERVICE INDUSTRY PROVIDES US WITH
THE BACKGROUND AND KNOWHOW TO
OFFER YOU THE BEST IN SERVICING AND
OUR \$9.50 PER HOUR SERVICE RATES ARE
VERY HARD TO BEAT. 50 WNY PAY MORE!

DON'T FORGET TO ENQUIRE ABOUT OUR FINANCE PLAN.



YP-150

EMOTATORS ROTATORS

MODEL 502CXX Heavy duty.
Rotation torque — 600 Kg/cm
Brake torque — 4000 Kg/cm

Only \$196.



MODEL 102MXX Extra Heavy Duty
Rotation torque — 800 Kg/cm
Brake torque — 16,000 Kg/cm

GFS Price only \$314

MODEL 103LBX Medium duty.
Rotation torque — 450 Kg/cm
Brake torque — 1500 Kg/cm
GFS Price only \$145

Freight and Insurance extra.

Prices include Sales Tax.
90 DAY LIMITED WARRANTY APPLIES TO ALL EQUIPMENT BUT DOES NOT COVER FINAL TUBES OR SEMI-CONDUCTORS.

PRICES AND SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE.

G.F.S. ELECTRONIC IMPORTS 15 McKEON ROAD, MITCHAM, 3132. (03) 873 3939

AMATEUR RADIO SPECIALISTS

KENWOOD, DRAKE, YAESU



DRAKE Model TR-4C
Sideband Transceiver



YAESU FT101E SSB Transceiver

USED TEST INSTRUMENTS

Level meters,
oscillators,
V.T.V.M., Morse
key, electronic
keyers, matching
networks, HF and
VHF antennas

WE ARE
KENWOOD
AMATEUR
RADIO
Distributors



KENWOOD TS 520S
SSB Transceiver



KENWOOD TS 700S
2m All mode Transceiver

CUSTOM COMMUNICATIONS

UNIT 10, KNIGHT PARK ESTATE,
2 DONALD ST., FAIRFIELD.

681 3544

AFTER HOURS 674 1719

OPEN
6 DAYS
Bankcard
Easy Finance